


Central
Semiconductor Corp.

**Central
Semiconductor Corp.**
**Central™
Semiconductor Corp.**

145 Adams Avenue
Hauppauge, New York 11788



2N4918
2N4919
2N4920

PNP Silicon Transistor
General Purpose Power

JEDEC TO-126 Case

DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N4918, 2N4919, and 2N4920 are Silicon PNP Epitaxial Base Power Transistors designed for Medium power amplifier and switching applications.

MAXIMUM RATINGS ($T_A=25^{\circ}\text{C}$ Unless otherwise noted)

		<u>2N4918</u>	<u>2N4919</u>	<u>2N4920</u>
Collector-Base Voltage	V_{CB0}	40V	60V	80V
Collector-Emitter Voltage	V_{CE0}	40V	60V	80V
Emitter-Base Voltage	V_{EB0}		5.0V	
Collector Current, Continuous	I_C		1.0A	
Collector Current, Peak	I_{CM}		3.0A	
Base Current	I_B		1.0A	
Power Dissipation ($T_C=25^{\circ}\text{C}$)	P_D		30W	
Operating & Storage Junction Temperature	T_J, T_{stg}		-65 to +150°C	
Thermal Resistance, Junction to Case	θ_{J-C}		3.12°C/W	

ELECTRICAL CHARACTERISTICS ($T_C=25^{\circ}\text{C}$)

<u>SYMBOL</u>	<u>TEST CONDITIONS</u>	<u>MIN</u>	<u>MAX</u>	<u>UNIT</u>
I_{CB0}	$V_{CB}=\text{Rated } V_{CB}$		100	μA
I_{CEV}	$V_{CE}=\text{Rated } V_{CE0}, V_{EB}=1.5\text{V}$		100	μA
I_{CE0}	$V_{CE}=0.5\text{X Rated } V_{CE0}$		500	μA
I_{EB0}	$V_{EB}=5.0\text{V}$		1.0	mA
BV_{CE0}	$I_C=0.1\text{A}$	40(2N4918)		V
		60(2N4919)		V
		80(2N4920)		V
$V_{CE(s)}$	$I_C=1.0\text{A}, I_B=0.1\text{A}$		0.6	V
$V_{BE(s)}$	$I_C=1.0\text{A}, I_B=0.1\text{A}$		1.3	V
$V_{BE(on)}$	$V_{CE}=1.0\text{V}, I_C=1.0\text{A}$		1.3	V
hFE	$V_{CE}=1.0\text{V}, I_C=50\text{mA}$	40		-
hFE	$V_{CE}=1.0\text{V}, I_C=500\text{mA}$	20	100	-
hFE	$V_{CE}=1.0\text{V}, I_C=1.0\text{A}$	10		-
fT	$V_{CE}=10\text{V}, I_C=250\text{mA}, f=1.0\text{MHz}$	3.0		MHz
C_{ob}	$V_{CB}=10\text{V}, f=100\text{kHz}$		100	pF





OUTSTANDING SUPPORT AND SUPERIOR SERVICES

PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centalsemi.com

Worldwide Field Representatives:
www.centalsemi.com/wwreps

Worldwide Distributors:
www.centalsemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centalsemi.com/terms

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Central Semiconductor manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NTE158](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE63](#) [C4460](#)
[2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SD2150T100R](#) [SP000011176](#) [FMMTA92QTA](#) [2N2369ADCSM](#)
[2N5769](#) [2SC2412KT146S](#) [2SC5490A-TL-H](#) [2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#)
[US6T6TR](#) [NJL0281DG](#) [732314D](#) [CMXT3906 TR](#) [CPH3121-TL-E](#) [CPH6021-TL-H](#) [873787E](#) [IMZ2AT108](#) [UMX21NTR](#) [MCH6102-TL-E](#)
[NJL0302DG](#) [2N3583](#) [2SA1434-TB-E](#) [2SC3143-4-TB-E](#) [2SD1621S-TD-E](#) [NTE103](#) [30A02MH-TL-E](#) [NSV40301MZ4T1G](#) [NTE101](#) [NTE13](#)
[NTE15](#) [NTE16001](#)