

CentralTM Semiconductor Corp.

145 Adams Avenue, Hauppauge, NY 11788 USA
Tel: (631) 435-1110 • Fax: (631) 435-1824

Manufacturers of World Class Discrete Semiconductors

TIP29
TIP29A
TIP29B
TIP29C

SILICON NPN POWER TRANSISTOR
1 AMP, 30 WATTS

JEDEC TO-220 CASE

DESCRIPTION

The CENTRAL SEMICONDUCTOR TIP29 Series is a NPN Epitaxial-Base Silicon Power Transistor designed for power amplifier and high-speed switching applications.

MAXIMUM RATINGS ($T_C=25^{\circ}\text{C}$ unless otherwise noted)

	<u>SYMBOL</u>	<u>TIP29</u>	<u>TIP29A</u>	<u>TIP29B</u>	<u>TIP29C</u>	<u>UNIT</u>
Collector-Base Voltage	V_{CB0}	40	60	80	100	V
Emitter-Base Voltage	V_{EB0}	5.0	5.0	5.0	5.0	V
Collector-Emitter Voltage	V_{CE0}	40	60	80	100	V
Collector Current, Continuous	I_C	1.0	1.0	1.0	1.0	A
Collector Current, Peak	I_{CM}	3.0	3.0	3.0	3.0	A
Base Current	I_B	0.4	0.4	0.4	0.4	A
Power Dissipation	P_D	30	30	30	30	W
Power Dissipation ($T_A=25^{\circ}\text{C}$)	P_D	2.0	2.0	2.0	2.0	W
Operating and Storage Junction Temperature	T_J, T_{stg}	-65 TO +150		-65 TO +150		$^{\circ}\text{C}$

ELECTRICAL CHARACTERISTICS ($T_C=25^{\circ}\text{C}$ unless otherwise noted)

<u>SYMBOL</u>	<u>TEST CONDITIONS</u>	<u>MIN</u>	<u>MAX</u>	<u>UNIT</u>
I_{CE0}	$V_{CE}=30\text{V}$ (TIP29, TIP29A)		0.3	mA
I_{CE0}	$V_{CE}=60\text{V}$ (TIP29B, TIP29C)		0.3	mA
I_{CES}	$V_{CE}=\text{Rated } V_{CE0}$		0.2	mA
I_{EB0}	$V_{EB}=5.0\text{V}$		1.0	mA
BV_{CE0}	$I_C=30\text{mA}$, (TIP29)	40		V
BV_{CE0}	$I_C=30\text{mA}$, (TIP29A)	60		V
BV_{CE0}	$I_C=30\text{mA}$, (TIP29B)	80		V
BV_{CE0}	$I_C=30\text{mA}$, (TIP29C)	100		V
$V_{CE(SAT)}$	$I_C=1.0\text{A}$, $I_B=125\text{mA}$		0.7	V
$V_{BE(on)}$	$V_{CE}=4.0\text{V}$, $I_C=1.0\text{A}$		1.3	V
h_{FE}	$V_{CE}=4.0\text{V}$, $I_C=0.2\text{A}$	40		-
h_{FE}	$V_{CE}=4.0\text{V}$, $I_C=1.0\text{A}$	15	75	-
h_{fe}	$V_{CE}=10\text{V}$, $I_C=0.2\text{A}$, $f=1\text{ kHz}$	20		-
f_T	$V_{CE}=10\text{V}$, $I_C=0.2\text{A}$, $f=1\text{ MHz}$	3		MHz
t_{on}	$I_C=1.0\text{A}$, $I_{B1}=I_{B2}=100\text{mA}$, $R_L=30\text{ OHMS}$	0.5 TYP		μS
t_{off}	$I_C=1.0\text{A}$, $I_{B1}=I_{B2}=100\text{mA}$, $R_L=30\text{ OHMS}$	2.0 TYP		μS



OUTSTANDING SUPPORT AND SUPERIOR SERVICES

PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centalsemi.com

Worldwide Field Representatives:
www.centalsemi.com/wwreps

Worldwide Distributors:
www.centalsemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centalsemi.com/terms

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Central Semiconductor manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NTE158](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE63](#) [C4460](#)
[2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SD2150T100R](#) [SP000011176](#) [FMMTA92QTA](#) [2N2369ADCSM](#)
[2N5769](#) [2SC2412KT146S](#) [2SC5490A-TL-H](#) [2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#)
[US6T6TR](#) [NJL0281DG](#) [732314D](#) [CMXT3906 TR](#) [CPH3121-TL-E](#) [CPH6021-TL-H](#) [873787E](#) [IMZ2AT108](#) [UMX21NTR](#) [MCH6102-TL-E](#)
[NJL0302DG](#) [2N3583](#) [2SA1434-TB-E](#) [2SC3143-4-TB-E](#) [2SD1621S-TD-E](#) [NTE103](#) [30A02MH-TL-E](#) [NSV40301MZ4T1G](#) [NTE101](#) [NTE13](#)
[NTE15](#) [NTE16001](#)