





FREQ (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
0.300	0.29	27.77
1.799	0.31	27.12
3.297	0.32	25.54
6.294	0.32	22.57
9.291	0.36	20.74
12.288	0.42	19.93
16.784	0.48	20.47
19.781	0.51	22.15
22.778	0.54	25.31
25.775	0.58	31.28
30.270	0.64	34.79
33.267	0.69	29.22
36.264	0.75	27.63
39.261	0.81	28.73
42.258	0.87	32.22
49.751	1.07	21.92
60.240	1.47	19.52
67.733	1.98	31.14
69.231	2.19	25.29
70.730	2.50	19.43
72.228	3.00	14.48
73.727	3.80	10.45
75.225	5.03	7.34
76.724	6.74	5.13
81.219	13.66	2.10
103.697	43.80	0.56
105.195	45.39	0.54
109.691	50.01	0.51
120.180	60.53	0.46
135.165	84.08	0.44
136.664	90.76	0.44
138.162	87.61	0.44
139.661	83.24	0.44
168.132	68.62	0.44
195.105	65.57	0.44
225.075	63.39	0.42
273.027	61.18	0.41
300.000	60.22	0.42

Product Control:

Crystek Part Number:	CLPFL-0070-BNC	Release Date:	25-Jul-2017
Revision Level:	D	Responsible:	K. Piotrowicz

Rev D
Page 3 of 3



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Signal Conditioning](#) category:

Click to view products by [Crystek](#) manufacturer:

Other Similar products are found below :

[MAPDCC0001](#) [MAPDCC0004](#) [PD0409J5050S2HF](#) [880157](#) [HHS-109-PIN](#) [DC1417J5005AHF](#) [AFS14A30-2185.00-T3](#) [AFS14A35-1591.50-T3](#) [DS-323-PIN](#) [B39321R801H210](#) [1A0220-3](#) [JP510S](#) [LFB212G45SG8C341](#) [LFB322G45SN1A504](#) [LFL182G45TC3B746](#) [SF2159E](#) [30057](#)
[FM-104-PIN](#) [CER0813B](#) [MAPDCC0005](#) [3A325](#) [40287](#) [41180](#) [ATB3225-75032NCT](#) [BD0810N50100AHF](#) [BD2425J50200AHF](#)
[C5060J5003AHF](#) [JHS-115-PIN](#) [JP503AS](#) [DC0710J5005AHF](#) [DC2327J5005AHF](#) [DC3338J5005AHF](#) [43020](#) [LFB2H2G60BB1C106](#)
[LFL15869MTC1B787](#) [X3C19F1-20S](#) [XC3500P-20S](#) [10013-20](#) [SF2194E](#) [CDBLB455KCAX39-B0](#) [TGL2208-SM, EVAL](#) [RF1353C](#)
[PD0922J5050D2HF](#) [1E1305-3](#) [1F1304-3S](#) [1G1304-30](#) [B0922J7575AHF](#) [2020-6622-20](#) [TP-103-PIN](#) [BD1222J50200AHF](#)