





FREQ (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
0.300	0.22	29.62
1.800	0.24	29.18
3.300	0.23	27.72
6.290	0.23	24.80
9.290	0.26	22.85
12.300	0.30	21.84
16.800	0.36	21.97
19.800	0.39	23.29
22.800	0.42	26.06
25.800	0.45	30.97
30.300	0.50	27.81
33.300	0.55	22.72
36.300	0.61	19.52
39.300	0.68	17.47
49.800	0.87	15.95
60.200	0.97	24.16
67.700	1.12	27.34
76.700	1.41	25.71
81.200	1.64	31.80
82.700	1.74	34.49
84.200	1.86	32.75
85.700	2.03	26.72
87.200	2.27	21.11
88.700	2.61	16.43
90.200	3.14	12.56
91.700	3.92	9.42
93.200	5.02	6.97
94.700	6.45	5.16
105.000	20.10	1.27
110.000	25.64	0.96
120.000	36.88	0.68
135.000	50.34	0.54
140.000	54.18	0.53
164.000	89.22	0.49
195.000	66.87	0.47
225.000	63.67	0.45
273.000	60.96	0.43
300.000	59.93	0.43

Product Control:

Crystek Part Number:	CLPFL-0090-BNC	Release Date:	25-Jul-2017
Revision Level:	D	Responsible:	K. Piotrowicz

Rev D
Page 3 of 3



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Signal Conditioning](#) category:

Click to view products by [Crystek](#) manufacturer:

Other Similar products are found below :

[MAPDCC0001](#) [MAPDCC0004](#) [PD0409J5050S2HF](#) [880157](#) [HHS-109-PIN](#) [DC1417J5005AHF](#) [AFS14A30-2185.00-T3](#) [AFS14A35-1591.50-T3](#) [DS-323-PIN](#) [B39321R801H210](#) [1A0220-3](#) [JP510S](#) [LFB212G45SG8C341](#) [LFB322G45SN1A504](#) [LFL182G45TC3B746](#) [SF2159E](#) [30057](#) [FM-104-PIN](#) [CER0813B](#) [MAPDCC0005](#) [3A325](#) [40287](#) [41180](#) [ATB3225-75032NCT](#) [BD0810N50100AHF](#) [BD2425J50200AHF](#) [C5060J5003AHF](#) [JHS-115-PIN](#) [JP503AS](#) [DC0710J5005AHF](#) [DC2327J5005AHF](#) [DC3338J5005AHF](#) [43020](#) [LFB2H2G60BB1C106](#) [LFL15869MTC1B787](#) [X3C19F1-20S](#) [XC3500P-20S](#) [10013-20](#) [SF2194E](#) [CDBLB455KCAX39-B0](#) [TGL2208-SM, EVAL](#) [RF1353C](#) [PD0922J5050D2HF](#) [1E1305-3](#) [1F1304-3S](#) [1G1304-30](#) [B0922J7575AHF](#) [2020-6622-20](#) [TP-103-PIN](#) [BD1222J50200AHF](#)