

# Miniature Incandescent Indicators

WITH LIGHT SHIELD LENS CAPS  
FOR MOUNTING IN 1/16" CLEARANCE HOLE  
FOR 2 TO 120V OPERATION



T-3 1/4  
MINIATURE  
BAYONET BASE

See lamp ratings  
on page K.

Recognized under the component  
program of Underwriters'  
Laboratories Inc.

75W., 125V.



## MATERIAL AND FINISHES

- **Mounting Bushing and Light Shield Cap:** Standard—brass polished chrome finish. Optional—black nickel or satin chrome finish.
- **Mounting Nut:** Brass, white nickel finish.
- **Internal-tooth Lockwasher:** Phosphor bronze, white nickel finish.
- **Terminals:** Solder — brass, hot tinned with elongated slot. Screw—brass, white nickel finish.



21-1310-2900-301

## PUSH-IN CAPS

solder terminal	screw terminal
<p>+ SIGN MARKED ON THE TERMINAL CONNECTED TO THE CENTER CONTACT</p>	<p>+ SIGN MARKED ON THE TERMINAL CONNECTED TO THE CENTER CONTACT</p>
21-0410-29-301	21-1310-29-301

21 SERIES  
22 SERIES  
89 SERIES  
90 SERIES

## BASE PART NUMBERS

CAP PART NUMBERS	COMPLETE ASSEMBLY PART NUMBERS
<p><b>PUSH-IN CAP with SNAP LOCK</b> 21-2900-300 one opening, 1/2" x 1/2"</p>	<p>21-0410-2900-301</p> <p>21-1310-2900-301</p>
<p><b>PUSH-IN CAP with SNAP LOCK</b> 22-2900-300 one opening, 3/32" x 1/2"</p>	<p>22-0410-2900-301</p> <p>22-1310-2900-301</p>
<p><b>PUSH-IN CAP with SNAP LOCK</b> 89-2900-300 one opening, 3/16" x 9/16"</p>	<p>89-0410-2900-301</p> <p>89-1310-2900-301</p>
<p><b>PUSH-IN CAP with SNAP LOCK</b> 90-2900-300 one opening, 3/16" x 1/2"</p>	<p>90-0410-2900-301</p> <p>90-1310-2900-301</p>

Part numbers shown in gray are normally  
in inventory at your Dialight Distributor.

Order complete with lamp to be assured of receiving the  
indicator light and correct lamp together for immediate use.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Lamp Holders & Accessories](#) category:*

*Click to view products by [Dialight](#) manufacturer:*

Other Similar products are found below :

[M81969/17-09](#) [D38999/20ZF11SA](#) [D38999/20ZF11SA-LC](#) [D38999/20ZJ35SA](#) [D38999/24ZF32BN](#) [D38999/24ZF35SN](#) [D38999/24ZF35SN-LC](#) [D38999/24ZG35SN-LC](#) [8101000002201](#) [811730-1](#) [983-0SE14-07S8](#) [DAK83S-20](#) [DTS20Z9-35SA](#) [MS18236-1YN](#) [DTS24Z21-11SN](#) [DTS24Z21-16AN](#) [DTS24Z21-16PN](#) [DTS24Z21-16PN-LC](#) [MS25041-8-327](#) [BACC63CN1404S8A](#) [BACC63CN1407S8A](#) [EN2997S01407F8](#) [EN2997SE01407F8](#) [169-0412-11-201](#) [PBMBN](#) [251-7538-15-504](#) [2802](#) [2802](#) [294502](#) [983-0S14-04S8](#) [983-0S14-07S8](#) [983-0S14-07S8-L](#) [983-0SE14-04S8](#) [162-8430-0932-502-327](#) [183-9730-14-602](#) [21-16](#) [251-8738-15-504](#) [259-1930-29-801](#) [3062](#) [350-0410-01-203](#) [367-8430-09-802](#) [367-8430-09-810](#) [371-8738-14-504](#) [D38999/20ZA35SA](#) [D38999/20ZG35SA](#) [D38999/24ZC35SA](#) [D38999/24ZF11SN-LC](#) [D38999/24ZF32SN-LC](#) [D38999/24ZG39SN-LC](#) [D38999/24ZG41PN-LC](#)