


521 SERIES INCANDESCENT LAMPS

T-3 1/4 MINIATURE BAYONET BASE

| PART NO. | LAMP NO. | VOLTS | AMPS | MSCD | LIFE HOURS |
|----------|----------|--------|------|------|------------|
| - | 49 | 2.0 | .06 | 0.04 | 1,000 |
| - | 45 | 3.2 | .35 | 0.50 | 3,000 |
| - | 47 | 6.3* | .15 | 0.50 | 3,000 |
| - | 1847 | 6.3* | .15 | 0.38 | 3,000 |
| - | 44 | 6.3* | .25 | 0.90 | 3,000 |
| - | 1866 | 6.3* | .25 | 0.65 | 20,000 |
| 521-0755 | 755 | 6.3* | .15 | 0.33 | 20,000 |
| - | 1891 | 14.0* | .24 | 2.0 | 500 |
| 521-1815 | 1815 | 14.0* | .20 | 1.4 | 3,000 |
| 521-0756 | 756 | 14.0* | .08 | 0.31 | 15,000 |
| - | 1819 | 28.0* | .04 | 0.34 | 2,500 |
| - | 1829 | 28.0* | .07 | 1.0 | 1,000 |
| - | 1820 | 28.0* | .10 | 1.6 | 1,000 |
| 521-0313 | 313 | 28.0* | .17 | 3.5 | 500 |
| 521-0757 | 757 | 28.0* | .08 | 0.62 | 7,500 |
| - | 1828 | 37.5 | .05 | 0.65 | 3,000 |
| 521-1835 | 1835 | 55.0 | .05 | 1.1 | 5,000 |
| 521-9109 | 120MB | 120.0* | .025 | 0.36 | 10,000 |



T-3 1/4 MINIATURE BAYONET BASE INCANDESCENT LAMP

* Also available in T-3 1/4 multichip and T 3 1/4 cluster Based LED versions. See pages 39 and 40 for information.

Note: 120 volt version only available in T-3 1/4 cluster version. See page 40 for information.

S-6 DOUBLE CONTACT BAYONET BASE

| PART NO. | LAMP NO. | VOLTS | AMPS | LIFE HOURS |
|----------|-------------|-------|-------|------------|
| - | 6S6DC-24V | 24 | 0.025 | 3,000 |
| - | 6S6DC-30V | 30 | 0.2 | 3,500 |
| - | 6S6DC-48V | 48 | 0.125 | 3,500 |
| 521-9080 | 6S6DC-75V | 75 | 0.08 | 3,000 |
| 521-9081 | 6S6DC-125V | 125 | 0.05 | 4,000 |
| - | 6S6DC-135V | 135 | 0.05 | 3,000 |
| - | 6S6DC-145V | 145 | 0.04 | 3,800 |
| - | 10S6DC-230V | 230 | 0.04 | 3,000 |
| 521-9096 | 10S6DC-250V | 250 | 0.04 | 3,000 |



S-6 DOUBLE CONTACT BAYONET BASE INCANDESCENT LAMP

S-6 CANDELABRA SCREW BASE

| PART NO. | LAMP NO. | VOLTS | AMPS | LIFE HOURS |
|----------|-----------|-------|-------|------------|
| 521-9062 | 6S6-6V | 6 | 1.0 | 3,000 |
| 521-9063 | 6S6-12V | 12 | 0.5 | 3,000 |
| 521-9064 | 6S6-24V | 24 | 0.25 | 3,000 |
| - | 6S6-30V | 30 | 0.2 | 3,500 |
| - | 6S6-48V | 48 | 0.125 | 3,500 |
| - | 6S6-75V | 75 | 0.08 | 3,000 |
| 521-9068 | 6S6-125V | 125 | 0.05 | 4,000 |
| 521-9072 | 6S6-135V | 135 | 0.05 | 3,000 |
| - | 6S6-145V | 145 | 0.04 | 3,800 |
| - | 10S6-230V | 230 | 0.04 | 3,000 |



S-6 CANDELABRA SCREW BASE INCANDESCENT LAMP

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Lamps](#) category:

Click to view products by [Dialight](#) manufacturer:

Other Similar products are found below :

[5AB](#) [6180](#) [8111](#) [8623](#) [912](#) [120PS](#) [1224](#) [DE603](#) [DW50](#) [IFL-LX2162-16T](#) [C9A](#) [C9A](#) [3015](#) [303](#) [19](#) [PR13](#) [268](#) [GT-NE6H1225T](#)
[CM5004WW](#) [32-2211T](#) [509K](#) [5314N1](#) [5314N2](#) [WWT1-EW10/GRN](#) [4925H1](#) [DW07](#) [1141](#) [MS25231-313](#) [E73](#) [CM2](#) [7683EBP](#) [8553](#)
[XE135B](#) [WWT2-EW34BLA](#) [6S6/30V](#) [7367](#) [1301910036](#) [7A1H](#) [8630FBBB](#) [WT3F-20](#) [85](#) [106](#) [105](#) [BGF717-UV1](#) [1974D](#) [1495](#) [400](#) [502](#)
[67](#) [PR12](#)