

1/4" Dia. x 5/8" to 1" length ferrule fuses

**AGA-V (axial leads)**

**AGA**

**Specifications**  
**Description:** Fast-acting fuse.

**Dimensions:**  
1/4" x 5/8"  
(6.4 x 15.9mm).

**Construction:**  
Glass tube.

**Ratings:**

Volts — 125Vac (or less)

Amps — 1/6-30A

IR — 10,000 (1/6-1 1/2A @ 125Vac)

— 200A (2-5A @ 125Vac)

— 1000A (6-30A @ 32Vac)

**Agency Information:** CE, Std. 248-14, UL File E19180, UL Listed, Guide JDYX 0-1 1/2A UL Recognized, Guide JDYX2 2-12A.

**Features and Benefits**

- Fast-acting for maximum protection.
- Size rejects insertion of other fuse types.

**Typical Applications**

- Electronic Circuits

**Catalog Numbers (Amps)**  
**With Axial Leads\***

|            |             |             |
|------------|-------------|-------------|
| AGA-V-1/6  | AGA-V-1     | AGA-V-7 1/2 |
| AGA-V-1/10 | AGA-V-1 1/2 | AGA-V-10    |
| AGA-V-1/6  | AGA-V-2     | AGA-V-15    |
| AGA-V-1/4  | AGA-V-2 1/2 | AGA-V-20    |
| AGA-V-3/6  | AGA-V-3     | AGA-V-25    |
| AGA-V-1/2  | AGA-V-5     | AGA-V-30    |
| AGA-V-5/10 | AGA-V-6     |             |
| AGA-V-3/4  | AGA-V-7     |             |

**Without Axial Leads**

|          |           |           |
|----------|-----------|-----------|
| AGA-1/6  | AGA-1     | AGA-7 1/2 |
| AGA-1/10 | AGA-1 1/2 | AGA-10    |
| AGA-1/6  | AGA-2     | AGA-15    |
| AGA-1/4  | AGA-2 1/2 | AGA-20    |
| AGA-3/6  | AGA-3     | AGA-25    |
| AGA-1/2  | AGA-5     | AGA-30    |
| AGA-5/10 | AGA-6     |           |
| AGA-3/4  | AGA-7     |           |

\*AGA-V is UL Listed 0-5A, UL Recognized 6-12A.



**AGW**

**Specifications**

**Description:** Fast-acting fuse.

**Dimensions:** 1/4" x 7/8"  
(6.4 x 22.2mm).

**Construction:** Glass tube.

**Ratings:**

Volts — 32Vac

Amps — 1-30A

IR — 100A

**Features and Benefits**

- Fast-acting for maximum protection.
- Size rejects insertion of other fuse types.

**Typical Applications**

- Electronic Circuits

**Catalog Numbers (Amps)**

|           |           |        |
|-----------|-----------|--------|
| AGW-1     | AGW-4     | AGW-15 |
| AGW-1 1/2 | AGW-5     | AGW-20 |
| AGW-2     | AGW-6     | AGW-25 |
| AGW-2 1/2 | AGW-7 1/2 | AGW-30 |
| AGW-3     | AGW-10    |        |



**AGX-V (axial leads)**

**AGX**

**Specifications**  
**Description:** Fast-acting fuse.

**Dimensions:** 1/4" x 1"  
(6.4 x 25.4mm).

**Construction:** Glass tube.

**Ratings:**

Volts — 250Vac (1/600-2A)

— 125Vac (2 1/2-7A)

— 32V (8-30A)

Amps — 1/600-30A

IR — 35A (1/600-2A @ 250Vac)

— 10,000A (2 1/2-7A @ 125Vac)

— 1000A (8-30A @ 32V)

**Agency Information:** CE, Std. 248-14, UL File E19180 UL Listed, Guide JDYX, 0-5A UL Recognized, Guide JDYX2, 6-20A CSA File 47233; Class 1422-01, 0-5A.

**Features and Benefits**

- Size rejects insertion of other fuse types.

**Typical Applications**

- Electronic Circuits

**Catalog Numbers (Amps)**  
**With Axial Leads\*\***

|             |             |          |
|-------------|-------------|----------|
| AGX-V-1/600 | AGX-V-3/6   | AGX-V-5  |
| AGX-V-1/200 | AGX-V-4/10  | AGX-V-6  |
| AGX-V-1/100 | AGX-V-1/2   | AGX-V-7  |
| AGX-V-1/2   | AGX-V-3/4   | AGX-V-8  |
| AGX-V-1/6   | AGX-V-1     | AGX-V-10 |
| AGX-V-1/10  | AGX-V-1 1/2 | AGX-V-15 |
| AGX-V-1/6   | AGX-V-1 1/2 | AGX-V-20 |
| AGX-V-3/6   | AGX-V-2     | AGX-V-25 |
| AGX-V-2/10  | AGX-V-2 1/2 | AGX-V-30 |
| AGX-V-1/4   | AGX-V-3     |          |
| AGX-V-3/10  | AGX-V-4     |          |

**Without Axial Leads**

|           |           |        |
|-----------|-----------|--------|
| AGX-1/600 | AGX-3/6   | AGX-5  |
| AGX-1/200 | AGX-4/10  | AGX-6  |
| AGX-1/100 | AGX-1/2   | AGX-7  |
| AGX-1/2   | AGX-3/4   | AGX-8  |
| AGX-1/6   | AGX-1     | AGX-10 |
| AGX-1/10  | AGX-1 1/2 | AGX-15 |
| AGX-1/6   | AGX-1 1/2 | AGX-20 |
| AGX-3/6   | AGX-2     | AGX-25 |
| AGX-2/10  | AGX-2 1/2 | AGX-30 |
| AGX-1/4   | AGX-3     |        |
| AGX-3/10  | AGX-4     |        |

\*\*AGX-V is UL Recognized from 6-20A @ 32Vac



Electronic  
Fuses

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Cartridge Fuses](#) category:*

*Click to view products by [Eaton](#) manufacturer:*

Other Similar products are found below :

[MBO-20](#) [MDA-V-1/100](#) [12C10X38GI](#) [AGA-V-2-1/2](#) [AGC-V-3-12-R](#) [AGY-50](#) [MSL-3](#) [MSL-4](#) [MSL-5](#) [BK1/C436-2A](#) [BK1-GMA-1-6-R](#)  
[BK1-GMA-200-R](#) [BK1GMA-6-R](#) [BK1/GMC-100-R](#) [BK1/GMC-1.5-R](#) [BK1-GMC-2-5-R](#) [BK1GMD-4-R](#) [BK1S500-250-R](#) [BK1S500-32-R](#)  
[BK1-S500-4-R](#) [BK1S500-5-R](#) [BK1-S505-1-R](#) [BK1-S506-2-R](#) [BK1-S506-3-15-R](#) [BK1/S506-63-R](#) [BK/ABC-5RX](#) [BK/AGW-B-4](#) [BK/AVX-](#)  
[1/4](#) [BK/C515S-250-R](#) [BK/MBO-20](#) [BK/MBO-8](#) [BK/MDM-3/4](#) [BK-MDQ-4](#) [BK/S505-V-2.5A](#) [BK/TDC120-15](#) [BK/TDC120-20](#)  
[BK/TDC122-45](#) [BP/MDL-7](#) [1C10X38AM](#) [S505-V-500MA](#) [SEF-1697-1-002](#) [AGA-V-7-1/2](#) [AGC-15WX](#) [AGC-2-1-2-R](#) [20.0M6.3X32F](#)  
[20C8X32GI](#) [GMC-50-R](#) [361.250](#) [MBO-8](#) [TDC121-30](#)