

Pin indication Fuses

Low Voltage
Supplementary
Fuses

GBA

GLD

Specifications

Class: Supplemental

Description: Fast-acting, pin indication fuse.

Dimensions: 1/4" x 1 1/4"
(6.6 x 31.7mm) 3AG.

Construction: Fiber tube

Ratings:

Volts — See Agency Info below

Amps — 1/2-15A

IR — See Agency Info below

Agency Information: CE, Std. 248-14, UL Listed, 0-5A/125Vac, 10,000 AIC, Guide JDYX, File E19180, UL Recognized, 6A/125Vac, 1000AIC 8-15A/50Vac/dc, 300 AIC Guide JDYX2, File E19180, CSA Certified: 0-5A/125Vac, 10,000 AIC Class 1422-01, File 53787.

Features and Benefits

- Type GBA has a "red" pin indicator providing visual identification of failed circuits, resulting in faster troubleshooting (reduced circuit downtime).
- Type GLD has an plated pin to activate transmitting an electrical signal to indicate the location of opened circuits, resulting in reduced downtime.

Typical Applications

- Control Circuits
- Electronic Circuits

GLD Catalog Numbers (Amps)

GLD-1/2	GLD-2	GLD-6
GLD-3/4	GLD-3	GLD-10
GLD-1	GLD-4	GLD-12
GLD-1 1/2	GLD-5	GLD-15

GBA Catalog Numbers (Amps)

GBA-1/2	GBA-2	GBA-8
GBA-3/4	GBA-3	GBA-10
GBA-1	GBA-4	GBA-15
GBA-1 1/2	GBA-5	

Recommended fuse blocks/fuse holders for 1/4" x 1 1/4" indicating fuses

- Page 41

Data Sheet: 2012



MIC & MIN

Specifications

Class: Supplemental

Description: Fast-acting, pin indication fuse.

Dimensions: 1 3/32" x 1 1/2" (10.3 x 38.1mm) 5AG.

Construction:

Fiber tube

Ratings:

Volts — 250Vac (1-15A)

— 32V (20-30A)

Amps — 1-30A

IR — 35A (1A @250Vac)

— 100A (2-3A @250Vac)

— 200A (5-10A @250Vac)

— 750A (15A @250Vac)

— 10,000A (20-30A @32V)

— 35A (1A @250Vac)

Agency Information: CE, Std. 248-14, MIC—0-15A UL Listed, Guide JDYX, File E19180, MIN—1-5A CSA Certified, Class 1422-01, File 53787.

Features and Benefits

- Type MIN has a "red" pin indicator providing visual identification of failed circuits, resulting in faster trouble shooting (reduced circuit downtime).
- Type MIC has silver-plated pin transmitting an electrical signal indicating location of a failed circuit, resulting in faster troubleshooting (reduced circuit downtime).

Typical Applications

- Control Circuits
- PLC Circuits
- Electronic Circuits

MIC Catalog Numbers (Amps)

MIC-1	MIC-5	MIC-20
MIC-2	MIC-10	MIC-25
MIC-3	MIC-15	MIC-30

MIC - (1-15)UL Listed 125Vac / IR = 10kA

MIN Catalog Numbers (Amps)

MIN-1	MIN-5	MIN-20
MIN-2	MIN-10	MIN-25N

Recommended signal block for 1 3/32" x 1 1/2" indicating fuses

- Page 41

Data Sheet: 2047



FNA

Specifications

Class: Supplemental

Description: Time-delay, pin indication fuse.

Dimensions: 1 3/32" x 1 1/2"
(10.3 x 38.1mm).

Construction: Fiber tube

Ratings:

Volts — 250Vac (1/10-3/10A)

— 125Vac (1-15A)

— 32V (20-30A)

Amps — 1/10-30A

IR — 35A (1/10-3/10A @ 250Vac)

— 10,000A (1/10-15A @ 125Vac)

— 1000A (20-30A @ 32V)

Agency Information: CE, Std. 248-14, UL Listed 1/10-3/10A, IR 35A@ 250V, IR 10kA@ 125V, Guide JDYX, File 19180, CSA Certified, 0-3/10A/250V, 1-10A/125V, Class 1422-01, File 53787.

Features and Benefits

- FNA has a pin indicator providing visual identification of failed circuits, resulting in reduced circuit downtime.
- Time-delay response allows close sizing on control transformers and relays

Typical Applications

- Control Circuits
- Electronic Circuits

Catalog Numbers (Amps)

FNA-1/10	FNA-3/10	FNA-2 1/2	FNA-6 1/4
FNA-1/8	FNA-1	FNA-2 3/10	FNA-7
FNA-15/100	FNA-1 1/8	FNA-3	FNA-8
FNA-3/10	FNA-1 1/4	FNA-3 3/10	FNA-9
FNA-1/4	FNA-1 1/10	FNA-3 1/2	FNA-10
FNA-3/10	FNA-1 1/2	FNA-4	FNA-12*
FNA-1/10	FNA-1 3/10	FNA-4 1/2	FNA-15*
FNA-1/2	FNA-1 9/10	FNA-5	FNA-20*
FNA-3/10	FNA-2	FNA-5 1/10	FNA-25*
FNA-3/4	FNA-2 1/4	FNA-6	FNA-30

*12-30A versions are dual-tube construction

Recommended signal block for 1 3/32" x 1 1/2" indicating fuses

- Page 41

Data Sheet: 2029



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Industrial & Electrical Fuses](#) category:

Click to view products by [Eaton](#) manufacturer:

Other Similar products are found below :

[MTH-4](#) [MTH-8](#) [BP/NON-30](#) [NLN2](#) [NLN25](#) [KTN-R-10](#) [LPS-RK-2SP](#) [ABU-35](#) [FLSR100](#) [BLF6](#) [KLK003](#) [LPS-RK-100](#) [LPS-RK-15](#) [LPS-RK-20](#) [LPS-RK-70](#) [LPS-RK-90](#) [NLS10](#) [FRN-R-30ID](#) [FRS-R-20ID](#) [KLK015](#) [CHSF-80](#) [LDFJ350.X](#) [FUSE](#) [5A/32V](#) [FK-1](#) [381280](#) [384515](#) [381050](#) [491335](#) [492138](#) [004184220](#) [004184223](#) [004184228](#) [004185224](#) [004181214](#) [3050611.0,5](#) [432001](#) [BAF-4](#) [FRN-R-600](#) [MIC-20](#) [BBS-4/10](#) [BBS-3/4](#) [BBS-1/2](#) [C10G32](#) [C10M20](#) [JJN-100](#) [JJN-15](#) [JJN-60L](#) [KRP-C-700SP](#) [KTK-R-1-1/2](#) [3RU1136-1KB0](#) [LP-CC-12](#)