

Pin indication Fuses

GBA

GLD

Specifications

Class: Supplemental

Description: Fast-acting, pin indication fuse.

Dimensions: 1/4" x 1 1/4"
(6.6 x 31.7mm) 3AG.

Construction: Fiber tube

Ratings:

Volts — See Agency Info below

Amps — 1/2-15A

IR — See Agency Info below

Agency Information: CE, Std. 248-14, UL Listed, 0-5A/125Vac, 10,000 AIC, Guide JDYX, File E19180, UL Recognized, 6A/125Vac, 1000AIC 8-15A/50Vac/dc, 300 AIC Guide JDYX2, File E19180, CSA Certified: 0-5A/125Vac, 10,000 AIC Class 1422-01, File 53787.

Features and Benefits

- Type GBA has a "red" pin indicator providing visual identification of failed circuits, resulting in faster troubleshooting (reduced circuit downtime).
- Type GLD has an plated pin to activate transmitting an electrical signal to indicate the location of opened circuits, resulting in reduced downtime.

Typical Applications

- Control Circuits
- Electronic Circuits

GLD Catalog Numbers (Amps)

GLD-1/2	GLD-2	GLD-6
GLD-3/4	GLD-3	GLD-10
GLD-1	GLD-4	GLD-12
GLD-1 1/2	GLD-5	GLD-15

GBA Catalog Numbers (Amps)

GBA-1/2	GBA-2	GBA-8
GBA-3/4	GBA-3	GBA-10
GBA-1	GBA-4	GBA-15
GBA-1 1/2	GBA-5	

Recommended fuse blocks/fuse holders for 1/4" x 1 1/4" indicating fuses

- Page 41

Data Sheet: 2012



MIC & MIN

Specifications

Class: Supplemental

Description: Fast-acting, pin indication fuse.

Dimensions: 1 3/32" x 1 1/2" (10.3 x 38.1mm) 5AG.

Construction:

Fiber tube

Ratings:

Volts — 250Vac (1-15A)

— 32V (20-30A)

Amps — 1-30A

IR — 35A (1A @250Vac)

— 100A (2-3A @250Vac)

— 200A (5-10A @250Vac)

— 750A (15A @250Vac)

— 10,000A (20-30A @32V)

— 35A (1A @250Vac)

Agency Information: CE, Std. 248-14, MIC—0-15A UL Listed, Guide JDYX, File E19180, MIN—1-5A CSA Certified, Class 1422-01, File 53787.

Features and Benefits

- Type MIN has a "red" pin indicator providing visual identification of failed circuits, resulting in faster trouble shooting (reduced circuit downtime).
- Type MIC has silver-plated pin transmitting an electrical signal indicating location of a failed circuit, resulting in faster troubleshooting (reduced circuit downtime).

Typical Applications

- Control Circuits
- PLC Circuits
- Electronic Circuits

MIC Catalog Numbers (Amps)

MIC-1	MIC-5	MIC-20
MIC-2	MIC-10	MIC-25
MIC-3	MIC-15	MIC-30

MIC - (1-15)UL Listed 125Vac / IR = 10kA

MIN Catalog Numbers (Amps)

MIN-1	MIN-5	MIN-20
MIN-2	MIN-10	MIN-25N

Recommended signal block for 1 3/32" x 1 1/2" indicating fuses

- Page 41

Data Sheet: 2047



FNA

Specifications

Class: Supplemental

Description: Time-delay, pin indication fuse.

Dimensions: 1 3/32" x 1 1/2"
(10.3 x 38.1mm).

Construction: Fiber tube

Ratings:

Volts — 250Vac (1/10-3/10A)

— 125Vac (1-15A)

— 32V (20-30A)

Amps — 1/10-30A

IR — 35A (1/10-3/10A @ 250Vac)

— 10,000A (1/10-15A @ 125Vac)

— 1000A (20-30A @ 32V)

Agency Information: CE, Std. 248-14, UL Listed 1/10-3/10A, IR 35A@ 250V, IR 10kA@ 125V, Guide JDYX, File 19180, CSA Certified, 0-3/10A/250V, 1-10A/125V, Class 1422-01, File 53787.

Features and Benefits

- FNA has a pin indicator providing visual identification of failed circuits, resulting in reduced circuit downtime.
- Time-delay response allows close sizing on control transformers and relays

Typical Applications

- Control Circuits
- Electronic Circuits

Catalog Numbers (Amps)

FNA-1/10	FNA-3/10	FNA-2 1/2	FNA-6 1/4
FNA-1/8	FNA-1	FNA-2 3/10	FNA-7
FNA-15/100	FNA-1 1/8	FNA-3	FNA-8
FNA-3/10	FNA-1 1/4	FNA-3 3/10	FNA-9
FNA-1/4	FNA-1 1/10	FNA-3 1/2	FNA-10
FNA-3/10	FNA-1 1/2	FNA-4	FNA-12*
FNA-1/10	FNA-1 3/10	FNA-4 1/2	FNA-15*
FNA-1/2	FNA-1 9/10	FNA-5	FNA-20*
FNA-3/10	FNA-2	FNA-5 1/10	FNA-25*
FNA-3/4	FNA-2 1/4	FNA-6	FNA-30

*12-30A versions are dual-tube construction

Recommended signal block for 1 3/32" x 1 1/2" indicating fuses

- Page 41

Data Sheet: 2029



Low Voltage
Supplementary
Fuses

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Eaton manufacturer:](#)

Other Similar products are found below :

[BK1-S506-500-R](#) [BK1-S506-6-3-R](#) [BK-MDL-3-R](#) [BK1-S506-2-R](#) [MPI4040R4-1R5-R](#) [BK/ABC-1](#) [BK/MDA-15](#) [GMA-5A](#) [GMA250MA](#)
[TDC600-10A](#) [89096-015](#) [8946K153](#) [8961K155](#) [M22-D-R-GB0/K11](#) [M22-L-R/R](#) [6422](#) [6580](#) [CTX20-16-52LP-R](#) [CWL530FI](#)
[CXM/CO/GP/R/BB](#) [6HD36](#) [714125](#) [MBO-2](#) [7314K36](#) [7321K2](#) [F02A-1-1/2A](#) [F02A-1-1/2AS](#) [F02A-1AS](#) [F02A-2AS](#) [F02A-3/4A](#)
[F03A250V12A](#) [F03B125V4A](#) [MCR-4](#) [MDA-2-8/10-R](#) [MDA-30A](#) [MDA-V-1/16](#) [F60C500V10AS](#) [F60C500V15AS](#) [7563K84](#) [7634K36](#)
[MDQ-3/16](#) [MDQ-7/10](#) [MDQ-V-1/10](#) [MDQ-V-1-1/4](#) [MDQ-V-1/16](#) [MDQ-V-1/2](#) [MDQ-V-1/4](#) [MDQ-V-3/16](#) [MDQ-V-3/8](#) [MDQ-V-6/10](#)