



**SPECIFICATIONS WITH CIRCUIT**

MODEL	DMT-1606S-NL	DMT-1612S-NL
RATED VOLTAGE (V)	6	12
OPERATING VOLTAGE (V)	4~7	6~18
CURRENT (mA)	30 MAX.	
SOUND OUTPUT AT 10CM (dB)	85 MIN.	
RESONANT FREQUENCY(HZ)	2300 <span style="color:red">△</span>	
OPERATING TEMPERATURE (°C)	-20~+70	
WEIGHT (g)	7	

NOTE:  
ALL DIMS ARE GIVEN IN MM.

PROJECTION

RDI, Inc. 400 Columbus Avenue Valhalla, NY 10595

Research Develop Innovate

SCALE	NONE
TITLE	AUDIO ALERT W/OSCILLATING CIRCUIT-ROHS COMPLIANT
TOLERANCE	EXCEPT AS NOTED
DR. DATE	JOEY 11/05/02
REF.	P/N: DMT-16S SERIES-NL

DEC. INCHES	N/A
CK.	SL
PRE-	BZ
DRAWING NO.	0961
SIZE	A
REV.	C

ECON#	DATE	SYM	REVISION RECORD	AUTH	BY	ANG.
08-203	06/03/08	C	CHANGED P/N TO DMT-16S SERIES-NL&REVISED 6.6mm TO 6.0mm& REVISED 2200HZ TO 2300HZ&REVISED THE TITLE	BM	JY	±0.5
07-150	03/16/07	B	CHANGED THE PART TO ROHS COMPLIANT	GM	JY	±1.
03-396	5/27/03	A	ADDED DMT-1612, DMT-1606-S AND DMT-1612-S, P/N DMT-16 SERIES WAS DMT-1606	BM	SL	±1.
ECON#	DATE	SYM	REVISION RECORD	AUTH	BY	ANG.

THIS DOCUMENT IS OWNED BY, AND THE INFORMATION CONTAINED IN IT IS PROPRIETARY TO, RDI. BY RECEIPT HEREOF THE HOLDER AGREES NOT TO USE THE INFORMATION AND NOT TO DISCLOSE IT TO ANY THIRD PARTY, NOR REPRODUCE THIS DOCUMENT WITHOUT THE WRITTEN CONSENT OF RDI, AND AGREES TO RETURN THIS DOCUMENT FORTHWITH UPON REQUEST.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Piezo Buzzers & Audio Indicators](#) category:*

*Click to view products by [Electronics manufacturer](#):*

Other Similar products are found below :

[PFD-21A29W](#) [PLD-21N30W](#) [REM-6027F-1.5](#) [RH1020C-010-NFP-G-NL](#) [PFD-27N36W](#) [KBS-20DA-7AS](#) [KBS-27DA-5C-105](#)  
[RFS5015382PNL](#) [MSR516NP](#) [DMT-1606S-NL](#) [OMT112](#) [SCE016SD3CM4B](#) [DMT-09-1-4B-NL](#) [HBO0302C-58/1248](#) [AT-3045-TF-LW110-R](#) [SMA-17-S](#) [BMS3650L-LF](#) [SMT-0540-T-7-R](#) [SMT-0540-T-2-R](#) [AT-0927-TT-2-R](#) [AT-2310-T-LW100-R](#) [SMI-1324-TW-5V-4-R-T/R](#)  
[SMI-1324-TW-5V-2-R-T/R](#) [SC0715BL](#) [AI-1027-TWT-5V-R](#) [SC235AF](#) [SMT-0827-TW-5V-R](#) [AT-2830-TWT-R](#) [AT-1220-TT-5-R](#) [AT-1220-TT-10-R](#) [AT-1127-ST-2-R](#) [AT-1220-TWT-5V-R](#) [AT-1750-TFL-LW95-R](#) [SMT-1427-S-R](#) [SMT-1127-S-R](#) [AI-3245-TF-LW95-R](#) [AI-2438-TT-R](#) [AB2040B](#) [SMT-1324-TW-5V-R](#) [AT-2429-TWT-R](#) [AI-1223-TWT-12V-3-R](#) [AI-1440-TWT-24V-2-R](#) [AB4113B](#) [AI-2304-TF-LW120-12V-R](#) [AI-4329-P-SP28-R](#) [XL-5020-TF-LW150-S-R](#) [SMA-30-P17.5](#) [AI-5025-TWT-R](#) [X-5735-LW350-S-2-R](#) [AW-10PR](#)