

MA160 True RMS 200A AC/DC Open Jaw Clamp Meter



Open jaw design provides quick current measurements in tight locations without breaking the circuit. True RMS provides accurate readings on noisy, distorted or non-sinusoidal waveforms. Convenient built-in Non-Contact Voltage (NCV) Detector allows quick detection of live voltages while the LED backlight, with two level brightness, and flashlight help take measurements in dimly lit environment.



Features

- 0.57" (14.5mm) open jaw size allows current measurements in tight spaces
- Built-in Non-Contact Voltage (NCV) detector with audible alert and LED indicator
- Relative Mode for Capacitance Zero and offset adjustment
- 2000 count 2-level backlit LCD display
- Convenient LED worklight for viewing in dimly lit area
- Continuity and Diode Test
- Auto Power Off with disable
- Ergomic housing with built-in test lead holders
- CAT III-600V rating
- Complete with test leads, two AA batteries, and pouch

Specifications	Range	Basic Accuracy
AC/DC Current	200A (0.1A)	±(2.5%+5d)
AC Voltage	750V (1mV)	±(2.5%+3d)
DC Voltage	1000V (1mV)	±(0.8%+3d)
Non-Contact Voltage (NCV)	100 to 750V	
Resistance	60MΩ (0.1Ω)	±(1.0%+2d)
Capacitance	60mF (0.01nF)	±(4.0%+20d)
Continuity /Diode Test	Yes	
Dimensions	8.3x2.1x1.4" (210x53x35mm)	
Weight	5.8oz (164g)	

Ordering

MA160 200A True RMS AC/DC Open Jaw Clamp Meter



UPC Code: 793950316016

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)