

MA260 CAT IV True RMS 200A AC Open Jaw Clamp Meter



Easy-to-use, one button, Auto Sense technology allows meter to recognize the input being measured and will automatically switch to the correct mode of operation. Its convenient Open Jaw design provides quick measurements in tight locations. True RMS provides accurate readings.



Features

- Smart Auto Sensing technology enables the meter to recognize the input and automatically switch to the correct mode of operation
- For AC Voltage, Auto Sense feature evaluates input signal and adjusts Input Impedance to eliminate effects of ghost voltages
- 0.6" (16mm) open jaw size
- True RMS for accurate readings of noisy, distorted or non-sinusoidal waveforms
- Built-in non-contact voltage detector with LED indicator
- 10,000 count backlit LCD display
- Smart Data Hold freezes the reading on the display and automatically changes if a new reading is larger than 50 counts
- Auto Power Off with disable
- Battery capacity (%) displayed on power-up
- Slim housing construction with built-in test lead holders
- Complete with test leads and two AAA batteries

| Specifications | Range | Max Resolution | Basic Accuracy |
|---------------------------|--|----------------|----------------|
| AC Current | 200A | 0.1A | ±3.0% |
| AC Voltage | 1.3V to 1000V | 0.1V | ±0.9% |
| DC Voltage | 2.1V to 1000V | 0.1V | ±0.3% |
| Non-contact Voltage (NCV) | 80 to 1000V AC (50 to 60Hz) | | |
| Resistance (Ω) | 0 to 10k Ω | 1 Ω | ±0.9% |
| Input Impedance | 6k Ω up to 30V; Increases to 420k Ω at 1000V | | |
| Diode | 0.4 to 0.8V | 0.1V | ±1.0% |
| Continuity | Beeper (25 Ω threshold) | | |
| Dimensions | 7.6 x 2.1 x 1.2" (193 x 54 x 31mm) | | |
| Weight | 9.9oz (280g) | | |

Ordering

MA260 CAT IV True RMS 200A AC Open Jaw Clamp Meter



UPC Code: 793950382622

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#)
[CIE600](#) [TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374](#)
[FC](#) [TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [MA610](#) [EA30-](#)
[NIST](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#) [DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#)