


MF100 AC/DC Magnetic Field Meter



Measuring AC Magnetic Field output from sprinkler relay system

Extech's MF100 measures both AC and DC Magnetic Field in Gauss and mT (milli Tesla) with a uniaxial Hall effect sensor and built-in ATC (Automatic Temperature Compensation). It also conveniently indicates North or South Pole on the display.

Applications:

- Electric transmission equipment
- Power line
- Microwave oven
- Air conditioner
- Refrigerator
- Computer monitor
- Video/audio device
- Particle accelerators
- MRI
- Industrial & research labs
- Transportation Systems
- Elevators
- Battery Power
- Wind Power



Features

- Utilizes Hall effect sensor with ATC (Automatic Temperature Compensation)
- N pole/S pole indicator
- Zero button for DC measurement
- Data Hold and Min/Max
- Auto power off with disable
- Complete with uniaxial magnetic probe sensor and protective cover, 9V battery, and hard carrying case

Specifications	Range	Max Resolution	Basic Accuracy
DC milli Tesla	300.00mT	0.01mT	±(5% + 10d)
	3000.0mT	0.1mT	±(5% + 10d)
DC Gauss	3000.0G	0.1G	±(5% + 10d)
	30,000G	1G	±(5% + 10d)
AC milli Tesla	150.00mT	0.01mT	±(5% + 20d)
	1500.0mT	0.1mT	±(5% + 20d)
AC Gauss	1500.0G	0.1G	±(5% + 20d)
	15,000G	1G	±(5% + 20d)
Number of Axis	Uniaxial		
AC Bandwidth	50Hz/60Hz		
Dimensions	7.8x2.7x1.2" (195x68x30mm)		
Weight	9.5oz (270g)		

Ordering

MF100..... AC/DC Magnetic Field Meter



UPC Code: 793950361108

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Environmental Test Equipment](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[CW40](#) [F150C10E3DRT](#) [F150LTC20](#) [F150CD10E2](#) [F150L75](#) [F150LRS](#) [S-11](#) [FLUKE-LDG](#) [382153](#) [FM100](#) [RH210](#) [382253](#) [MO290-P](#)
[GEO-CABLE-REEL-50M](#) [T197914](#) [RD300-L](#) [IR11BD](#) [IR11GM](#) [IR12GM](#) [IR21BD](#) [IR31CE](#) [IR32BC](#) [IR33BC](#) [MP7217TC](#) [NGM-1](#) [SGX-](#)
[7NH3](#) [UT381](#) [F150-SLC50](#) [AW-CO-1000](#) [AW-NmHc-100](#) [3.000.401](#) [AX-7535](#) [CS-9S6SS-A](#) [P 2800 A](#) [P 2801](#) [P 2802](#) [P 5039](#) [P 5130](#) [P](#)
[5055](#) [P 5060](#) [P 5065](#) [P 5086](#) [P 5090](#) [P 5110](#) [P 5115](#) [P 5135](#) [P 5140](#) [P 5145](#) [P 5150](#) [P 5160](#)