

PCB/SMD Mount Reed Switch/Sensor

Product Name	Normally Open Reed Sensor	Item No.	FRS-11A16SMDH
		<p>Advantages:</p> <ol style="list-style-type: none"> 1. Easy installation, operate in magnetic field. 2. Passive switch, no need outer power 3. Cut through any non-iron materials. 	
Item Numbers	FRS-11A16SMDH	FRS-11A16SMDH02A	
Built-in reed switch	MKA10110	RI-02	
Switch Form	Form A-SPST	Form A-SPST	
Operate Range (AT)	8-40	9-15	
Operate Time (ms)	0.35	0.30	
Resonant Frequency (Hz)	5000	10800	
Switched Power (max.)	10W	10	
Switched Vdc/Vac (max.)	100V	200/140	
Switched Current (max.)	0.5A	0.5A	
Carry Current (max.)	0.5A	0.5A	
Breakdown Voltage (min.)	110-150V	200-230	
Contact Resist. (max.)	150m Ω	150	
Contact Capacit. (max.)	0.5pF	0.3	
Insulation Resist. (min.)	10 ⁶	10 ¹²	
Mould Case	Black Epoxy Resin		
Sealed technique	Black Epoxy Resin		
Work Temperature	-55~+230		
Installation	2 pins, SMT		

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Board Mount Hall Effect/Magnetic Sensors](#) category:

Click to view products by [FAST Sensors](#) manufacturer:

Other Similar products are found below :

[HGPRDT005A](#) [AH1894-FA-7](#) [AH277AZ4-AG1](#) [AV-10448](#) [SS41C](#) [AH1894-Z-7](#) [TLE4946-1L](#) [TLE4976L](#) [SS85CA](#) [BU52003GUL-E2](#)
[AH277AZ4-BG1](#) [AH3376-P-B](#) [TLE4941](#) [TLE4945-2L](#) [AH3360-FT4-7](#) [TLE4941-1](#) [AH374-P-A](#) [SS41-JL](#) [AH1913-W-7](#) [AH3373-P-B](#)
[MA732GQ-Z](#) [MA330GQ-Z](#) [S-57K1NBL2A-M3T2U](#) [S-57P1NBL9S-M3T4U](#) [S-576ZNL2B-L3T2U](#) [S-576ZNL2B-A6T8U](#) [S-57P1NBL0S-](#)
[M3T4U](#) [S-57A1NSL1A-M3T2U](#) [S-57K1RBL1A-M3T2U](#) [S-57P1NBH9S-M3T4U](#) [S-57P1NBH0S-M3T4U](#) [S-57A1NSH1A-M3T2U](#) [S-](#)
[57A1NSH2A-M3T2U](#) [S-57K1NBH1A-M3T2U](#) [S-57A1NNL1A-M3T2U](#) [S-5701BC11B-L3T2U5](#) [S-57GNNL3S-A6T8U](#) [S-57TZ1L1S-](#)
[A6T8U](#) [S-57GSNL3S-A6T8U](#) [S-5716ANDH0-I4T1U](#) [S-57GSNL5S-L3T2U](#) [S-57GDNL3S-L3T2U](#) [S-57GNNL3S-L3T2U](#) [S-57RBNL8S-](#)
[L3T2U](#) [S-57RBNL9S-A6T8U](#) [S-57RB1L8S-L3T2U](#) [S-57GDNL5S-L3T2U](#) [S-57RBNL9S-L3T2U](#) [S-57TZ1L1S-L3T2U](#) [S-57TZNL1S-](#)
[A6T8U](#)