

i6000sFlex AC Current Probe



The i6000sflex is an AC current probe utilising the Rogowski principle. It can be used to measure currents up to 6000A when used in conjunction with oscilloscopes, recorders or data loggers. The flexible and lightweight measuring head allows quick and easy installation in hard to reach areas.

Function	I6000s Flex-24	I6000s Flex-36
Use with DMMs (i3000 w/ BNC adapter)	x	x
Use with oscilloscopes and power quality	x	x
Bandwidth up to 20 kHz	x	x
Bandwidth up to 100 kHz	x	x
Battery life 200 hours	x	x
Battery life 400 hours	x	x
Permanent data logging (via external power supply)	x	x
Conductor diameter upto 170 mm (6.5 in)	x	x
Conductor diameter upto 275 mm (10.5 in)		x

General Specifications:

Phase error	$\pm 1^\circ$ (45 to 65 Hz), $\pm 10^\circ$ (at 5 kHz)
Linearity	$\pm 0.2\%$ of reading from 10% to 100% of range
Position sensitivity	$\pm 2\%$ of range, cable >25mm (1") from coupling
External field	$\pm 1\%$ with cable > 200mm (8") from head
Noise level	0.1mV rms (0.03% of range)
Operating temperature	-20°C to 85°C (-4°F to 185°F) Electronics
Storage temperature	-20°C to 85°C (-4°F to 185°F) Electronics
Gain variation	$\pm 0.08\%/^\circ\text{C}$
Common mode	voltage Voltage between the Output and Earth must not exceed 30V
Power supply	2 x AA MN1500 (1.5V) LR6 batteries
Low battery indication	Red LED
External power	Battery eliminator, via 2.1mm connector, 3V DC
Socket type	A16M500
Safety	BS EN 61010-1: 1993, 600V CAT III Pol. Deg 2 EMC EN61326: 1998
Enclosure	IP5X, Flame retardant UL94 -V0 rated
Material	Valox 357 X
Output connections	Hypotronics connector type D01EEB306FST
Weight	0.19 kg (0.4 lb)

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Fluke](#) manufacturer:

Other Similar products are found below :

[FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#)
[CIE600](#) [TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374](#)
[FC](#) [TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [MA610](#) [EA30-](#)
[NIST](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#) [DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#)