

TECHNICAL DATA

# Fluke T6 Electrical Testers with FieldSense technology



## Measure voltage...without test leads

Measure voltage up to 1000 V ac through the open fork, without test lead contact to live voltage.\* Without opening covers or removing wire nuts. On wires up to AWG 4/0 (120 mm<sup>2</sup>), carrying as much as 200 A. It will change your job. Safer. Faster. Easier.

## Product Highlights

- FieldSense technology for ac voltage, current and frequency measurement without making electrical contact to live voltage\*
- Simultaneous voltage and current display (T6-1000)—shows all power supply measurements at a glance for efficient troubleshooting
- 1 to 1000 V ac or dc (T6-1000); 600 V ac or dc (T6-600)
- 0.1 to 200 A ac
- Resistance 1 Ω to 100 kΩ (T6-1000), 1 Ω to 2 kΩ (T6-600)
- Frequency measurement 45 Hz to 66 Hz (T6-1000)
- Works with wires up to AWG 4/0 (120 mm<sup>2</sup>) with a 17.8 mm jaw opening.
- HOLD button temporarily freezes the reading for easy viewing
- Easy to read display with backlight
- Accepts optional Fluke TPAK Magnetic Meter Hanger for convenient operation
- Standard two-year warranty; extendable to four years through product registration within 45 days of purchase\*

+ Requires capacitive path to ground, provided through user in most applications. Ground connection via test lead may be required in some situations.

\* Register product online within 45 days of purchase to extend warranty to four years. See <http://a.fluke.com/registration> for details.



## Specifications

Measurement Specifications					
Function	Requires test leads	T6-600	T6-1000	Resolution	Accuracy <sup>(1)</sup>
		Range	Range		
FieldSense ac voltage	No	600 V	1000 V	1 V	±(3 % + 3 counts) <sup>[2] [3]</sup> 45 Hz - 66 Hz
FieldSense ac current	No	200.0 A	200.0 A	0.1 A	±(3 % + 3 counts) 45 Hz - 66 Hz
FieldSense frequency [Hz]	No		45 Hz - 66 Hz	1 Hz	±(1 % + 2 counts) <sup>[3]</sup>
Volts ac	Yes	600 V	1000 V	1 V	±(1.5 % + 2 counts) 45 Hz - 66 Hz
Volts dc	Yes	600 V	1000 V	1 V	±(1 % + 2 counts)
Resistance	Yes	2000 Ω	2000 Ω	1 Ω	±(1 % + 2 counts)
	Yes		20.00 kΩ	0.01 kΩ	±(1 % + 2 counts)
	Yes		100.0 kΩ	0.1 kΩ	±(1 % + 2 counts)
Safety (measurement category)		600 V CAT III	1000 V CAT III 600 V CAT IV		

Accuracy<sup>(1)</sup>: ± ( [ % of reading ] + [ number of least significant digits ] ). Accuracy is specified for 1 year after calibration, at 18 °C to 28 °C (64 °F to 82 °F) with relative humidity to 90 %. AC conversions are ac-coupled, RMS responding.

Accuracy<sup>(2)</sup>: Add 3 % without an external ground connection. External ground connection required for user wearing insulated gloves, standing on an insulated ladder and otherwise insulated from earth ground.

Accuracy<sup>(3)</sup>: FieldSense specified from 16V to 100% of range.

## General Specifications

Calibration	1-year calibration cycle
Dimensions	61.1 mm x 259.3 mm x 43.8 mm
Weight	0.35 kg (0.78 lb)
Fork opening	17.8 mm
Temperature Operating: Storage:	-10 °C to +50 °C (14 °F to 122 °F) -30 °C to +60 °C (-22 °F to +140 °F)
Altitude Operating: Storage:	2,000 m (6,562 feet) 10,000 m (32,808 feet)
Relative Humidity	0 % to 90 %, 5 °C to 30 °C (41 °F to 86 °F) 0 % to 75 %, 30 °C to 40 °C (86 °F to 104 °F) 0 % to 45 %, 40 °C to 50 °C (104 °F to 122 °F)
Battery Type and Life	2 x AA (IEC LR6); 360 hours continuous, typical; 200 hours using FieldSense
Temperature coefficient	0.1 x (specified accuracy) / °C for <18 °C or >28 °C ( < 64.4 °F or > 82.4 °F )
Safety	IEC/EN 61010-1, IEC/EN 61010-2-033: Pollution Degree 2
Electromagnetic Environment	IEC/EN 61326-1: Portable



## Ordering information

**Fluke T6-600 Electrical Tester**

**Fluke T6-1000 Electrical Tester**

### Included with product

Attached test leads with removable 4 mm probe caps, user documentation

### Optional accessories

H-T6 Belt Holster

TPAK Magnetic Hanger

PRV240FS Proving Unit

TP1 Probe Set, Flat-Blade (US/UK flat tip)

TP38 Probe set, round (EU)

AC285 SureGrip Alligator Clips

AC220 SureGrip Alligator Clips

Service Information Sheet, PN 686953

**Fluke.** Keeping your world up and running.®

### Fluke Corporation

PO Box 9090, Everett, WA 98206 U.S.A.

### Fluke Europe B.V.

PO Box 1186, 5602 BD Eindhoven, The Netherlands

Modification of this document is not permitted without written permission from Fluke Corporation.

### For more information call:

In the U.S.A. (800) 443-5853 or Fax (425) 446-5116

In Europe/M-East/Africa +31 (0)40 267 5100 or Fax +31 (0)40 267 5222

In Canada (800)-36-FLUKE or Fax (905) 890-6866

From other countries +1 (425) 446-5500 or Fax +1 (425) 446-5116

Web access: <http://www.fluke.com>

©2017 Fluke Corporation. Specifications subject to change without notice. 8/2017 6009251b-en

\* Two-year additional warranty offer may be discontinued without notice

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Digital Multimeters](#) category:*

*Click to view products by [Fluke](#) manufacturer:*

Other Similar products are found below :

[6111-517](#) [FS881](#) [40705X](#) [C.A 6133 LAUNCH KIT](#) [P 1020 A](#) [P 3340](#) [SEFRAM7303](#) [BS K-CLIP](#) [19290](#) [IBT6K](#) [1000-219](#) [1001-613](#) [1006-969](#) [1008-221](#) [1012-597](#) [1013-099](#) [30XR](#) [34XR](#) [35XP](#) [TESTO 745](#) [0590 7450](#) [TESTO 760-2](#) [0590 7602](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-594](#) [AX-LCR42A](#) [AX-MS811](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM525S](#) [BM805S](#) [BM807S](#) [BM817S](#) [BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#) [BM867S](#) [BM907S](#) [33XR](#)