



# IBC™ OneClick Cleaner Solution

Research has shown over 85% of fiber related problems in data centers, campus, and other enterprise or telecom environments are caused by contaminated connectors or end-faces.

For best optical performance, it is imperative that all optical fiber connections are clean and free of contaminants. An easy to use fiber cleaning tool becomes a necessity for both installers as well as fiber optic technicians and troubleshooters.

With Fluke Networks IBC OneClick Cleaners, harmful contaminants are easily removed from a wide variety of connector types. Even with no training, field technicians and fiber installers can use a simple insertion and push motion to remove residue, debris and dust that can negatively impact network performance. These cleaners are great complements to the existing Fluke Networks fiber optic solvent pen, cleaning cube and cleaning kits for all fiber environments.

The IBC OneClick Cleaner family is specifically designed to provide a cost effective solution for most bulkhead connectors and end-faces, including MPO/MTP connectors.

The Fluke Networks IBC™ OneClick Cleaners are a family of mechanical cleaning tools designed to clean fiber optic connector end faces on patch cables, within adapters or patch panels. These IBC™ OneClick Cleaners are molded with an antistatic material and use a novel dry cleaning strand that gently sweeps and removes harmful contaminants from the connector without damaging the connector end face. These tools are particularly effective at removing contaminants during fiber optic installation that include:

- Road Dust (ISO 12103-1)
- Skin Oil Residue
- Salt Water Residue
- Alcohol Residue
- Vegetable Residue
- Graphite dryer Lint
- Hand Lotion
- Distilled Water Residue

## IBC OneClick 1.25mm Cleaner and 2.5mm Cleaner

The IBC OneClick 1.25mm Cleaner is designed to clean LC, LC secure keyed and MU connectors while the OneClick 2.5mm Cleaner is used to clean SC, ST, FC and E2000 connectors with either UPC or APC polished ferrules. Unlike traditional swab cleaners that rely on the technique of the user, the IBC OneClick Cleaners provide consistent cleaning every time. The user can easily engage the cleaner using a simple push motion and the user will hear a “click” sound when the process is completed.

### Features:

- Simple pushing motion to engage tool
- Audible CLICK to alert the user when tool is fully engaged



IBC OneClick Cleaner Tools - 2.5mm, 1.25mm and MPO

- Clean over 500 end faces per unit
- Tip extender to 208mm for hard to reach connectors
- Crush resistant to over 250N
- Impact resistant to survive drops over 1.5m

## IBC OneClick MPO Cleaner





The MPO Cleaner is designed for cleaning the fiber arrays on MPO/MTP® based connectors. This tool is capable of cleaning MT based connector systems loaded in a bulkhead adapter and on unmated cable assemblies. The IBC™ OneClick MPO Cleaners will clean both female (no guide pin) and male (with steel guide pin) patch panel. The tool will also clean both flat polished multimode and 8° angled singlemode MT ferrules.

### Features:

- Simple dial turn engagement that is easy to operate
- Audible CLICK to alert the operator when cleaning is completed
- Clean over 600 end faces per unit
- Cleans male and female MT ferrules
- Nozzle is keyed for precise alignment of the cleaning tip to the fiber array
- Alignment cap lid opens for cleaning the unmated connectors



## IBC OneClick Cleaners Ordering Information

Model	Description
<p>NFC-IBC-1.25mm</p> 	OneClick cleaner for 1.25 mm LC and MU connector and end faces (5 count)
<p>NFC-IBC-2.5mm</p> 	OneClick cleaner for 2.5 mm SC, ST, FC, E2000 connector and end faces (5 count)
<p>NFC-IBC-MPO</p> 	OneClick cleaner for MPO/MTP connector (5 count)
<p>NFC-KIT-CASE-E</p> 	Enhanced Fiber Optic Cleaning Kit - Includes a OneClick 1.25mm cleaner, a OneClick 2.5mm cleaner, a OneClick MPO cleaner, a solvent pen, a cleaning cube and a softcase

Connector Type	NFC-IBC-1.25mm	NFC-IBC-2.5mm	NFC-IBC-MPO	NFC-KIT-CASE-E	NFC-KIT-CASE*	NFC-KIT-BOX**
SC		X		X	X	X
ST		X		X	X	X
FC		X		X	X	X
LC	X			X	X	
MU	X			X	X	
MPO/MTP			X	X		
E2000		X		X	X	X

<b>Total Number of Cleans per SKU</b>	2500	2500	3000	2150	620	560
---------------------------------------	------	------	------	------	-----	-----

\*Note 1: NFC-KIT-CASE includes cleaning cube, 10 cleaning cards, solvent pen, and 1.25 and 2.5mm cleaning swabs.

\*\*Note 2: NFC-KIT-BOX includes cleaning cube with 5 cleaning cards, solvent pen, and 2.5mm cleaning swabs.

**Fluke Networks**  
P.O. Box 777, Everett, WA USA 98206-0777

Fluke Networks operates in more than 50 countries worldwide. To find your local office contact details, go to [www.flukenetworks.com/contact](http://www.flukenetworks.com/contact).

©2011 Fluke Corporation.  
Printed in U.S.A. 8/2011 4101991A

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [fluke](#) manufacturer:*

Other Similar products are found below :

[FLUKE-1630-2FC](#) [665080](#) [677393](#) [708396](#) [FLK-VT04-CHARGER](#) [FLUKE 1663](#) [FLUKE-355](#) [FLUKE-424D](#) [FLUKE 80PK-11](#) [FLUKE 80PK-22](#) [FLUKE 80PK-26](#) [FLUKE A3002FC](#) [FLUKE C280](#) [FLUKE I200](#) [FLUKE I3000FLEX-24](#) [FLUKE I400](#) [FLUKE TLK287](#) [FLUKE TP1](#) [FOC-ST/FC](#) [FUSE-15A/600BLSTR](#) [DSP-SR](#) [1553041](#) [1576734](#) [1610198](#) [1633984](#) [C28Y](#) [2096971](#) [2148281](#) [2166266](#) [RS41](#) [2477950](#) [2550519](#) [2558118](#) [2577126](#) [2584901](#) [2811795](#) [2840276](#) [STL120-III](#) [1LAC-A](#) [FLUKE 116/323](#) [FLUKE 52](#) [FLUKE 54](#) [FLUKE-789](#) [FLUKE-805](#) [FLUKE 80K-15](#) [FLUKE 8808/TL](#) [FLUKE-971](#) [FLUKE C101](#) [FLUKE I410](#) [FLUKE T3000FC](#)