

UPS with USB and LCD display, 3000 VA, black

EG-UPS-036



ULTIMATE DEFENCE

- Informative LCD display
- Provides backup power prevents data loss
- Protects your sensitive and valuable equipment
- Compact and reliable ideal for home and small office use

Features

- Uninterruptable 3000 VA power supply for PC's
- Automatic output voltage regulation (AVR)
- USB interface
- LCD status indication
- Short circuit protection
- Surge, spike and lightning protection
- Audible and visual alarms
- Overcharge and overdischarge protection
- Including practical UPS Management software

Packaging

Q'ty in crtn, pcs	1
Crtn volume, CUM	0.0396
Crtn weight, kgs	20.82
Individual package size LxWxH:	500x300x150 mm
Carton size LxWxH:	550x240x300 mm
Country of origin	CN
Barcode	8716309124744
Customs code	8504408590

Package contents

- UPS
- Power cord
- USB cable
- Software CD
- Spare fuse

Specifications

Type: line interactive
 Waveform: sine wave (AC mains), modified (square) sine wave (battery)
 Input: 220 V AC \pm 25% (162-295V), 50 / 60 Hz \pm 10%
 Output: 220 V AC \pm 10%, 50 / 60 Hz \pm 1% (220 V AC \pm 10 % at inverter mode)
 Switching time: less than 10 ms
 Backup time: 8...20 mins (depends on the load)
 Battery: sealed lead-acid 12 V DC / 7 Ah x 4 pcs
 Charge time: up to 90% after 6-8 hours
 Sockets: 1 x C14 input, 3 pcs x C13 output, 3 pcs x german Shuko output
 Interface communication: USB-BF socket, RI45

System requirements

Software is compatible with Windows 7/8/10/11, Windows 2008 server

In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work

Certificates



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [UPS - Uninterruptible Power Supplies](#) category:

Click to view products by [Gembird](#) manufacturer:

Other Similar products are found below :

[SMART-1400-RM](#) [UPS1500ITSIT](#) [QUINT4-UPS/24DC/24DC/20/EI](#) [QUINT4-UPS/24DC/24DC/40/EI](#) [QUINT4-UPS/24DC/24DC/10/US](#)
[QUINT4-UPS/24DC/24DC/20/US](#) [QUINT4-UPS/24DC/24DC/40/US](#) [2789910000](#) [2786240000](#) [5AVRZP2000](#) [51942](#) [50717](#) [50719](#) [EG-](#)
[UPS-035](#) [51945](#) [50725](#) [50721](#) [50177](#) [EG-UPS-PS3000-02](#) [51940](#) [50720](#) [UPS-RACK-1200](#) [5AVRZP5000](#) [50722](#) [5AVRZP1000](#) [50351](#)
[51944](#) [50726](#) [EG-UPS-PS2000-02](#) [51941](#) [5AVR3000SE](#) [EG-UPS-036](#) [50724](#) [EG-UPSO-1000](#) [EG-UPS-PS1000-01](#) [SDUCFRELAYCARD](#)
[SDUCFRELAYCARD](#) [SDUMBUSCARD](#) [50348](#) [ISRELAY](#) [6EP1931-2EC21](#) [6EP1933-2EC51](#) [SDU-24-BAT](#) [6EP1931-2DC21](#) [AK-B1-](#)
[500E](#) [AK-B1-700BE](#) [AK-I1-200](#) [AK-I2-150](#) [AK-S1-300](#) [AK-T1-250](#)