

## Online UPS, 10000 VA, USB + SNMP slot, terminals without cables

EG-UPS0-10000

### ULTIMATE DEFENCE

- Pure sine wave output
- Provide backup power Prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sinewave input
- Compact and reliable ideal for home and small office use



### Features

- Online type UPS: double voltage conversion with pure sine wave output without switching the power
- USB interface
- Automatic AC voltage regulation (AVR)
- Intelligent overload and short-circuit protection
- Audible and visual alarms
- LCD display and LED status indication
- Internal battery with overcharge and over-discharge protection

### Packaging

Q'ty in crtn, pcs	1
Crtn volume, CUM	0.16988
Crtn weight, kgs	70
Individual package size LxWxH:	685x310x800 mm
Carton size LxWxH:	685x310x800 mm
Country of origin	CN
Barcode	8716309124850
Customs code	8504408590

### Package contents

UPS without cords

### Specifications

Type: online  
 Waveform: sine, <2% distortion at linear load (<5% non-linear), PF > 0.99  
 Input: AC 176 ~ 288 V, 40 70 Hz autodetect  
 Output: AC 208 V / 220 V / 230 V / 240 V (settable) ±1%, 45Hz/65Hz autosense  
 Switching time: near 0 ms  
 Backup time: 30 mins (depends on the load)  
 Battery: UPS with sealed lead-acid 12V/9Ah 16 pcs; 192 V DC  
 Charge time: 90% capacity restored in 8 hours  
 Input Sockets: Terminal block input Single-phase three-wire (1F + N + PE);

### System requirements

In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

### Certificates



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [UPS - Uninterruptible Power Supplies](#) category:*

*Click to view products by [Gembird](#) manufacturer:*

Other Similar products are found below :

[UPS1500ITSIT](#) [TRIO-UPS-2G/3AC/24DC/20](#) [QUINT4-UPS/24DC/24DC/20/EI](#) [QUINT4-UPS/24DC/24DC/40/EI](#) [QUINT4-UPS/24DC/24DC/10/US](#) [QUINT4-UPS/24DC/24DC/20/US](#) [QUINT4-UPS/24DC/24DC/40/US](#) [2789910000](#) [2786240000](#) [2789890000](#) [5AVRZP2000](#) [51942](#) [50717](#) [50719](#) [50725](#) [50177](#) [5AVR2000SE](#) [51940](#) [UPS-RACK-1200](#) [5AVRZP5000](#) [50722](#) [5AVRZP1000](#) [50351](#) [50726](#) [51941](#) [5AVR3000SE](#) [50724](#) [5AVRZP3000](#) [UPS-RACK-2000](#) [50728](#) [AVR-3000 PRO](#) [AVR-1000 PRO](#) [5AVRZ10000](#) [50718](#) [50723](#) [WAKSPOWER11-G4-06K0-RT-BC192](#) [5AVR0500SE](#) [5AVR1000SE](#) [50727](#) [AK-C1-600](#) [50342](#) [AK-C1-800](#) [AVR-2000 PRO](#) [WAKSPOWER11-G4-10K0-RT-BC192](#) [AK-C1-500](#) [EG-UPS0-10000](#) [TSPC 240-124UPS](#) [SDUCFRELAYCARD](#) [SDUCFRELAYCARD](#) [SDUMBUSCARD](#)