

## GPE-X323 Series



### FEATURES


- 1/2/3/4 Independent Isolated Output
- 4.3 Inch LCD Display
- Setting & Read Back Resolution 100mV/10mA (\*1)
- Output On/off
- Analog Control (Remote I/O) For Output ON/OFF
- Set View Function For Checking an Original V/I Setting During Output On
- Key Lock Function
- Tracking Series And Parallel Operation
- Smart Cooling Fan Achieving Low Noise
- Optional European Jack Type Terminal



The GPE-X323 series is cutting edge, economical linear DC Power supplies. The GPE-X323 series features output power from 192 to 217 watts, three independent isolated output channels (for GPE-3323), high resolution, low noise, high reliability, and compact size. The GPE-X323 series has a built-in digital panel control design to replace conventional control method. This unique design allows the GPE-X323 series linear DC power supply to provide users with more efficient functionalities, including set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage and current parameters. Additionally, output key light facilitates users in clearly reading the operational status of power supply.

### Tracking Series and Parallel Operation

In addition to independent output channels, the GPE-X323 series provides tracking series and parallel operation (For GPE-2323/GPE-3323/GPE-4323). The series and parallel connections allow power supplies to output 32V/6A (Parallel Connection) and 64V/3A (Series Connection).



Internal connection for tracking Series and Parallel operation via control panel

### Convenient Function


The GPE-X323 series has a built-in set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage/current parameters.



The key lock function prevent DUTs from unnecessary damages caused by mis-operation.

### Remote I/O for output On/Off function

The GPE-X323 Series also provides the analog control (Remote I/O) function for external output On/Off control.



For controlling the output On/Off function through the specific pin assignment of remote control connector which is in rear panel.



Front



Rear Panel

### APPLICATIONS

- Laboratories and Educational Facilities
- Product Testing and Quality Assurance
- Service Operation and Post-Sales Support
- Product Development and Debugging

## SPECIFICATIONS

		GPE-4323				GPE-3323			GPE-2323		GPE-1326
OUTPUT MODE	Number of Channel Voltage Current Tracking Series Voltage Tracking Parallel Current	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1
		0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	5V	0~32V	0~32V	0~32V
		0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A
		0~64V				0~64V			0~64V		
		0~6A				0~6A			0~6A		
CONSTANT VOLTAGE OPERATION	Line Regulation Load Regulation Ripple & Noise Recovery Time	$\leq 0.01\%+3mV$ $\leq 0.01\%+3mV$ (rating current $\leq 3A$ ); $\leq 0.02\%+5mV$ (rating current $> 3A$ ) $\leq 1mVrms$ (5Hz~1MHz) $\leq 100\mu s$ (50% Load Change, minimum load 0.5A)									
CONSTANT CURRENT OPERATION	Line Regulation Load Regulation Ripple & Noise	$\leq 0.2\%+3mA$ $\leq 0.2\%+3mA$ $\leq 3mArms$									
TRACKING OPERATION (CH1,CH2)	Tracking Error Parallel Regulation Series Regulation Ripple & Noise	$\leq 0.1\%+10mV$ of Master(0~32V) No Load , with Load add load regulation $\leq 100mV$ Line : $\leq 0.01\%+3mV$ Load : $\leq 0.01\%+3mV$ (rating current $\leq 3A$ ); $\leq 0.02\%+5mV$ (rating current $> 3A$ ) Line : $\leq 0.01\%+5mV$ Load : $\leq 100mV$ $\leq 2mVrms$ , 5Hz ~ 1MHz									
CH3 OPERATION FOR (GPE-3323)	Output Voltage Output Current Line Regulation Load Regulation Ripple & Noise	5.0V, $\pm 5\%$ 5A $\leq 3mV$ $\leq 5mV$ 1mVrms(5Hz~1MHz)									
METER	Voltage Resolution Current Resolution Setting Accuracy Readback Accuracy	100mV (*1) 10mA (*1) Voltage $\pm$ (0.1% of reading +30mV); Current $\pm$ (0.3% of reading +6mA) Voltage $\pm$ (0.1% of reading +30mV); Current $\pm$ (0.3% of reading +6mA)									
INSULATION	Chassis and Terminal Chassis and AC Cord	20M $\Omega$ or above (DC 500V) 30M $\Omega$ or above (DC 500V)									
ENVIRONMENT CONDITION	Operation Temp Storage Temp Operating Humidity Storage Humidity	0~40 $^{\circ}C$ -10~70 $^{\circ}C$ $\leq 80\%$ RH $\leq 70\%$ RH									
OTHER	Power Source Dimensions & Weight	AC100V/120V/220V $\pm 10\%$ ; 230V(+10%~-6%); 50/60Hz 210(W)x 155(H) x 306(D) mm ; Approx. 7kg									

Note : (\*1) For a higher resolution (10mV/1mA), please follow the setting procedure of the user manual on p35.  
 When using a higher resolution, the current or voltage adjustment may be limited by the knob sensibility.

Specifications subject to change without notice. PE-x303CD1DH

### ORDERING INFORMATION

**GPE-1326** Single Channel, 192W Linear DC Power Supply  
**GPE-2323** 2 Channels, 192W Linear DC Power Supply  
**GPE-3323** 3 Channels, 217W Linear DC Power Supply  
**GPE-4323** 4 Channels, 212W Linear DC Power Supply

### ACCESSORIES

User Manual (CD) x 1 ; Power Cord x 1  
**GPE-1326** Test Lead GTL-104A x 1; GTL-105 x 1 ; or European GTL-204A x 1, GTL-203A x1  
**GPE-2323** Test Lead GTL-104A x 2; or European GTL-204A x 2  
**GPE-3323** Test Lead GTL-104A x 3; or European GTL-204A x 3  
**GPE-4323** Test Lead GTL-104A x 2; GTL-105A x 2 or European GTL-204A x 2, GTL-203A x 2

Global Headquarters

#### GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan  
 T +886-2-2268-0389 F +886-2-2268-0639  
 E-mail: marketing@goodwill.com.tw

China Subsidiary

#### GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

No. 521, Zhujiang Road, Snd, Suzhou Jiangsu 215011 China  
 T +86-512-6661-7177 F +86-512-6661-7277  
 E-mail: marketing@instek.com.cn

Malaysia Subsidiary

#### GOOD WILL INSTRUMENT (SEA) SDN. BHD.

No. 1-3-18, Elit Avenue, Jalan Mayang Pasir 3,  
 11950 Bayan Baru, Penang, Malaysia  
 T +604-6111122 F +604-6115225  
 E-mail: sales@goodwill.com.my

Europe Subsidiary

#### GOOD WILL INSTRUMENT EURO B.V.

De Run 5427A, 5504DG Veldhoven, THE NETHERLANDS  
 T +31(0)40-2557790 F +31(0)40-2541194

U.S.A. Subsidiary

#### INSTEK AMERICA CORP.

5198 Brooks Street Montclair, CA 91763, U.S.A.  
 T +1-909-399-3535 F +1-909-399-0819  
 E-mail: sales@instekamerica.com

Japan Subsidiary

#### TEXIO TECHNOLOGY CORPORATION.

7F Towa Fudosan Shin Yokohama Bldg., 2-18-13 Shin  
 Yokohama, Kohoku-ku, Yokohama, Kanagawa,  
 222-0033 Japan  
 T +81-45-620-2305 F +81-45-534-7181  
 E-mail: info@texio.co.jp

Korea Subsidiary

#### GOOD WILL INSTRUMENT KOREA CO., LTD.

Room No.503, Gyeonginro 775 (Mullae-Dong 3Ga,  
 Ace Hightech-City B/D 1Dong), Yeongduengpo-Gu,  
 Seoul 150093, Korea.  
 T +82-2-3439-2205 F +82-2-3439-2207  
 E-mail : gwinstek@gwinstek.co.kr

**GW INSTEK**  
 Simply Reliable



www.gwinstek.com

www.facebook.com/GWInstek

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Switching Power Supplies](#) category:*

*Click to view products by [GW Connect](#) manufacturer:*

Other Similar products are found below :

[70841011](#) [73-551-0005](#) [AAD600S-4-OP](#) [R22095](#) [KD0204](#) [9021](#) [S-15F-12](#) [LDIN100150](#) [LPM000-BBAR-01](#) [LPX17S-C](#) [EVS57-10R6/R](#)  
[FDC40-24S12](#) [FP80](#) [FRV7000G](#) [22929](#) [CQM1IA121](#) [40370121900](#) [VI-PU22-EXX](#) [40370121910](#) [LDIN5075](#) [432703037161](#) [WRB01X-U](#)  
[LPX140-C](#) [08-30466-1040G](#) [09-160CFG](#) [70841004](#) [70841025](#) [VPX3000-CBL-DC](#) [VI-LUL-IU](#) [LPM000-BBAR-05](#) [LPM000-BBAR-08](#)  
[LPM124-OUTA1-48](#) [LPM000-BBAR-07](#) [LPM109-OUTA1-10](#) [LPM616-CHAS](#) [08-30466-1055G](#) [08-30466-2175G](#) [DMB-EWG](#) [TVQF-](#)  
[1219-18S](#) [6504-226-2101](#) [CQM1IPS01](#) [XPFM201A+](#) [MAP80-4000G](#) [LFP300F-24-TY](#) [SMP21-L20-DC24V-5A](#) [VI-MUL-ES](#) [08-30466-](#)  
[0065G](#) [CME240P-24](#) [VI-RU031-EWWX](#) [08-30466-0028G](#)