

GSP-9300B

NEW



PRACTICAL, AFFORDABLE AND NEVER CARELESS!

GSP-9300B is a 3GHz spectrum analyzer to meet basic RF measurement requirements. It provides the frequency stability of 0.025ppm; the aging rate of 1ppm/year; a built-in preamplifier; the base noise of -149dBm/Hz, and more than 20 measurement applications, including AM/FM modulation signal analysis, signal channel analysis, and CATV parameter test. While collocating with TG option, GSP-9300B can conduct frequency response or power linearity tests for components.

For monitoring signals, GSP-9300B provides Topographic display mode, which is capable of distinguishing continuous or random signals by using color temperature. Spectrogram mode provides a time axis on spectrum display that allows users to observe signal variations based upon the reference of time. Split window mode allows different parameter settings for each display window. Additionally, GSP-9300B also provides user-friendly user interfaces such as display mode, help, multi-languages, and fast data logging, etc. Interfaces and software include USB/RS-232/LXI/MicroSD/GPIB (option)/DVI output and dedicated PC software IVI Driver.

GSP-9300B, with its unique features, including auto wake-Up, sequence function, and limit line testing, is specially designed to meet the requirements of production lines. The patent design of heat conduction allows GSP-9300B to substantially reduce the warm-up time so as to expedite production processes. Options include tracking generator, carrying bag, battery module, EMI antenna set and rack accessories. The compact design of GSP-9300B satisfies either field testing or the integration of automatic testing systems.

To sum up, GSP-9300B is a stable, light and all-purpose test equipment, which is the most ideal choice for the educational market, production line, and general signal monitoring applications, etc. Most important, the pricing of GSP-9300B is beyond your imagination and it is the number one choice for users with budget considerations.

Frequency Stability : 0.025ppm

Wireless communications applications are nowadays ubiquitous. Signals in the limited spectrum are getting very crowded. Therefore, the demands of signal efficiency and frequency stability are higher and stricter. To meet high precision measurement requirements, GSP-9300B provides the frequency stability of 0.025ppm and the aging rate of 1ppm/year, which only appear in high-end T&M equipment.

Built-in Preamplifier

Engineers often face the challenge of measuring small RF signals during product development stage. GSP-9300B's built-in preamplifier provides the base noise of -149dBm. When collocating with the built-in EMI filter and the dedicated EMI near field probe, GSP-9300B can conduct EMI tests and debugging.

More Than 20 Measurement Applications

GSP-9300B provides rich signal processing functions, including AM/FM modulation signal analysis, signal channel analysis, and CATV parameter test, characteristic test on signal stability, and frequency response or power linearity tests for components to substantially bring up the measurement convenience. Most competitors in the same class only offer a few test functions, and the standard built-in functions of GSP-9300B are options for competitors.

FEATURES

- Frequency Range : 9kHz ~ 3 GHz
- 0.025ppm Frequency Stability and 1ppm Aging Rate
- Built-in Preamplifier, 50dB Attenuator, and Sequence Function
- RBW : 1Hz ~ 1MHz
- Sensitivity : -149dBm/Hz (@PreAmp on)
- Built-in AM/FM Demodulation & Analysis
- Built-in P1dB point, Harmonic, Channel Power, N-dB Bandwidth, OCBW, ACPR, SEM, TOI, CNR, CTB, CSO, Noise Marker, Frequency Counter, Time Domain Power, Gated Sweep
- Built-in Spectrogram, Topographic and Dual-View Display Modes
- Remote Control Interface : LAN, USB, RS-232
- Options : Tracking Generator, GPIB Interface

APPLICATIONS

- For the Quick Check and Analysis of Spectral Characteristic
- Analyze AM, FM Signal Characteristics
- Monitor Satellite Uplink Signals From Satellite Uplink Truck
- Test Systems That Require a Very Compact Instrument
- Measure The Frequency Response of Cable, Attenuator, Filter and Amplifier

SPECIFICATIONS

FREQUENCY

FREQUENCY

| | | |
|------------|---------------|--|
| Range | 9 kHz ~ 3 GHz | |
| Resolution | 1 Hz | |

FREQUENCY REFERENCE

| | | |
|--------------------------------------|---|------------------------------|
| Accuracy | $\pm(\text{period since last adjustment} \times \text{aging rate}) + \text{stability over temperature} + \text{supply voltage stability}$ | |
| Aging Rate | $\pm 1 \text{ ppm max.}$ | 1 year after last adjustment |
| Frequency Stability Over Temperature | $\pm 0.025 \text{ ppm}$ | 0 ~ 50 °C |
| Supply Voltage Stability | $\pm 0.02 \text{ ppm}$ | |

FREQUENCY READOUT ACCURACY

| | | |
|-----------------------------|---|--|
| Start, Stop, Center, Marker | $\pm(\text{marker frequency indication} \times \text{frequency reference accuracy} + 10\% \times \text{RBW} + \text{frequency resolution})$ | |
| Trace Points | Max. 601 points, Min. 6 points | |

MARKER FREQUENCY COUNTER

| | | |
|------------|--|---|
| Resolution | 1 Hz, 10 Hz, 100 Hz, 1 kHz | |
| Accuracy | $\pm(\text{marker frequency indication} \times \text{frequency reference accuracy} + \text{counter resolution})$ | RBW/Span ≥ 0.02 ; Mkr level to DNL $> 30 \text{ dB}$ |

FREQUENCY SPAN

| | | |
|------------|-----------------------------------|------------|
| Range | 0 Hz (zero span), 100 Hz ~ 3 GHz | |
| Resolution | 1 Hz | |
| Accuracy | $\pm \text{frequency resolution}$ | RBW : Auto |

PHASE NOISE

| | | |
|---------------------|-------------------------|---|
| Offset from Carrier | | $F_c = 1 \text{ GHz}; \text{RBW} = 1 \text{ kHz}; \text{VBW} = 10 \text{ Hz}; \text{Average} \geq 40$ |
| 10 kHz | $< -88 \text{ dBc/Hz}$ | Typical |
| 100 kHz | $< -95 \text{ dBc/Hz}$ | Typical |
| 1 MHz | $< -113 \text{ dBc/Hz}$ | Typical |

RESOLUTION BANDWIDTH (RBW) FILTER

| | | |
|------------------|--|---|
| Filter Bandwidth | 1 Hz ~ 1 MHz in 1-3-10 sequence 200 Hz, 9 kHz, 120 kHz, 1 MHz | -3dB bandwidth -6dB bandwidth Nominal Normal Bandwidth ratio: -60dB:-3dB |
| Accuracy | $\pm 8\%$, RBW = 1 MHz ; $\pm 5\%$, RBW < 1 MHz | |
| Shape Factor | $< 4.5 : 1$ | |

VIDEO BANDWIDTH (VBW) FILTER

| | | |
|------------------|---------------------------------|----------------|
| Filter Bandwidth | 1 Hz ~ 1 MHz in 1-3-10 sequence | -3dB bandwidth |
|------------------|---------------------------------|----------------|

AMPLITUDE

AMPLITUDE RANGE

| | | |
|-------------------|---|--|
| Measurement Range | 100 kHz ~ 1 MHz 1 MHz ~ 10 MHz 10 MHz ~ 3 GHz | Displayed Average Noise Level (DANL) to 18 dBm DANL to 21 dBm DANL to 30 dBm |
|-------------------|---|--|

ATTENUATOR

| | | |
|------------------------|--------------------------|----------------------|
| Input Attenuator Range | 0 ~ 50 dB, in 1 dB steps | Auto or manual setup |
|------------------------|--------------------------|----------------------|

MAXIMUM SAFE INPUT LEVEL

| | | |
|---------------------|------------------------|---------------------------------------|
| Average Total Power | $\leq +33 \text{ dBm}$ | Input attenuator $\geq 10 \text{ dB}$ |
| DC Voltage | $\pm 50 \text{ V}$ | |

1 dB GAIN COMPRESSION

| | | |
|---------------------------|---------------------|--|
| Total Power at 1st Mixer | $> 0 \text{ dBm}$ | Typical ; $F_c \geq 50 \text{ MHz}$; preamp. off |
| Total Power at the Preamp | $> -22 \text{ dBm}$ | Typical ; $F_c \geq 50 \text{ MHz}$; preamp. on Mixer power level (dBm) = input power (dBm) – attenuation (dB) |

DISPLAYED AVERAGE NOISE LEVEL (DANL)

| | | |
|-----------------|--|---------|
| Preamp off | 0 dB attenuation; RF Input is terminated with a 50Ω load. RBW 10 Hz; VBW 10 Hz; span 500 Hz; reference level = - 60 dBm; trace average ≥ 40 | |
| 9 kHz~100 kHz | $< -93 \text{ dBm}$ | Nominal |
| 100 kHz~1 MHz | $< -90 \text{ dBm} - 3 \times (f/100 \text{ kHz}) \text{ dB}$ | Nominal |
| 1 MHz~10 MHz | $< -122 \text{ dBm}$ | Nominal |
| 2.7 ~ 3.25 GHz | $< -116 \text{ dBm}$ | Nominal |
| Preamp on | 0 dB attenuation; RF Input is terminated with a 50Ω load. RBW 10 Hz; VBW 10 Hz; span 500 Hz; reference level = - 60 dBm; trace average ≥ 40 | |
| 100 kHz~1 MHz | $< -108 \text{ dBm} - 3 \times (f/100 \text{ kHz}) \text{ dB}$ | Nominal |
| 1 MHz~10 MHz | $< -142 \text{ dBm}$ | Nominal |
| 10 MHz~3.25 GHz | $< -142 \text{ dBm} + 3 \times (f/1 \text{ GHz}) \text{ dB}$ | Nominal |

LEVEL DISPLAY RANGE

| | | |
|----------------------|---|----------------------|
| Scales | Log, Linear | |
| Units | dBm, dBmV, dBuV, V, W | |
| Marker Level Readout | 0.01 dB | Log scale |
| Level Display Modes | 0.01 % of reference level | Linear scale |
| Number of Traces | Trace, Topographic, Spectrogram | Single/Split Windows |
| Detector | 4 | |
| Trace Functions | Positive-peak, negative-peak, sample, normal, RMS (not Video), Quasi-Peak (EMI), Average (EMI), Clear & Write, Max/Min Hold, View, Blank, Average | |

ABSOLUTE AMPLITUDE ACCURACY

| | | |
|----------------|---|--|
| Absolute Point | Center=160 MHz ; RBW 10 kHz; VBW 1 kHz; span 100 kHz; log scale; 1 dB/div; peak detector; 23°C \pm 1°C; Signal at Reference Level | |
| Preamp Off | $\pm 0.3 \text{ dB}$ | Ref level 0 dBm; 10 dB RF attenuation |
| Preamp On | $\pm 0.4 \text{ dB}$ | Ref level 0 dBm; -30 dB RF attenuation |

FREQUENCY RESPONSE

| | | |
|-------------------|--|--|
| Preamp Off | Attenuation : 10 dB; Reference: 160 MHz; 20 ~ 30°C | |
| 100 kHz ~ 2.0 GHz | $\pm 0.5 \text{ dB}$ | |
| 2 GHz ~ 3 GHz | $\pm 0.7 \text{ dB}$ | |
| Preamp On | Attenuation: 0 dB; Reference: 160 MHz; 20 ~ 30°C | |
| 1 MHz ~ 2 GHz | $\pm 0.6 \text{ dB}$ | |
| 2 GHz ~ 3 GHz | $\pm 0.8 \text{ dB}$ | |

ATTENUATION SWITCHING UNCERTAINTY

| | | |
|--------------------|------------------------|---------------------------------------|
| Attenuator Setting | 0 ~ 50 dB in 1 dB step | |
| Uncertainty | $\pm 0.25 \text{ dB}$ | Reference : 160 MHz, 10dB attenuation |

RBW FILTER SWITCHING UNCERTAINTY

| | | |
|--------------|-----------------------|------------------------|
| 1 Hz ~ 1 MHz | $\pm 0.25 \text{ dB}$ | Reference : 10 kHz RBW |
|--------------|-----------------------|------------------------|

LEVEL MEASUREMENT UNCERTAINTY

| | | |
|----------------------------|----------------------|--|
| Overall Amplitude Accuracy | $\pm 1.5 \text{ dB}$ | 20 ~ 30°C; frequency $> 1 \text{ MHz}$; Signal input 0 ~ -50 dBm; Reference level 0 ~ -50 dBm; Input attenuation 10 dB; RBW 1 kHz; VBW 1 kHz; after cal; Preamp Off |
| | $\pm 0.5 \text{ dB}$ | Typical |

SPURIOUS RESPONSE

| | | |
|---|---|---|
| Second Harmonic Intercept | +35 dBm +60 dBm | Preamp off; signal input -30dBm; 0 dB attenuation Typical; 10 MHz $< f_c < 775 \text{ MHz}$ Typical; 775 MHz $\leq f_c < 1.625 \text{ GHz}$ |
| Third-order Intercept | | Preamp off; signal input -30dBm; 0 dB attenuation 300 MHz ~ 3 GHz |
| Input Related Spurious Residual Response (Inherent) | $> 1 \text{ dBm}$ $< -60 \text{ dBc}$ $< -90 \text{ dBm}$ | Input signal level -30 dBm, Att. Mode, Att = 0dB; 20 ~ 30°C Input terminated; 0 dB attenuation; Preamp off |

SPECIFICATIONS

| | | |
|--|--|---|
| SWEEP | | |
| SWEEP TIME | | |
| Range | 204 μ s ~ 1000 s 50 μ s ~ 1000 s | Span > 0 Hz Span = 0 Hz; Min resolution = 10 μ s |
| Sweep Mode | Continuous; Single | |
| Trigger Source | Free run; Video; External | |
| Trigger Slope | Positive or negative edge | |
| RF PREAMPLIFIER | | |
| Frequency Range | 1 MHz ~ 3 GHz | |
| Gain | 18 dB | Nominal (installed as standard) |
| FRONT PANEL INPUT/OUTPUT | | |
| RF INPUT | | |
| Connector Type | N-type female | |
| Impedance | 50 Ω | Nominal |
| VSWR | <1.6:1 | 300 kHz ~ 3 GHz; Input attenuator \geq 10 dB |
| POWER FOR OPTION | | |
| Connector Type | SMB male | |
| Voltage/Current | DC +7V/500 mA max | With short-circuit protection |
| USB HOST | | |
| Connector Type | A plug | |
| Protocol | Version 2.0 | Support Full/High/Low speed |
| MICRO SD SOCKET | | |
| Protocol | SD 1.1 | |
| Support Cards | Micro SD, Micro SDHC | Up to 32GB capacity |
| REAR PANEL INPUT/OUTPUT | | |
| REFERENCE OUTPUT | | |
| Connector Type | BNC female | |
| Output Frequency | 10 MHz | Nominal |
| Output Amplitude | 3.3V CMOS | |
| Output Impedance | 50 Ω | |
| REFERENCE INPUT | | |
| Connector Type | BNC female | |
| Input Reference Frequency | 10 MHz | |
| Input Amplitude | -5 dBm ~ +10 dBm | |
| Frequency Lock Range | Within \pm 5 ppm of the input reference frequency | |
| ALARM OUTPUT | | |
| Connector Type | BNC female | Open-collector |
| TRIGGER INPUT/GATED SWEEP INPUT | | |
| Connector Type | BNC female | |
| Input Amplitude | 3.3V CMOS | |
| Switch | Auto selection by function | |
| LAN TCP/IP INTERFACE | | |
| Connector Type | RJ-45 | |
| Base | 10Base-T; 100Base-Tx; Auto-MDIX | |
| USB DEVICE | | |
| Connector Type | B plug | |
| Protocol | Version 2.0 | For remote control only; supports USB TMC Supports Full/High/Low speed |
| IF OUTPUT | | |
| Connector Type | SMA female | |
| Impedance | 50 Ω | Nominal |
| IF Frequency | 886 MHz | Nominal |
| Output Level | -25 dBm | 10 dB attenuation; RF input : 0 dBm @ 1 GHz |
| EARPHONE OUTPUT | | |
| Connector Type | 3.5mm stereo jack, wired for mono operation | |
| VIDEO OUTPUT | | |
| Connector Type | DVI-I (integrated analog and digital), Single Link. Compatible with VGA or HDMI standard through adapter | |
| RS-232C INTERFACE | | |
| Connector Type | D-sub 9-pin female | Tx, Rx, RTS, CTS |
| GPIB INTERFACE (OPTIONAL) | | |
| Connector Type | IEEE-488 bus connector | |
| AC POWER INPUT | | |
| Power Source | AC 100 V ~ 240 V, 50/60 Hz | Auto range selection |
| BATTERY PACK (OPTIONAL) | | |
| Battery Pack | 6 cells, Li-Ion rechargeable, 3S2P | |
| Voltage | DC 10.8 V | With UN38.3 Certification |
| Capacity | 5200 mAh/56Wh | |
| GENERAL | | |
| Internal Data Storage | 16 MB nominal | |
| Power Consumption | < 65 W | |
| Warm-up Time | < 30 minutes | |
| Temperature Range | +5 $^{\circ}$ C ~ + 45 $^{\circ}$ C -20 $^{\circ}$ C ~ + 70 $^{\circ}$ C | Operating Storage |
| Dimensions & Weight | 350(W) x 210(H) x 100(D) mm, Approx. 4.5kg 13.8(W) x 8.3(H) x 3.9(D) inch, Approx. 9.9lb | Inc. all options (Basic + TG + GPIB + Battery) |
| TRACKING GENERATOR (OPTIONAL) | | |
| Frequency Range | 100 kHz ~ 3 GHz | |
| Output Power | -50 dBm ~ 0 dBm in 0.5 dB steps | |
| Connector Type | N-type female | 50 Ω Nominal |
| Output VSWR | < 1.6 : 1 | 300 kHz ~ 3 GHz, source attenuation \geq 12 dB |

Note : The specifications apply when the GSP-9300B is powered on for at least 30 minutes to warm-up to a temperature of 20 $^{\circ}$ C to 30 $^{\circ}$ C, unless specified otherwise.

Specifications subject to change without notice. GSP-9300BGD1DH

ORDERING INFORMATION

GSP-9300B 3 GHz Spectrum Analyzer

EMC Pretest Solution : **GKT-008** EMI Near Field Probe Set
GLN-5040A Line Impedance Stabilization Network
GIT-5060 Isolation transformer
GPL-5010 Transient Limiter

ACCESSORIES :

Power Cord, Certificate of Calibration, CD-ROM (with Quick Start Guide, User Manual, Programming Manual, SpectrumShot Software, SpectrumShot Guide & IVI Driver)

OPTIONS

Opt.01 Tracking Generator
Opt.02 Battery Pack

Opt.03 GPIB Interface

OPTIONAL ACCESSORIES

GSC-009 Soft Carrying Case
GRA-415 Rack Adapter Panel

FREE DOWNLOAD

SpectrumShot PC Software for Windows System (available on GW Instek website)
IVI Driver Supports LabVIEW/LabWindows/CVI Programming (available on NI website)

Global Headquarters
GOOD WILL INSTRUMENT CO., LTD.
T +886-2-2268-0389 F +886-2-2268-0639

China Subsidiary
GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.
T +86-512-6661-7177 F +86-512-6661-7277

Malaysia Subsidiary
GOOD WILL INSTRUMENT (M) SDN. BHD.
T +604-6111122 F +604-6115225

Europe Subsidiary
GOOD WILL INSTRUMENT EURO B.V.
T +31(0)40-2557790 F +31(0)40-2541194

U.S.A. Subsidiary
INSTEK AMERICA CORP.
T +1-909-399-3535 F +1-909-399-0819

Japan Subsidiary
TEXIO TECHNOLOGY CORPORATION.
T +81-45-620-2305 F +81-45-534-7181

Korea Subsidiary
GOOD WILL INSTRUMENT KOREA CO., LTD.
T +82-2-3439-2205 F +82-2-3439-2207

GW INSTEK

Simply Reliable



www.gwinstek.com

www.facebook.com/GWInstek

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [GW Connect](#) manufacturer:

Other Similar products are found below :

[93601-0203](#) [93601-2956](#) [93601-4227](#) [93604-0103](#) [93604-0109](#) [GDS-2072A](#) [GDS-2202E](#) [GPS-3303](#) [GPT-9603](#) [PSW 160-7.2](#) [PSW 80-13.5](#)
[GSP-730](#) [AFG-2105](#) [93600-0224](#) [93603-0066](#) [AFG-2025](#) [GAG-810](#) [GDM-8342 USB](#) [GDP-100](#) [GDS-1054B](#) [GDS-1104B](#) [GDS-2104A](#)
[GDS-3152](#) [GPD-3303S](#) [GPE-3323](#) [GPT-9602](#) [PPH-1503](#) [PSP-405](#) [PSW 160-14.4](#) [PSW 80-27](#) [GTL-115](#) [GTP-251R](#) [SPD-3606](#) [GDS-](#)
[1152A-U](#) [7803.6208.0](#) [PSW 30-72](#) [GAG-809](#) [GFG-3015 + RS232](#) [GPM-001](#) [LCR-6200](#) [MDO-2072EG](#) [MDO-2072EX](#) [MDO-2074EX](#)
[MDO-2102EG](#) [MDO-2102EX](#) [MDO-2104EX](#) [MDO-2204EG](#) [MSO-2102E](#) [MSO-2102EA](#) [MSO-2104EA](#)