

# Linear D.C. Power Supply



GPS-1830D/1850D/3030D



GPS-3030



GPS-3030DD



## FEATURES

- \* Light and Compact Design
- \* 0.01% High Regulation
- \* Constant Voltage and Constant Current Operation
- \* Remote Control for External Programmability
- \* Internal Select for Continuous or Dynamic Load
- \* Low Ripple and Noise
- \* Overload and Reverse Polarity Protection
- \* Series or Parallel Operation
- \* Optional European Type Jack Terminal for GPS-3030/GPS-3030D/GPS-3030DD

## European Type Jack Terminal



The GPS-Series is single output, 54W to 90W, linear DC power supplies. The GPS-Series includes both analog and digital display meters with varying power outputs. The GPS-Series features overload and reverse polarity protection as well as high regulation and low ripple/noise that are maintained at 0.01% and < 1mVrms, respectively. Continuous or dynamic internal load selection accommodates applications such as pulsed current. Remote control terminals offer programming and operation from an external device.

SPECIFICATIONS	
<b>CONSTANT VOLTAGE OPERATION</b>	
<b>Regulation</b>	Line regulation $\leq 0.01\% + 3mV$ Load regulation $\leq 0.01\% + 3mV$ (rating current $\leq 3A$ ) $\leq 0.01\% + 5mV$ (rating current $> 3A$ )
<b>Ripple &amp; Noise</b>	$\leq 0.5mVrms$ 5Hz ~ 1MHz (rating current $\leq 3A$ ) $\leq 1mVrms$ 5Hz ~ 1MHz (rating current $> 3A$ )
<b>Recovery Time</b>	$\leq 100\mu S$ (50% load change, minimum load 0.5A)
<b>Temp. Coefficient</b>	$\leq 300 ppm / ^\circ C$
<b>Output Range</b>	0 to rating voltage continuously adjustable
<b>CONSTANT CURRENT OPERATION</b>	
<b>Regulation</b>	Line regulation $\leq 0.2\% + 3mA$ Load regulation $\leq 0.2\% + 3mA$
<b>Ripple Current</b>	$\leq 3mA_{rms}$
<b>Output Range</b>	0 to rating current continuously adjustable (Hi / Lo range switchable)
<b>METER</b>	
<b>Analog</b>	V-meter and I-meter 2.5 class Dimensions 50 x 50 mm
<b>Digital</b>	3 1/2 digits 0.5" LED display (GPS-1830D/1850D/3030D) 3 1/2 digits 0.39" LED display (GPS-3030DD) Accuracy $\pm (0.5\% \text{ of rdg} + 2 \text{ digits})$
<b>INSULATION</b>	
<b>Chassis and Terminal</b>	20M $\Omega$ or above (DC 500V)
<b>Chassis and AC Cord</b>	30M $\Omega$ or above (DC 500V)
<b>POWER SOURCE</b>	
AC 100V/120V/220V/240V $\pm 10\%$ , 50/60Hz	
<b>DIMENSIONS</b>	
128(W) x 145(H) x 285(D) mm	

ORDERING INFORMATION					
	Model	Output Volts(V)	Output Amps(A)	Weight (kg)	
	GPS-3030	90W D.C. Power Supply	0 ~ 30	0 ~ 3	5
	GPS-1830D	54W D.C. Power Supply	0 ~ 18	0 ~ 3	4
	GPS-1850D	90W D.C. Power Supply	0 ~ 18	0 ~ 5	5
	GPS-3030D	90W D.C. Power Supply	0 ~ 30	0 ~ 3	5
	GPS-3030DD	90W D.C. Power Supply	0 ~ 30	0 ~ 3	5
ACCESSORIES :					
User manual x 1 , Power cord x 1					
Test lead GTL-105A x 1 ( $\leq 3A$ ) or GTL-104A x 1 ( $\leq 10A$ )					
European test lead GTL-203A x 1 ( $\leq 3A$ ) or GTL-204A x 1 ( $\leq 10A$ )					

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Switching Power Supplies](#) category:*

*Click to view products by [GW INSTEK](#) manufacturer:*

Other Similar products are found below :

[70841011](#) [73-551-0005](#) [73-551-0048](#) [EVS57-5R3/A](#) [PS3E-B12F](#) [PS3E-E12F](#) [AAD600S-4-OP](#) [R22095](#) [KD0204](#) [9021](#) [LDIN100150](#)  
[LPM000-BBAR-01](#) [LPX17S-C](#) [EVS57-10R6/R](#) [FP80](#) [FRV7000G](#) [22929](#) [PS3E-F12F](#) [CQM1IA121](#) [40370121900](#) [VI-PU22-EXX](#)  
[40370121910](#) [LDIN5075](#) [LPM615-CHAS](#) [LPX140-C](#) [09-160CFG](#) [70841025](#) [VPX3000-CBL-DC](#) [VI-LUL-IU](#) [LPM000-BBAR-05](#) [LPM000-](#)  
[BBAR-08](#) [LPM124-OUTA1-48](#) [LPM000-BBAR-07](#) [LPM109-OUTA1-10](#) [LPM616-CHAS](#) [08-30466-1055G](#) [08-30466-2175G](#) [08-30466-](#)  
[2125G](#) [DMB-EWG](#) [TVQF-1219-18S](#) [6504-226-2101](#) [CQM1IPS01](#) [SP-300-5](#) [CQM1-IPS02](#) [VI-MUL-ES](#) [22829](#) [08-30466-0065G](#) [VI-](#)  
[RU031-EWWX](#) [08-30466-0028G](#) [VP-C2104853](#)