

The Smarter way to Characterize Components



NEW



LCR-8200 Series


High Frequency LCR Meter

- Wide Test Frequency 10Hz ~ 30MHz/20MHz/10MHz/5MHz/1MHz
- 7" LCD color Display
- 0.08% Basic Accuracy
- Displaying Four Measurement Results Simultaneously From 17 Selectable Measurement Parameters Freely
- 15 Steps List Measurement
- Two Curves Sweep Mode
- Internal DC Bias Voltage $\pm 12V$
- USB Storage Available
- ALC Function Available
- Standard Interfaces : RS-232C, USB Host/Device, LAN, GPIB and Handler
- Universal Power Input



Diverse Meas. Item & Display

Four Displayed items can be selected from 17 measurement parameters freely



Two Curves Graphic

7" color display, under graphic mode is capable to display two parameters sweep curve

www.gwinstek.com

GW INSTEK
Simply Reliable

SPECIFICATIONS					
	LCR-8230	LCR-8220	LCR-8210	LCR-8205	LCR-8201
TEST FREQUENCY	DC, 10Hz~30MHz; 6 Digits, $\pm 0.0007\%$	DC, 10Hz~20MHz; 6 Digits, $\pm 0.0007\%$	DC, 10Hz~10MHz; 6 Digits, $\pm 0.0007\%$	DC, 10Hz~5MHz; 6 Digits, $\pm 0.0007\%$	DC, 10Hz~1MHz; 6 Digits, $\pm 0.0007\%$
OUTPUT IMPEDANCE	25 Ω / 100 Ω SELECTABLE				
BASIC ACCURACY	$\pm 0.08\%$				
TEST SPEED	MAX: 2.5ms(>10kHz), FAST: 50ms(>20Hz), MEDIUM: 100ms SLOW: 300ms, SLOW2: 600ms				
TEST SIGNAL LEVEL	AC Voltage 10mV ~ 2Vrms (FREQ. ≤ 1 MHz), 10mV ~ 1Vrms (FREQ. > 1MHz or FREQ. ≤ 1 MHz and RO=25 Ω) AC Current 100 μ A ~ 20mA rms (RO=100 Ω), 400 μ A ~ 40mA rms (RO=25 Ω) DCR Voltage 1Vdc (40mA max.)				
MEASUREMENT PARAMETERS	Maximum four parameters can be measured and displayed at the same time Impedance (Z), Inductance (Ls / Lp), Capacitance (Cs / Cp), AC Resistance (Rs / Rp), Quality Factor (Q), Dissipation Factor (D), Admittance (Y), Conductance (G), Reactance (X), Phase Angle ($\theta d / \theta r$), Susceptance (B), DC Resistance (Rdc)				
LIST MEASUREMENT	Listed Steps 15 Listed Parameters Freq/Vac/Iac/DC Bias/Comp/BIN Trigger AUTO, REPEAT, SINGLE				
SWEEP MEASUREMENT	Swept Graphical Two of measurement parameters Swept Parameters Freq/Vac/Iac, Keep Trace				
OTHER FUNCTIONS	Auto Level Control (ALC) Standard DC Bias 0 ~ ± 12 V Handler PASS, FAIL and OK, NG or BIN 1-9				
OTHER FEATURES	Correction Open/Short/HF Load/Load V/I Monitor Vac, Iac, Vdc, Idc Comparator Value, Δ , $\Delta\%$ Buzzer OFF, Pass, Fail Average 1 to 64				
DISPLAY	7" LCD color display (800 x 480)				
INTERFACE	USB/GPIB/LAN/RS-232/Handler/USB Host/TRIGGER Input				
POWER SOURCE	AC 100V~240V, 50/60Hz; Consumption: 65VA (max.)				
DIMENSIONS & WEIGHT	346 (W) x 145 (H) x 335 (D) mm; Approx. 3.3kg				

Specifications subject to change without notice. LCR-8000CD1DS

ORDERING INFORMATION	OPTION ASSESSORIES
LCR-8230 DC, 10Hz~30MHz High Frequency LCR Meter LCR-8220 DC, 10Hz~20MHz High Frequency LCR Meter LCR-8210 DC, 10Hz~10MHz High Frequency LCR Meter LCR-8205 DC, 10Hz~5MHz High Frequency LCR Meter LCR-8201 DC, 10Hz~1MHz High Frequency LCR Meter	<p>LCR-05A Test Fixture for Axial & Radial Lead Components (up to 30MHz)</p> <p>LCR-06B Test Lead with Kelvin clip(4 wire type)</p> <p>LCR-07 Test Lead with Alligator clip(2 wire type)</p> <p>LCR-08 Test Fixture(Tweezers) for SMD/Chip Components</p> <p>LCR-10A Test Fixture for Bottom Electrode Components(up to 30MHz)</p> <p>LCR-12 Test Lead with Kelvin clip(4 wire type)</p> <p>LCR-15A Test Fixture for SMD/Chip components (up to 30MHz)</p> <p>GTL-234 RS-232C cable</p> <p>GTL-248 GPIB Cable</p> <p>GTL-246 USB Cable</p> <p>LCR-DB1 External DC Bias Voltage Box</p>
ACCESSORIES	FREE DOWNLOAD
User Manual (CD) x 1, AC Power Cord x 1, Test Fixture LCR-06B x 1, Safety Sheet x 1	PC Software LCR Meter



GOOD WILL INSTRUMENT CO., LTD.
No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
T +886-2-2268-0389 F +886-2-2268-0639
E-mail: marketing@goodwill.com.tw



GW INSTEK
Simply Reliable

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Component Testers](#) category:

Click to view products by [GW INSTRON](#) manufacturer:

Other Similar products are found below :

[410-413](#) [FLUKE 9062](#) [BK894](#) [BK895](#) [BK880](#) [2841](#) [BK2840](#) [BK2841](#) [BK830C](#) [C.A 6608](#) [C.A 6609](#) [815](#) [FLUKE-9040EUR](#) [881](#) [894](#)
[AK57X](#) [35121](#) [770734](#) [ET30A](#) [LCR200](#) [LCR203](#) [PRT200](#) [UM200](#) [T5-H5-1AC-KIT/US](#) [SRL-10](#) [VT-1100](#) [69127](#) [RT310](#) [LCR-900-OPT1](#)
[35100](#) [35130](#) [P 2170](#) [P 2175](#) [P 2180](#) [P 3705](#) [P 3710](#) [P 3730](#) [VS-AVT-C02-L03](#) [VS-AVT-C08-L10E](#) [1212598](#) [PRM-5](#) [T3LCR1002](#)
[T3LCR1300](#) [T3LCR1100](#) [VS-AVT-RKBB2](#) [VS-AVT-RKBB3](#) [VS-AVT-RKBB4](#) [NCVT-4IR](#) [LCR55A](#) [ET30B](#)