




Quality Products. Service Excellence.

Studio Grade Impedance Matching Transformers 1140 Series

Features



- Designed with Nickel alloy cores for high performance and Wide Bandwidth
- Frequency Response: 20 Hz – 20 kHz ± 0.35 dB, (ref. @ 1 kHz)
- Low distortion at levels up to +27 dBu @ 20 Hz.
- Excellent Shielding – Mu Metal enclosures
- Line Output Transformers are open style (not Mu Metal)



Microphone Input Transformers

Part No.	Impedance Ratio	Turns Ratio	Max Input @ 20Hz	THD @ 20Hz	Frequency Response 20Hz / 20kHz
1140-MN-A	150:15K	1:10	-2.5 dBu	0.02%	-0.05 dB/ -0.06 dB
1140-MN-B	150: 3.8K	1:5	+7.0dBu	0.015%	-0.04 dB/ +0.00 dB

Microphone Splitter Transformers

Part No.	Impedance Ratio	Turns Ratio	Max Input @ 20Hz	THD @ 20Hz	Frequency Response 20Hz / 20kHz
1140-MS-A	150:150	1:1	+2.0 dBu	0.05%	-0.14 dB/-0.06 dB
1140-MS-B	150:150:150	1:1	+2.0 dBu	0.030%	-0.08 dB/+0.06 dB
1140-MS-C	150:150:150:150	1:1:1:1	+11 dBu	0.030%	-0.05 dB/+0.20 dB

Line Input Transformers

Part No.	Impedance Ratio	Turns Ratio	Max Input @ 20Hz	THD @ 20Hz	Frequency Response 20Hz / 20kHz
1140-LN-A	10k:20k	1:4	+16 dBu	0.02%	-0.04 dB/+0.10 dB
1140-LN-B	10K:10K	1:1	+20 dBu	0.020%	-0.03 dB/+0.10 dB
1140-LN-C	36K:2.2K / 10K:600	4:1	+26 dBu	0.015%	-0.20 dB/+0.05 dB
1140-LN-D	40K:2.4K	4:1	+21 dBu	0.060%	-0.12 dB/+0.06 dB
1140-LN-E	600:600	1:1	+19 dBu	0.020%	-0.06 dB/+0.00 dB

Line Output Transformers

Part No.	Impedance Ratio	Turns Ratio	Max Input @ 20Hz	THD @ 20Hz	Frequency Response 20Hz / 20kHz
1140-LU-A	10K:600	4:1	+23 dBu	0.00%	-0.06 dB/+0.04 dB
1140-LU-B	600:600	1:1	+21 dBu	0.150%	-0.20 dB/+0.03 dB
1140-LU-C	600:600	1:1	+18 dBu	0.001%	-0.05 dB/+0.02 dB
1140-LU-D	600:600	1:1	+24 dBu	0.080%	-0.18 dB/+0.03 dB
1140-LU-E	600:600	1:1	+22 dBu	0.001%	-0.03 dB/+0.02 dB
1140-LU-F	600:150	2:1	+27 dBu	0.001%	-0.01 dB/+0.01 dB
1140-LU-G	600:600	1:1	+27 dBu	0.001%	-0.02 dB/+0.02 dB

open style (not Mu Metal)

Direct Box Transformers

Part No.	Impedance Ratio	Turns Ratio	Max Input @ 20Hz	THD @ 20Hz	Frequency Response 20Hz / 20kHz
1140-DB-A	200K:1.5K	12:1	+22 dBu	0.02%	-0.07 dB/-0.07 dB

Data subject to change without notice

© 2022. Hammond Manufacturing Ltd. All rights reserved.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Audio Transformers](#) / [Signal Transformers](#) category:

Click to view products by [Hammond](#) manufacturer:

Other Similar products are found below :

[CX2041NLT](#) [MGPWT-00449-P](#) [PE-64961](#) [H1302FNLT](#) [H5008FNL](#) [H5012FNL](#) [H5020FNLT](#) [H5077NLT](#) [H5084FNLT](#)
[B78476A9558A003](#) [1812WBT2-4](#) [1879479-1](#) [HX2260FNL](#) [HX5014FNL](#) [EX2024FNL](#) [FL1066](#) [T1137NLT](#) [T3012NL](#) [PE-65812FNL](#) [PE-65848FNLT](#) [H1174FNL](#) [H1302FNL](#) [H5015FNL](#) [H5019EFNL](#) [H5062FNLT](#) [CX2047LNL](#) [MGPWT-00059-P](#) [MGPWT-00266-P](#) [MGPWT-00278-P](#) [MGPWT-00431-P](#) [TTC-100](#) [TTC-143-H](#) [TTC-5032-1](#) [BX1194WNLT](#) [HX1234NLT](#) [HX5008FNLT](#) [HX5019FNL](#) [HX5084NL](#) [3-1879385-5](#) [TX1263NLT](#) [4-1879391-0](#) [P2004NLT](#) [T1142NL](#) [HX6101FNL](#) [HX1148NL](#) [HX5020FNLT](#) [HX5014FNLT](#) [T1124NL](#) [1879732-1](#)
[2-1879391-5](#)