



Silicon Epitaxial Planar Switching Diode

Features

- Small package
- Low forward voltage
- Fast reverse recovery time
- Small total capacitance



Marking Code: **5D**
SOT-23 Plastic Package

Applications

- Ultra high speed switching application

Absolute Maximum Ratings ($T_a = 25\text{ }^\circ\text{C}$)

Parameter	Symbol	Value	Unit	
Repetitive Peak Reverse Voltage	V_{RRM}	85	V	
Continuous Reverse Voltage	V_R	75	V	
Continuous Forward Current	I_F	215	mA	
Repetitive Peak Forward Current	I_{FRM}	500	mA	
Non-Repetitive Peak Forward Surge Current	I_{FSM}	$t = 1\ \mu\text{s}$	4	A
		$t = 1\ \text{ms}$	1	
		$t = 1\ \text{s}$	0.5	
Power Dissipation	P_{tot}	350	mW	
Junction Temperature	T_j	150	$^\circ\text{C}$	
Storage Temperature Range	T_{stg}	- 65 to + 150	$^\circ\text{C}$	

Characteristics at $T_a = 25\text{ }^\circ\text{C}$

Parameter	Symbol	Min.	Max.	Unit	
Forward Voltage	V_F	-	at $I_F = 1\ \text{mA}$	715	mV
			at $I_F = 10\ \text{mA}$	855	mV
			at $I_F = 50\ \text{mA}$	1	V
			at $I_F = 150\ \text{mA}$	1.25	V
Reverse Current	I_R	-	at $V_R = 25\ \text{V}$	30	nA
			at $V_R = 75\ \text{V}$	1	μA
			at $V_R = 25\ \text{V}, T_j = 150\text{ }^\circ\text{C}$	30	μA
			at $V_R = 75\ \text{V}, T_j = 150\text{ }^\circ\text{C}$	50	μA
Reverse Breakdown Voltage	$V_{(BR)R}$	75	-	V	
Diode Capacitance	C_d	-	2	pF	
Reverse Recovery Time	t_{rr}	-	4	ns	




Figure 1. Reverse Voltage vs Reverse Current
BV - 1.0 to 100 uA




Figure 2. Reverse Current vs Reverse Voltage
IR - 10 to 100 V




Figure 3. Forward Voltage vs Forward Current
VF - 1.0 to 100 uA




Figure 4. Forward Voltage vs Forward Current
VF - 0.1 to 10 mA




Figure 5. Forward Voltage vs Forward Current
VF - 10 - 800 mA




Figure 6. Total Capacitance

PACKAGE OUTLINE

Plastic surface mounted package; 3 leads

SOT-23

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Diodes - General Purpose, Power, Switching category:](#)

Click to view products by [Hong Kong Chuangji manufacturer:](#)

Other Similar products are found below :

[MCL4151-TR3](#) [MMBD3004S-13-F](#) [RD0306T-H](#) [1N3611](#) [NTE156A](#) [NTE574](#) [NTE6244](#) [1SS193,LF](#) [1SS400CST2RA](#) [SDAA13](#)
[SHN2D02FUTW1T1G](#) [LS4151GS08](#) [1N4449](#) [1N456A](#) [1N4934-E3/73](#) [1N914BTR](#) [RFUH20TB3S](#) [D291S45T](#) [BAV300-TR](#) [BAW56DWQ-](#)
[7-F](#) [BAW56M3T5G](#) [BAW75-TAP](#) [MM230L-CAA](#) [IDW40E65D1](#) [JAN1N3600](#) [JAN1N4454UR-1](#) [LL4151-GS18](#) [SMMSD4148T3G](#)
[BYW95B/A52A](#) [NSVDAN222T1G](#) [CDSZC01100-HF](#) [LL4150-M-08](#) [1N4454-TR](#) [BAV70HDW-7](#) [BAS28-7](#) [JANTX1N6640](#) [BAW56HDW-](#)
[13](#) [BAS28 TR](#) [VS-HFA04SD60STR-M3](#) [NSVM1MA152WKT1G](#) [1SS388-TP](#) [RGP30D-E3/73](#) [VS-8EWF02S-M3](#) [BAV99TQ-13-F](#)
[BAV99HDW-13](#) [MMDB30-E28X](#) [IDP20C65D2XKSA1](#) [LS4148](#) [IDV15E65D2](#) [NSVM1MA152WAT1G](#)