

## 4-Way Power Splitter K7431358

### Reactive Splitter

### Description

Installation Equipment for Sencity Special Communication Antennas:  
4-Way Splitter 380-512 MHz  
For indoor and outdoor use



### Technical Data

#### Electrical Data

Signal Band 1					
Frequency	0.38 - 0.512 GHz				
Insertion Loss	0.05 dB				
Max. Composite Power	1000 W				
Input 1					
Connector Type	7/16				
Connector Gender	jack (female)				
		Output 1	Output 2	Output 3	Output 4
Connector Type	7/16	7/16	7/16	7/16	7/16
Connector Gender	jack (female)	jack (female)	jack (female)	jack (female)	jack (female)

Char. impedance 50 Ω

VSWR > 1.1

#### Mechanical Data

Dimensions 409 x 82 x 82 mm (Height x Width x Length)

Packing size (mm): 425x93x107

#### Environmental Data

Environmental conditions indoor/outdoor  
2011/65/EU (RoHS - including compliant  
2015/863 and 2017/2102)  
WEEE 2002/96/EC no special marking needed

Material:

Case: Aluminum

Inner conductor: Brass

Mounting:

Bracket for wall mounting included in the scope of supply. For mounting to tubular masts use clamps as listed below (order separately).

#### Related Products

734365 Tension Band 45-125mm

734364 Tension Band 120-140mm

## 4-Way Power Splitter K7431358

### Related Documents

Mounting instruction	DOC-0000871752
Security instruction	DOC-0000278984
Outline drawing	DOU-00397214

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Signal Conditioning](#) category:*

*Click to view products by [Huber & Suhner](#) manufacturer:*

Other Similar products are found below :

[MAPDCC0001](#) [MAPDCC0004](#) [PD0409J5050S2HF](#) [880157](#) [HHS-109-PIN](#) [DC1417J5005AHF](#) [AFS14A30-2185.00-T3](#) [AFS14A35-1591.50-T3](#) [DS-323-PIN](#) [B39321R801H210](#) [1A0220-3](#) [JP510S](#) [LFB212G45SG8C341](#) [LFB322G45SN1A504](#) [LFL182G45TC3B746](#) [SF2159E](#) [30057](#)  
[FM-104-PIN](#) [CER0813B](#) [MAPDCC0005](#) [3A325](#) [40287](#) [41180](#) [ATB3225-75032NCT](#) [BD0810N50100AHF](#) [BD2425J50200AHF](#)  
[C5060J5003AHF](#) [JHS-115-PIN](#) [JP503AS](#) [DC0710J5005AHF](#) [DC2327J5005AHF](#) [DC3338J5005AHF](#) [43020](#) [LFB2H2G60BB1C106](#)  
[LFL15869MTC1B787](#) [X3C19F1-20S](#) [XC3500P-20S](#) [10013-20](#) [SF2194E](#) [CDBLB455KCAX39-B0](#) [TGL2208-SM, EVAL](#) [RF1353C](#)  
[PD0922J5050D2HF](#) [1E1305-3](#) [1F1304-3S](#) [1G1304-30](#) [B0922J7575AHF](#) [2020-6622-20](#) [TP-103-PIN](#) [BD1222J50200AHF](#)