



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
71B® Strip solid wires ¼"; Strip stranded wires 5/16"	1 #14	2 to 3 #18		
	1 #14 w/1 #20 or #22	2 #18 w/1 #20		
	1 to 2 #16	2 #18 w/1 to 2 #22		
	1 #16 w/1 #18	1 #20 w/1 to 4 #22		
	1 #16 w/1 to 2 #20	2 to 4 #20		
	1 #16 w/1 to 3 #22	2 #20 w/1 to 3 #22		
	1 #16 w/1 #20 w/1 #18 or #20	3 #20 w/1 to 2 #22		
	1 #18 str.	4 #20 w/1 #22		
	1 #18 w/1 to 3 #20	2 #22 str.		
	1 #18 w/1 to 4 #22	3 to 4 #22		
1 to 2 #18 w/1 #20 w/1 #22	5 #22 sol			
Model	300 Volt Maximum		600 Volt Maximum	
72B® Strip wires 3/8"; Strip wires #16 and smaller ½"	1 #14 str.	2 #16 w/1 #20 w/1 #22		
	1 #14 w/1 #16	1 #18 str.		
	1 #14 w/1 to 2 #18	1 #18 w/1 to 4 #20 or #22		
	1 #14 w/1 to 3 #20	1 to 2 #18 w/1 #20 w/1 #22		
	1 #14 w/1 to 4 #22	1 #18 str. w/1 #20 str. (Tinned or untinned)		
	1 #16 str.	2 #18 w/1 to 3 #20 or #22		
	1 #16 w/1 to 3 #18	2 to 4 #18		
	1 #16 w/1 #18 w/1 #20	3 #18 w/1 to 2 #20 or #22		
	1 #16 w/1 to 4 #20 or #22	3 to 5 #20		
	1 #16 w/1 #22 w/1 #18 or #20	4 #18 w/1 #20 or #22		
	2 to 3 #16	3 #20 w/1 to 2 #22		
	2 #16 w/1 #18	4 #20 w/1 #22		
2 #16 w/1 to 2 #20	2 #22			
2 #16 w/1 to 3 #22				
Model	300 Volt Maximum		600 Volt Maximum	
73B® Strip wires 5/16"; Strip wires #16 and smaller stranded strip 3/8"	1 #14 w/2 #16	5 #18	1 to 2 #14	1 #16 w/1 #18 w/1 #22
	1 #14 w/1 #16 w/1 #18	1 #18 w/1 #20	1 #14 w/1 to 2 #18	2 #16
	1 #14 w/3 #18	4 #18 w/1 #20 or #22	1 #14 w/1 to 3 #20	2 #18 w/1 to 2 #20 or #22
	1 #14 w/4 #20	3 #18 w/2 #20 or #22	1 #14 w/1 to 3 #22	1 #18 w/2 to 4 #20
	2 #14 w/1 #18	2 #18 w/3 #22	1 #14 w/1 #16 w/1 #18	1 #18 w/ 3 to 4 #22
	2 #14 w/1 to 3 #20 or #22	1 #18 str. w/5 #22 str.	1 #14 w/1 #16	1 #18 str.
	3 to 4 #16	3 to 5 #20	1 #16 str.	3 #18 w/1 #20 or #22
	1 #16 w/4 #18	4 #20 w/1 #22	1 #16 w/1 to 2 #18	2 to 4 #18
	2 #16 w/2 to 3 #18	3 #20 w/1 to 2 #22	1 #16 w/1 to 3 #20 or #22	1 to 2 #18 w/1 #20 w/1 #22
	2 #16 w/3 #20	2 #20 w/2 to 3 #22	2 #16 w/1 to 2 #20	
	3 #16 w/1 #18	1 #20 w/4 #22	2 #16 w/1 to 3 #22	
	3 #16 w/1 to 2 #20 or #22	5 #22	2 #16 w/1 #18	
4 #16 w/1 #20 or #22		1 to 2 #16 w/1 #20 w/1 #22		



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Wire Connectors		
Model	300 Volt Maximum	600 Volt Maximum
74B® Strip wires 3/8"; Strip #16 and smaller 7/16"	1 #10 w/2 #12	1 #8 1 #10 1 to 3 #12 1 to 4 #14 2 to 5 #16 3 to 6 #20 1 #10 w/1 #12 1 #10 w/1 to 2 #14, #16 or #18 1 #10 w/3 to 4 #16 or #18 1 #12 w/1 to 3 #14, #16 or #18 1 #12 w/4 #16 or #18 2 #12 w/1 to 2 #14 2 #12 w/1 to 2 #16 or #18 1 #14 w/1 to 4 #16, #18 or #20 2 #14 w/1 to 3 #16, #18 or #20 3 #14 w/1 to 2 #16 3 #14 w/1 to 2 #18 or #20 4 #14 w/1 #16 or #18 1 #16 w/1 to 4 #18, #20 or #22 2 #16 w/1 to 3 #18, #20 or #22 3 #16 w/1 to 2 #18, #20 or #22 4 #16 w/1 to 2 #18, #20 or #22 1 #18 w/3 to 4 #20 or #22 2 #18 w/3 #20 or #22 1 #10 w/1 #12 w/1 #14 or #16 1 #10 w/1 #12 w/1 or 2 #18
		1 #10 w/1 #14 w/2 #16 1 #10 w/1 #14 w/1 to 3 #18 1 #10 w/2 #14 w/1 #16 1 #10 w/1 #16 w/1 or 2 #18 1 #12 w/1 #14 w/3 #16 1 #12 w/2 #14 w/2 #16 2 #12 w/1 #14 w/1 #16 or #18 2 #12 w/1 #16 w/1 to 2 #18 1 #14 w/1 #16 w/1 to 3 #20 1 #14 w/1 #18 w/1 to 3 #20 2 #14 w/1 #16 w/1 to 2 #18 or #20 2 #14 w/1 #16 w/1 to 3 #22 3 #14 w/1 #16 w/1 #18, #20 or #22 3 #14 w/1 #18 w/1 #20 or #22 1 #16 w/1 #18 w/2 to 3 #20 or #22 1 #16 w/1 #18 w/3 to 4 #22 1 #16 w/2 #20 w/2 #22 2 #16 w/1 #18 w/1 to 2 #20 or #22 3 #16 w/1 #18 w/1 #20 or #22 1 #18 w/2 #20 w/3 #22 2 #18 w/1 #20 w/3 #22 2 to 5 #18



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Wire Connectors		
Model	300 Volt Maximum	600 Volt Maximum
76B® Strip wires #14 and larger 7/16"; strip wires #16 and smaller 1/2"	1 #6 w/1 to 2 #16	1 #6 or #8
	1 #6 w/1 #14	1 #8 w/1 to 3 #16
	1 #6 w/1 #12	1 #8 w/1 to 2 #14
	1 #6 w/1 #14 w/1 to 4 #22	1 #8 w/1 #12
	1 #6 w/1 #14 w/1 to 2 #18	1 #8 w/1 #14 w/1 to 4 #20
	1 #6 w/1 #14 w/1 #16	1 #8 w/1 to 4 #18, #20 or #22
	2 #8 str.	1 #8 w/1 #14 w/1 to 2 #16
	1 #8 w/4 #16	1 #8 w/1 #12 w/1 #16 or #18
	1 #8 w/3 #14	1 to 2 #10
	1 #8 w/2 #12	1 #10 w/1 to 4 #16, #18, #20 or #22
	1 #8 w/1 #10	1 #10 w/5 #16
	1 #8 w/1 #14 w/4 #18	1 #10 w/1 to 3 #14
	1 #8 w/1 #14 w/3 to 4 #16	1 #10 w/1 to 2 #12
	1 #8 w/1 #12 w/1 to 4 #16 or #18	1 #10 w/1 to 2 #20 w/1 to 3 #22
	1 #8 w/1 #12 w/1 to 2 #14	1 #10 w/1 #18 w/1 to 4 #20 or #22
	1 #8 w/2 #12 w/1 to 2 #18	1 #10 w/1 #16 w/1 to 4 #20 or 22
	1 #8 w/2 #12 w/1 #14 to #16	1 #10 w/1 #16 w/1 to 4 #18
	1 #8 w/1 #10 w/1 #12 to #14	1 #10 w/1 #14 w/1 to 4 #18, #20 or #22
	3 #10	1 #10 w/1 #14 w/1 to 4 #16
	1 #10 w/4 #14	1 #10 w/2 #14 w/1 to 2 #16
	1 #10 w/3 #12	1 #10 w/1 #12 w/1 to 4 #18
	1 #10 w/2 #14 w/3 #16	1 #10 w/1 #12 w/1 to 3 #16
	1 #10 w/1 #12 w/4 #16	1 #10 w/1 #12 w/1 to 2 #14
	1 #10 w/1 #12 w/3 to 4 #14	1 #10 w/2 #12 w/1 #16 or #18
	1 #10 w/2 #12 w/2 to 3 #16 or #18	2 #10 w/1 to 3 #18
	1 #10 w/2 #12 w/1 to 2 #14	2 #10 w/2 #16
	2 #10 w/3 #16	2 #10 w/1 #14
	2 #10 w/2 to 3 #14	2 #10 w/1 #16 w/1 #18
	2 #10 w/1 to 2 #12	2 #10 w/1 #14 w/1 #20 or #22
	2 #10 w/1 #16 w/2 to 3 #18	1 to 4 #12
	2 #10 w/1 #14 w/2 to 3 #20 or #22	3 #12 w/1 #18 w/1 to 2 #22 or #22
	2 #10 w/1 #14 w/1 to 3 #18	3 #12 w/1 #16 w/1 to 2 #22 or #20
	2 #10 w/2 #14 w/1 #16	2 #12 w/2 #14 w/1 #16
	2 #10 w/1 #12 w1 to 3 #18	1 #14 w/3 to 4 #18
	2 #10 w/1 #12 w/1 to 2 #16	1 #14 w/2 #20 w/3 #22
	3 #10 w/1 #16 or #18	1 #14 w/1 #18 w/4 #22
	5 #12	1 #14 w/1 #18 w/3 to 4 #20
	2 #12 w/1 #14 w/3 #16	1 #14 w/1 #16 w/2 to 4 #20
	2 #12 w/2 #14 w/2 #16	1 to 2 #14 w/1 #16 w/1 to 3 #18
	3 #12 w/2 #14	2 #14 w/2 to 4 #16
	3 #12 w/3 #16	2 #14 w/1 to 2 #20 w/1 to 2 #22
	3 #12 w/1 #16 w/2 #18	2 #14 w/1 #18 w/1 to 3 #20 or #22
	3 #12 w/1 #14 w/1 to 2 #16	2 #14 w/1 #16 w/1 to 3 #20 or #22
	3 #12 w/1 #14 w/1 #18	3 #14 w/1 to 2 #16, #18, #20 or #22
	3 #12 w/2 #14 w/1 #16	3 #14 w/1 #18 w/1 to 2 #20 or #22
	4 #12 w/1 #14, #16, #18, #20 or #22	2 #12 w/1 to 3 #14
	1 #12 w/3 to 4 #22	
	1 #12 w/2 to 4 #18 or #20	
	1 #12 w/1 to 4 #14 or #16	
	1 #12 w/1 #20 w/2 to 4 #22	
	2 #12 w/1 #14 w/1 to 3 #20 or #22	
	1 #12 w/ #18 w/1 to 4 #20 or #22	
	1 #12 w/1 #16 w/1 to 4 #20 or #22	
	1 #12 w/1 #16 w/1 to 4 #18	
	1 #12 w/1 #14 w/1 to 4 #16, #18, #20 or #22	
	1 #12 w/2 #14 w/1 to 3 #16	
	2 #12 w/1 to 3 #20 or #22	
	2 #12 w/1 to 2 #16 or #18	
	2 #12 w/1 to 2 #20 w/1 to 2 #22	
	2 #12 w/1 #18 w/1 to 3 #20 or #22	
	2 #12 w/1 #16 w/1 to 3 #20 or #22	
	2 #12 w/1 #16 w/1 to 3 #18	
	2 to 5 #14	
	4 to 6 #16	
	2 #12 w/1 #14 w/1 to 3 #18 or #16	
	3 #12 w/1 #16 w/1 to 2 #18	
	3 #12 w/1 #14	
	3 #12 w/1 #14 w/1 #20	
	3 #12 w/1 #14 w/1 to 2 #22	
	3 #12 w/1 #14 w/1 #18	
	3 #12 w/1 to 2 #20 or #22	
	3 #12 w/1 to 3 #18	
	3 #12 w/1 to 2 #16	
	3 #12 w/1 #20 w/1 to 2 #22	
	3 #12 w/2 #20 w/1 #22	
	3 #14 w/1 #16 w/1 to 2 #18	
	4 #14 w/1 #18, #20 or #22	
	4 #14 w/2 #18	
	4 #14 w/1 #16	
	5 #14 w/1 #18	
	1 #16 w/4 #18	
	2 #16 w/3 #20	
	2 #16 w/3 to 4 #18	
	2 #16 w/1 #20 w/3 #22	
	2 #16 w/2 #20 w/2 #22	
	2 #16 w/1 #18 w/3 #22	
	2 #16 w/1 #18 w/2 to 3 #20	
	3 #16 w/1 to 2 #18, #20 or #22	
	3 #16 w/1 to 2 #20 w/1 #22	
	3 #16 w/1 #18 w/1 to 2 #20 or #22	
	4 #16 w/1 to 2 #22	
	4 #16 w/1 #18 or #20	
	4 to 5 #16 w/1 #22	



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Connectors				
Model	600 Volt Maximum			
59B® Strip wires 1/2"	1 #12 1 #12 w/1 to 3 #18 1 #12 w/1 to 2 #16 1 #12 w/1 #14 1 to 3 #14 1 #14 w/1 to 5 #18, #20 or #22 1 #14 w/1 to 3 #16 1 #14 w/1 #20 w/1 to 2 #22 1 #14 w/1 #18 w/1 to 2 #22 1 #14 w/1 #16 w/1 #20 or #22 2 #14 w/1 to 4 #20 or #22 2 #14 w/1 to 2 #18	2 #14 w/1 #16 2 #14 w/1 #20 w/1 to 2 #22 2 #14 w/1 #18 w/1 to 2 #22 2 #14 w/1 #16 w/1 #20 or #22 1 #16 Stranded OR 1#18 Str. 2 to 4 #16 1 #16 w/1 to 5 #18, #20 or #22 1 #16 w/1 #20 w/1 to 2 #22 1 #16 w/1 #18 w/1 to 2 #22 2 #16 w/1 to 4 #18, #20 or #22 2 #16 w/1 #20 w/1 to 2 #22 2 #16 w/1 #18 w/1 to 2 #22	3 #16 w/1 to 3 #20 or #22 3 #16 w/1 to 2 #18 3 #16 w/1 #20 w/1 to 2 #22 3 #16 w/1 #18 w/1 to 2 #22 4 #16 w/1 to 2 #22 4 #16 w/1 #18 or #20 4 #16 w/1 #20 w/1 #22 2 to 6 #18 3 #18 w/1 to 3 #20 or #22 3 #18 w/1 #20 w/1 to 2 #22 4 #18 w/1 to 2 #22 or #20 4 #18 w/1 #20	5 #18 w/1 #20 w/1 #22 1 #18 w/1 to 4 #20 or #22 1 #18 w/1 #20 w/1 to 2 #22 2 #18 w/1 to 4 #20 or #22 2 #18 w/1 #20 w/1 to 2 #22 2 to 6 #20 1 #20 w/2 to 5 #22 2 #20 w/1 to 4 #22 3 #20 w/1 to 3 #22 4 #20 w/1 to 2 #22 5 #20 w/1 #22 4 to 6 #22
IDEAL Wing-Nut® Wire Connectors				
Model	600 Volt Maximum			
451® Strip wires 3/8"	1 #10 1 #10 w/1 #12 1 #10 w/1 to 2 #14 1 #10 w/1 to 2 #16 1 #10 w/1 to 3 #18 1 to 3 #12 1 #12 w/1 to 5 #18	1 #12 w/1 to 3 #16 1 #12 w/1 to 2 #14 2 #12 w/1 to 2 #18 2 #12 w/1 #16 2 #12 w/1 #14 1 to 3 #14 1 #14 w/1 to 5 #18	1 #14 w/1 to 4 #16 2 #14 w/1 to 3 #18 2 #14 w/1 to 3 #16 3 #14 w/1 #16 3 #14 w/1 to 2 #18 2 to 4 #16 1 #16 w/1 to 5 #18	2 #16 w/1 to 4 #18 3 #16 w/1 to 3 #18 4 #16 w/1 to 2 #18 2 to 4 #18
Model	600 Volt Maximum			
452® & 344® Twister® Strip wires 1/2"	1 #6 1 to 2 #8 1 to 4 #10 1 to 5 #12 1 to 6 #14, #16 2 to 6 #18 3 to 6 #20 4 to 6 #22 1 #6 w/1 to 2 #12 1 #6 w/1 #10 1 #6 w/2 #14 w/1 to 2 #16 1 #6 w/1 #12 w/1 to 2 #14 1 #6 w/2 #12 w/1 #18 1 #6 w/1 #10 w/1 #14 1 #8 w/1 to 5 #16 1 #8 w/1 to 4 #14 1 #8 w/1 to 3 #12 1 #8 w/2 #12 w/1 to 2 #14 1 #8 w/1 to 2 #10 1 #8 w/1 #10 w/1 to 2 #14, #12 1 #8 w/2 #10 w/1 #14 1 #10 w/1 to 5 #18, #16 or #14 1 #10 w/1 or 4 #12 1 #10 w/1 #16 w/1 to 4 #18 1 #10 w/1 #14 w/1 to 4 #16 or #18 1 #10 w/2 #14 w/1 to 3 #16 1 #10 w/1 #12 w/1 to 4 #14 1 #10 w/1 #12 w/1 to 4 #16 or #18	1 #10 w/2 #12 w/1 to 3 #16 1 #10 w/2 #12 w/1 to 3 #18 1 #10 w/2 #12 w/1 to 2 #14 1 #10 w/3 #12 w/1 #14 2 #10 w/1 to 4 #18 or #16 2 #10 w/1 to 3 #14 or #12 2 #10 w/1 #16 w/1 to 3 #18 2 #10 w/2 #14 w/1 to 2 #16 2 #10 w/1 #12 w/1 to 3 #16 2 #10 w/1 #12 w/1 to 2 #14 2 #10 w/2 #12 w/1 to 2 #18 2 #10 w/2 #12 w/1 to 2 #16 2 #10 w/2 #12 w/1 #14 3 #10 w/1 to 3 #18 3 #10 w/1 to 3 #16 3 #10 w/1 to 2 #14 3 #10 w/1 #12 3 #10 w/1 #16 w/1 to 2 #18 3 #10 w/1 #14 w/1 to 2 #18 3 #10 w/1 #14 w/1 #16 3 #10 w/1 #12 w/1 #18 3 #10 w/1 #12 w/1 #16 1 #12 w/1 to 5 #18, #16 or #14 1 #12 w/1 #16 w/1 to 3 #18 2 #12 w/1 #16 w/1 to 3 #18 1 #12 w/1 #14 w/1 to 3 #18 1 to 2 #12 w/1 #14 w/1 to 3 #16 2 #12 w/1 #14 w/1 to 3 #18 1 #12 w/2 #14 w/1 to 2 #16 2 #12 w/2 #14 w/1 to 2 #16	2 #12 w/1 to 4 #18, #16 or #14 3 #12 w/1 to 3 #18, #16 or #14 3 #12 w/1 #16 w/1 to 2 #18 3 #12 w/1 #14 w/1 to 2 #18 3 #12 w/1 #14 w/1 to 2 #16 3 #12 w/1 #14 w/1 #16 4 #12 w/1 to 2 #16 4 #12 w/1 #14 4 #12 w/1 #16 w/1 #18 4 #12 w/1 #14 w/1 #18 or #16 1 #14 w/1 to 5 #22 or #20 1 #14 w/1 to 5 #18 or #16 1 #14 w/1 #16 w/1 to 3 #18 2 #14 w/1 #16 w/1 to 3 #18 2 #14 w/1 to 4 #22 or #20 2 #14 w/1 to 4 #18 or #16 3 #14 w/1 to 3 #22 or #20 3 #14 w/1 to 3 #18 or #16 3 #14 w/1 #16 w/1 to 2 #18 4 #14 w/1 to 2 #22 4 #14 w/1 to 2 #20, #18 or #16 4 #14 w/1 #16 w/1 #18 5 #14 w/1 #18 or #16 1 #16 w/1 to 5 #22, #20 or #18 1 #16 w/1 #20 w/1 to 2 #22 1 #16 w/2 #20 w/1 to 2 #22 2 #16 w/1 #20 w/1 to 2 #22 2 #16 w/2 #20 w/1 to 2 #22 1 #16 w/1 #18 w/1 to 3 #22 1 #16 w/1 #18 w/1 to 3 #20	2 #16 w/1 #18 w/1 to 3 #22 2 #16 w/1 #18 w/1 to 3 #20 2 #16 w/1 to 4 #22, #22 or #18 3 #16 w/1 to 3 #22, #20 or #18 3 #16 w/1 to 2 #22 w/1 #20 3 #16 w/1 #18 w/1 to 2 #22 3 #16 w/1 #18 w/1 to 2 #20 4 #16 w/1 to 2 #22, #20 or #18 4 #16 w/1 #22 w/1 #20 4 #16 w/1 #18 w/1 #22 4 #16 w/1 #18 w/1 #20 5 #16 w/1 #22, #20 or #18 1 #18 w/1 to 5 #22 or #20 1 #20 w/1 #22 w/1 to 3 #18 1 #20 w/2 #22 w/1 to 3 #18 2 #20 w/1 #22 w/1 to 3 #18 2 #18 w/1 to 4 #22, #20 3 #18 w/1 to 3 #22 or #20 4 #18 w/1 to 2 #22 or #20 5 #18 w/1 #22 or #20 1 #20 w/2 to 5 #22 2 #20 w/1 to 4 #22 3 #20 w/1 to 3 #22 4 #20 w/1 to 2 #22 5 #20 w/1 #22



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wing-Nut® Wire Connectors				
Model	600 Volt Maximum			
454® Strip wires 7/8"	1 to 2 #6	2 #6 w/1 #14 or #12	1 #8 w/1 #12 w/1 to 4 #14	1 #10 w/1 #12 w/1 to 4 #14
	2 to 3 #8	1 #6 w/1 #12 w/1 to 4 #14	1 #8 w/2 #12 w/1 to 3 #14	1 #10 w/2 #12 w/1 to 3 #14
	1 #8 w/1 to 5 #14 or #12	1 #6 w/2 #12 w/1 to 3 #14	1 #8 w/3 #12 w/1 to 2 #14	1 #10 w/3 #12 w/1 to 2 #14
	1 #8 w/1 to 4 #10	1 #6 w/3 #12 w/1 to 2 #14	1 #8 w/4 #12 w/1 #14	1 #10 w/4 #12 w/1 #14
	2 to 5 #10	1 #6 w/4 #12 w/1 #14	1 #8 w/1 #10 w/1 to 4 #14	1 #10 w/2 to 4 #12
	1 #10 w/3 to 5 #14	1 #6 w/1 #10 w/1 to 4 #14	1 #8 w/1 #10 w/1 to 4 #12	2 #10 w/1 #12 w/1 to 3 #14
	3 to 6 #12	1 #6 w/1 #10 w/1 to 3 #12	1 #8 w/2 #10 w/1 to 3 #14	2 #10 w/2 #12 w/1 to 2 #14
	1 #12 w/4 to 5 #14	1 #6 w/2 #10 w/1 to 2 #14	1 #8 w/2 #10 w/1 to 3 #12	2 #10 w/3 #12 w/1 #14
	2 #12 w/2 to 4 #14	1 #6 w/2 #10 w/1 #12	1 #8 w/3 #10 w/1 to 2 #14	2 #10 w/1 to 4 #14 or #12
	3 #12 w/1 to 3 #14	1 #6 w/1 #8 w/1 to 3 #14	1 #8 w/3 #10 w/1 #12	3 #10 w/1 #12 w/1 to 2 #14
	4 #12 w/1 #14	1 #6 w/1 #8 w/1 to 2 #12	2 #8 w/1 #12 w/1 to 3 #14	3 #10 w/2 #12 w/1 #14
	5 or 6 #14	1 #6 w/1 #8 w/1 #10	2 #8 w/2 #12 w/1 to 2 #14	3 #10 w/1 to 3 #14
	1 #6 w/1 to 4 #14	2 #8 w/1 to 4 #14	2 #8 w/3 #12 w/1 #14	3 #10 w/1 to 3 #12
	1 #6 w/1 to 5 #12	2 #8 w/1 to 3 #12	2 #8 w/1 #10 w/1 to 3 #14	4 #10 w/1 #14 w/1 #12
1 #6 w/1 to 3 #10	2 #8 w/1 to 2 #10	2 #8 w/1 #10 w/1 to 2 #12		
1 #6 w/1 to 2 #8	3 #8 w/1 to 2 #14	2 #8 w/2 #10 w/1 #14 sol		
IDEAL Greenie® Grounding Wire Connectors				
Model	600 Volt Maximum			
92® Strip wires 1"	1 #10 w/1 or 2 #12	2 to 4 #12	2 to 4 #14	
	1 #10 w/1 to 3 #14	3 #12 w/1 #14		
	1 #12 w/1 to 3 #14	2 #12 w/1 to 3 #14		
IDEAL Twister® Wire Connectors				
Model	600 Volt Maximum			
340® Strip wires #16 and larger 7/16"; strip wires #16 and smaller 3/8"	2 to 5 #22			
	2 to 5 #20			
	2 to 5 #18			
	2 to 4 #16			
	1 to 3 #12			
	1 #14 w/1 to 5 #18			
	2 #14 w/1 to 3 #18			
1 #12 w/1 to 5 #18				
1 #12 w/1 to 2 #14				
2 #12 w/1 to 2 #18				
2 #12 w/1 #14				
341® Strip wires ½"	1 to 3 #10	1 #16 w/1 to 4 #14 or #12	4 #18 w/1 #10	1 #22 w/1 #20 w/1 to 2 #16
	1 #10 w/1 #8	1 #16 w/1 to 2 #10	5 #18 w/1 #16 or #14	1 #14 w/1 to 2 #12 w/1 #10
	1 to 3 #12	2 #16 w/1 to 4 #14	2 to 6 #20	2 #14 w/1 #12 w/1 #10
	4 #12 sol	2 #16 w/1 to 3 #12	1 #20 w/1 to 4 #18, #16 or #14	1 #16 w/1 #12 w/1 #10
	1 #12 w/1 to 2 #10	2 #16 w/1 to 2 #10	2 #20 w/1 to 3 #18, #16 or #14	2 #16 w/1 #14 w/1 to 2 #12
	1 #12 w/1 #8	3 #16 w/1 to 3 #14	3 #20 w/1 to 2 #18, #16 or #14	2 #16 w/2 #14 w/1 #12
	2 #12 w/1 #10	3 #16 w/1 to 2 #12 or #10	4 #20 w/1 to 2 #18, #16 or #14	2 #16 w/1 #12 w/1 #10
	1 to 5 #14	4 #16 w/1 to 2 #14 or #12	3 to 6 #22	3 #16 w/1 #14 w/1 #12 or #10
	1 #14 sol w/1 to 3 #12	4 #16 w/1 #10	1 #22 sol w/1 #20 sol	4 #16 w/1 #12 w/1 #10
	1 #14 w/1 to 2 #10	5 #16 w/1 #14	1 #22 w/2 to 5 #20	1 #18 w/1 to 4 #16, #14 or #12
	2 #14 w/1 to 2 #12 or #10	2 #18 w/1 to 4 #16 or #14	1 #22 w/1 to 5 #18 or #16	5 #16 sol w/1 #10 sol
	2 #14 w/1 #8	3 #18 w/1 to 3 #12	2 #22 w/1 to 4 #20, #18 or #16	1 #16 w/1 to 2 #14 w/1 #12 or #10
	3 #14 w/1 #12 or #10	2 #18 w/1 to 2 #10	3 #22 w/1 to 3 #20, #18 or #16	2 to 6 #18
	3 #14 w/2 #12	3 #18 w/1 to 3 #16, #14 or #12	#164 #22 w/1 to 2 #20, #18 or #16	1 #18 w/1 to 2 #10
	4 #14 w/1 #12 or #10	3 #18 w/1 to 2 #10	1 #22 w/1 #18 w/1 #16	
	1 to 6 #16	4 #18 w/1 to 2 #16, #14 or #12		



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Twister® Wire Connectors				
Model	600 Volt Maximum			
342® Strip wires 5/8"	1 to 2 #8 1 #8 w/1 #6 2 to 4 #10 1 #10 w/1 to 2 #8 2 #10 w/1 #8 2 to 6 #12 1 #12 w/1 to 2 #10 1 #12 w/3 #10 1 #12 w/1 to 2 #8 1 to 2 #12 w/1 #6 2 #12 w/1 to 2 #10 2 #12 w/1 #8 or #6 2 #12 w/2 #8 3 #12 w/1 #10 or #8 3 #12 w/2 #10 4 #12 w/1 #10	3 to 6 #14 1 #14 w/1 to 4 #12 1 #14 w/1 to 3 #10 1 #14 w/1 to 2 #8 1 to 2 #14 w/1 #6 2 #14 w/1 to 3 #12 2 #14 w/1 to 3 #10 2 #14 w/1 #8 3 #14 w/1 to 3 #12 or #10 3 or 4 #14 w/1 #8 3 #14 w/1 #6 4 #14 w/1 to 2 #12 or #10 4 #14 w/1 #6 5 #14 w/1 #12 or #10 5 #14 w/1 #8 1 #16 w/2 to 5 #14 or #12	1 #16 w/1 to 3 #10 2 #16 w/1 to 4 #14 or #12 2 #16 w/1 to 2 #10 3 #16 w/1 to 3 #14 3 #16 w/1 to 2 #12 or #10 4 #16 w/1 to 2 #14 or #12 4 #16 w/1 #10 3 #18 w/3 #16 or #14 3 #18 w/1 to 2 #12 or #10 4 #18 w/1 to 2 #16, #14 or #12 5 #18 w/1 #16, #14, #12 or #10 1 #12 w/1 #10 w/1 #8 1 #14 w/1 #12 w/1 to 2 #10 1 #14 w/1 #12 w/1 #8 or #6 1 #14 w/2 #12 w/1 to 2 #10 1 #14 w/2 #12 w/1 #8	1 #14 w/3 #12 w/1 #10 1 #14 w/1 #10 w/1 #8 2 #14 w/1 #12 w/1 to 2 #10 2 #14 w/1 #12 w/1 #8 2 #14 w/2 #12 w/1 #10 2 #14 w/1 #10 w/1 #8 3 #14 w/1 #10 w/1 #8 1 #16 w/1 #14 w/1 to 2 #12 2 #16 w/1 #14 w/1 to 2 #12 2 #16 w/2 #14 w/1 #12 or #10 2 #16 w/1 #12 w/1 #10 3 #16 w/1 #14 w/1 to 2 #12 3 #16 w/1 #14 w/1 #10 4 #16 w/1 #14 w/1 #12
IDEAL WeatherProof™ Wire Connectors				
Model	600 Volt Maximum			
61® Strip wires 3/8"; Strip wires #18 and smaller 7/16"	1 or 2 #14 1 #16 Str 2 #16 1 to 4 # 18 Str 2 to 4 #18 Sol 2 to 4 #20 1 #14 with 1 #16 1 #14 w/ 1 #16 w/ 1 #18			
Model	600 Volt Maximum			
62® Strip wires 1/2"	2 to 6 #18 1 to 6 #16 1 to 5 #14 1 to 3 #12	4 #12 solid 1 to 3 #10 1 #18 with 1 to 4 #16, #14, or #12	1 #18 with 1 to 2 #10 2 #18 with 1 to 4 #16 or #14 1 #14 with 1 to 3 #12 1 #14 with 1 to 2 #10	2 #14 with 1 to 2 #12 or #10 1 #12 with 1 #10
Model	600 Volt Maximum			
63® Strip wires 5/8"	3 to 6 #14 2 to 6 #12 2 to 5 #10 1 to 2 #8	1 #16 with 2 to 5 #14 or #12 1 #16 with 1 to 3 #10 1 #14 with 1 to 4 #12 1 #14 with 1 to 3 #10	1 #14 with 1 to 2 #8 1 #12 with 1 to 2 #10 or #8 1 to 2 #12 with 1 #6 3 #12 with 1 #10 or #8	1 #10 with 1 to 2 #8 1 #8 with 1 #6
IDEAL UnderGround™ Wire Connectors				
Model	600 Volt Maximum			
60® Strip wires 1/2"	2 #10 1 to 3 #12 1 #12 w/1 #8 or #10 2 #12 w/1 #10 1 to 4 #14 1 #14 sol w/1 to 2 #12 1 #14 w/1 to 2 #10	2 #14 w/1 #10 or #12 3 #14 w/1 #12 1 #16 w/2 #10 1 #16 w/1 to 3 #12 or #14 1 #16 w/1 #10 or #12 and 1 to 2 #14 2 #16 w/1 to 2 #12	2 #16 w/1 #12 w/1 #14 2 #16 w/1 to 2 #14 2 #16 w/1 #10 3 #16 w/1 to 2 #14 3 #16 w/1 #12 1 #18 w/1 to 3 #12, #14 or #16 2 #18 w/1 to 2 #10 or #12	2 #18 w/1 to 2 #14 or #16 3 #18 w/1 to 2 #14 or #16 1 #20 w/1 to 4 #16 or #18 2 #18 or #16



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL UnderGround™ Wire Connectors				
Model	600 Volt Maximum			
64 [®] Strip wires 5/8"	3 or 4 #22 solid 3 or 4 #20 solid 2 to 4 #18, #16 or #14 1 to 3 #12 or #10	1 #18 with 1 to 4 #16 or #14 or #12 1 #16 with 1 to 4 #14 or #12 1 #14 with 1 to 2 #12 or #10	2 #14 with 1 #12 or #10 2 #12 with 1 #10 1 #8 with 1 #12 or #10	
Model	600 Volt Maximum			
66 [®] Strip wires 1"	1 or 2 #6 2 or 3 #8 2 to 5 #10 3 to 6 #12 1 #6 w/1 to 2 #8 1 #6 w/1 to 3 #10 1 #6 w/1 to 5 #12	1 #6 w/1 to 4 #14 2 #6 w/1 #10 or #12 2 #6 w/1 to 2 #14 1 #8 w/1 to 4 #10 1 #8 w/1 to 5 #12 or #14 2 #8 w/1 to 2 #10 2 #8 w/1 to 3 #12	2 #8 w/1 to 4 #14 3 #8 w/1 to 2 #14 1 #10 w/2 to 4 #12 1 #10 w/3 to 5 #14 2 #10 w/1 to 4 #12 or #14 3 #10 w/1 to 3 #12 or #14 4 #10 w/1 to 2 #12 or #14	1 #12 w/4 to 5 #14 2 #12 w/2 to 4 #14 3 #12 w/1 to 3 #14 4 #12 w/1 #14
IDEAL Twister [®] AL/CU Wire Connectors				
Model	600 Volt Maximum			
	Copper-to-Copper only combinations			Copper-to-Aluminum combinations. Not for use on Aluminum-to-Aluminum conductors.
65 [®] Strip wires 1/2"	4 to 6 #22 3 to 6 #20 2 to 6 #18 1 to 6 #16 1 to 5 #14 1 to 3 #12 4 #12 sol 1 to 3 #10 2 #22 w/3 to 5 #20 1 #22 w/1 to 5 #18, #16 2 #22 w/1 to 4 #20, #18, #16 3 #22 w/1 to 3 #20, #18, #16 4 #22 w/1 to 2 #20, #18, #16 1 #20 w/1 to 4 #18, #16, #14 2 #20 w/1 to 3 #18, #16, #14 3 #20 w/1 to 2 #18, #16, #14 4 #20 w/1 to 2 #18, #16, #14 1 #18 w/1 to 4 #16, #14, #12 1 #18 w/1 to 2 #10 2 #18 w/1 to 4 #16, #14, #12 2 to 3 #18 w/1 to 2 #10 4 #18 w/1 to 2 #16, #14, #12 4 #18 w/1 #10 5 #18 w/1 #16 or #14 1 #16 w/1 to 4 #14, #12 1 #16 w/1 to 2 #10	2 #16 w/1 to 4 #14 3 #16 w/1 to 3 #14 3 #16 w/1 to 2 #12, #10 4 #16 w/1 to 2 #14, #12 4 #16 w/1 #10 5 #16 w/1 #14 5 #16 sol w/1 #10 sol 1 #14 sol w/1 to 3 #12 1 to 2 #14 w/1 to 2 #10 2 #14 w/1 to 2 #10 2 #14 w/1 #8 3 #14 w/1 #12 or #10 3 #14 w/2 #12 4 #14 w/1 #12 or #10 1 #12 w/1 to 2 #10 1 #12 w/1 #8 2 #12 w/1 #10 1 #10 w/1 #8 1 #22 w/1 #18 w/1 #16 1 #22 w/1 #20 w/1 to 2 #16 1 #16 w/1 to 2 #14 w/1 #12 or #10 1 #16 w/1 #12 w/1 #10 2 #16 w/1 #14 #w/1 to 2 #12 2 #16 w/2 #14 w/1 #12 2 #16 w/1 #12 w/1 #10	3 #16 w/1 #14 w/1 #12 or #10 4 #16 w/1 #12 w/1 #10 1 #14 w/1 to 2 #12 w/1 #10 2 #14 w/1 #12 w/1 #10	1 #10 AL sol. w/1 to 2 #10 CU sol. 1 #10 AL w/1 to 2 #12 CU 1 #10 AL w/1 to 2 #14 CU 1 #10 AL w/1 to 2 #16 CU 2 #10 AL sol. w/1 #12 CU 2 #10 AL sol. w/1 #14 CU 2 #12 AL sol. w/1 #10 CU sol. 2 #12 AL sol. w/1 #10 CU str. 1 #12 AL sol. w/1 to 2 #10 CU sol or str 1 #12 AL str. w/1 to 2 #10 CU sol. 1 #12 AL w/1 to 2 #12 CU 2 #12 AL sol. w/1 #12 CU 1 #12 AL w/1 to 2 #14 CU 2 #12 AL sol. w/1 #14 CU 1 #10 AL w/1 to 2 #18 CU 2 #10 AL sol. w/1 #16 CU 2 #10 AL sol. w/1 #18 CU 1 #12 AL w/1 to 2 #16 CU 1 #12 AL w/1 to 2 #18 CU 2 #12 AL sol. w/1 #16 CU 2 #12 AL sol. w/1 #18 CU 2 #16 w/1 to 3 #12 2 #16 w/1 to 2 #10



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan B-CAP® Wire Connectors				
Model	600 Volt Maximum			
B1 Strip wires 1/2"; Strip wires #16 and smaller 5/8"	#22 4 to 6	#16 w/#22 2 to 6*	#12 w/#18 2 to 3*	
	#20 3 to 6	#16 w/#20 2 to 6*	#12 w/#16 2 to 3*	
	#18 2 to 6	#16 w/#18 2 to 5*	#12 w/#14 2 to 3*	
	#16 2 to 5	#14 w/#22 2 to 4*	1 #10 w/1 #12	
	#14 2 to 4	#14 w/#20 2 to 4*	1 #10 w/1 to 2 #14	
	#12 2 to 3	#14 w/#18 2 to 4*	1 #10 w/1 to 2 #16	
	#20 w/#22 3 to 6*	#14 w/#16 2 to 4*	1 #10 w/1 to 3 #18	
#18 w/#22 3 to 6*	#12 w/#22 2 to 3*			
#18 w/#20 3 to 6*	#12 w/#20 2 to 3*			
Model	600 Volt Maximum			
B2 Strip wires 1/2"; Strip wires #16 and smaller 5/8"	#22 5 to 6	#10 2 stranded	#12 w/#22 2 to 6*	1 #10 w/1 to 3 #12
	#20 3 to 6	#20 w/#22 4 to 6*	#12 w/#20 2 to 6*	2 #10 w/1 #12
	#18 2 to 6 solid	#18 w/#22 3 to 6*	#12 w/#18 2 to 5*	1 #8 stranded w/1 #14
	#18 2 to 5 stranded	#18 w/#20 3 to 6*	#12 w/#16 2 to 5*	stranded
	#16 2 to 6 solid	#16 w/#22 3 to 6*	#12 w/#14 2 to 5*	1 #8 stranded w/1 #12
	#16 2 to 5 stranded	#16 w/#20 2 to 6*	1 #10 w/1 to 4 #18	stranded
	#14 2 to 6 solid	#16 w/#18 2 to 6*	2 #10 w/1 to 3 #18	1 #8 stranded w/1 #10
	#14 2 to 5 stranded	#14 w/#22 2 to 6*	1 #10 w/1 to 4 #16	stranded
	#12 2 to 5 solid	#14 w/#20 2 to 6*	2 #10 w/1 to 3 #16	1 #12 w/1 #14 w/1 to 4 #16
	#12 2 to 4 stranded	#14 w/#18 2 to 6*	to 4 #14	1 #12 w/2 #14 w/1 or 2 #16
#10 2 to 3 solid	#14 w/#16 2 to 6*	2 #10 w/1 to 2 #14	2 #12 w/1 #14 w/1 to 3 #16	
Model	600 Volt Maximum			
B4 Strip wires 3/4"	#14 4 to 6	#8 2 stranded	1 #8 w/1 to 4 #14	2 #8 w/1 or 2 #10
	#12 2 to 5	#6 2 stranded	1 #8 w/1 to 4 #12	1 #6 w/1 to 4 #14
	#10 2 to 5 solid	#12 w/#14 2 to 6*	2 #8 w/1 to 3 #12	1 #6 w/1 to 4 #12
	#10 2 to 4 stranded	#10 w/#14 2 to 5*	3 #8 solid w/1 #12	1 #6 w/1 or 2 #10
	#8 2 or 3 solid	#10 w/#12 2 to 5*	1 #8 w/1 to 4 #10	1 #6 w/1 or 2 #8
Model	600 Volt Maximum			
BGR/WGR	2 or 3 #10	1 #10 w/1 to 4 #14	2 to 5 #12	2 to 5 #14
	2 #10 w/1 or 2 #12	1 #10 w/1 to 3 #12 w/1 #14	4 #12 w/1 #14	
	2 #10 w/1 #12 w/1 #14	1 #10 w/1 or 2 #12 w/1 or 2 #14	3 #12 w/1 or 2 #14	
	2 #10 w/1 to 3 #14	#14	2 #12 w/1 to 3 #14	
	1 #10 w/1 to 3 #12	1 #10 w/1 #12 w/1 to 3 #14	1 #12 w/1 to 4 #14	



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan B-Twist™ Wire Connectors				
Model	600 Volt Maximum			
BT-2 Strip wires 1/2"	#10 1 to 4	1#10 w/2 #12 w/1 to 2 #14	3 #12 w/1 to 3 #18, #16 or #14	1 #16 w/1 #18 w/1 to 3 #22 or #20
	#12 1 to 5	1 #10 w/3 #12 w/1 #14	3 #12 w/1 #16 w/1 to 2 #18	2 #16 w/1 to 3 #22, #20 or #18
	#14 1 to 6	1 #10 w/1 to 4 #18 or #16	3#12 w/1 #14 w/1 to 2#18 or #16	3 #16 w/1 to 3 #22 w/1 #20
	#16 1 to 6	2 #10 w/1 to 3 #14	3 #12 w/2 #14 w/1 #16	3 #16 w/1 to 2 #22 w/1 #20
	#18 2 to 6	2 #10 w/1 to 3 #12	4 #12 w/1 to 2 #16	3 #16 w/1 #18 or 2 #22 or #20
	#20 3 to 6	2 #10 w/1 #16 w/1 to 3 #18	4 #12 w/1 #14	4 #16 w/1 to 2 #22, #20 or #18
	#22 4 to 6	2 #10 w/2 #14 w/1 to 2 #16	4 #12 w/1 #16 w/1 #18	4 #16 w/1 #22 w/1 #20
	1 #8 w/1 to 5 #16	2 #10 w/1 #12 w/1 to 3 #16	4 #12 w/1 #14 w/1 #18 or #16	4 #16 w/1 #18 w/1 #22 or #20
	1 #8 w/1 to 4 #14	2 #10 w/1 #12 w/1 to 4 #14	1 #14 w/1 to 5#22, #20, #18 or #16	5 #16 w/1 #22, #20 or #18
	1 #8 w/1 to 3 #12	2 #10 w/2 #12 w/1 to 2 #18 or #16	1 to 2 #14 w/1 #16 w/1 to 3 #18	1 #18 w/1 to 5 #22 or #20
	1 #8 w 2 #12 w/1 to 4 #14	2 #10 w/2 #12 w/1 #14	2 #14 w/1 to 4#22, #20, #18 or #16	1 to 3 #18 w/1 to 2 #22 w/1 #20
	1 #8 w/1 to 2 #10	3 #10 w/1 to 3 #18 or #16	3 #14 w/1 to 3#22, #20, #18 or #16	1 to 3 #18 w/2 #22 or #20
	1 # w/1 #10 w/1 to 2 #14 or #12	3 #10 w/1 to 2 #14	3 #14 w/1 #16 w/1 to 2 #18	2 #18 w/1 to 4 #22 or #20
	1 #8 w/2 #10 w/1 #14	3 #10 w/1 #12	3 #14 w/1 #16 w/1 to 2 #18	3 #18 w/1 to 3 #22 or #20
	1 #10 w/1 to 5 #18, #16 or #14	3 #10 w/1 #16 w/1 to 2 #18	4 #14 w/1 to 2 #22, #20, #18 or #16	4 #18 w/1 to 2 #22 or #20
	1 #10 w/1 to 4 #12	3 #10 w/1 #14 w/1 to 2 #18	4 #14 w/1 #16 w/1 to 2 #18	5 #18 w/1 #22 or #20
	1 #10 w/1 #16 w/1 to 4 #18	3 #10 w/1 #14 w/1 #16	4 #14 w/1 to 2 #22, #20, #18 or #16	1 #20 w/3 to 5 #22
	1 #10 w/1 #14 w/1 to 4 #18 or #16	3 #10 w/1 #12 w/1 #18 or #16	4 #14 w/1 #16 w/1 #18	2 #20 w/2 to 4 #22
	1 #10 w/2 #14 w/1 to 3 #16	1 #12 w/1 to 5 #18, #16 or #14	5 #14 w/1 #18 or #16	3 #20 w/2 to 3 #22
	1 #10 w/1 #12 w/1 to 4 #18 or #16	1 to 2 #12 w/1 #16 w/1 to 3 #18	1 #16 w/1 to 5#22, #20 or #18	4 #20 w/2 #22
1 #10 w/1 #12 w/1 to 4 #14	1 to 2 #12 w/1 #14 w/1 to 3 #18 or #16	1 to 2#16 w/1 to 2 #20 w/1 to 2 #22 or #20	5 #20 w/1 #22	
1 #10 w/2 #12 w/1 to 3 #18 or #16	1 to 2 #12 w/2 #14 w/1 #16			
	2 #12 w/1 to 4 #18, #16 or #14			
Buchanan WireTwist™ Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
WT-1 Strip solid wires 1/4"; strip stranded wires 5/16"	1 #14	1 #18 w/1 to 3 #20		
	1 to 2 #16	1 #18 w/1 to 4 #22		
	2 to 3 #18	2 #22 stranded only		
	2 to 4 #20	4 #20 w/1 #22		
	3 to 4 #22	3 #20 w/1 to 2 #22		
	5 #22 solid	2 #20 w/1 to 3 #22		
	1 #14 w/1 #20 or 22	1 #20 w/1 to 4 #22		
	1 #16 w/1 #18	1 #16 w/1 #20 w/1 #18 or #20		
	1 #16 w/1 to 2 #20	1-2 #18 w/1 #20 w/1 #22		
	1 #16 w/1 to 3 #22			
Model	300 Volt Maximum		600 Volt Maximum	
WT-2 Strip wires 3/8"; strip wires #16 and smaller 1/2"	1 #14 Stranded only	1 #16 w/1 to 3 #18		
	1 #16 Stranded only	1 #16 w/1 #18 w/1 #20		
	2 to 3 #16	1 #16 w/1 to 4 #20 or #22		
	1 #18 Stranded only	4 #18 w/1 #20 or #22		
	2 to 4 #18	3 #18 w/1 to 2 #20 or #22		
	3 to 5 #20	2 #18 w/1 to 3 #20 or #22		
	1 #14 w/1 #16	1 #18 w/2 to 4 #20		
	1 #14 w/1 to 2 #18	1 #18 w/3 to 4 #22		
	1 #14 w/1 to 3 #20	4 #20 w/1 #22		
	1 #14 w/1 to 4 #22	3 #20 w/1 to 2 #22		
	2 #16 w/1 #18	2 #16 w/1 #20 w/1 #22		
	2 #16 w/1 to 2 #20	1 #16 w/1 #22 w/1 #18 or #20		
2 #16 w/1 to 3 #22	1 to 2 #18 w/1 #20 w/1 #22			



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WireTwist™ Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
WT-3 Strip wires 5/16"; strip wires #16 and smaller 3/8"	5 #18	2 #16 w/2 to 3 #18	1 to 2 #14	2 #16 w/1 to 2 #22
	5 #22	2 #16 w/3 #22	1 #16 Stranded only	1 #16 w/1 to 2 #18
	3 to 4 #16	2 #16 w/3 #20	2 #16	1 #16 w/1 to 3 #20 or #22
	4 to 5 #20	1 #16 w/4 #18	1 #18 Stranded only	3 #18 w/1 #20 or #22
	2 #14 w/2 #16	4 #18 w/1 #20 or #22	2 to 4 #18	2 #18 w/1 to 2 #20
	2 #14 w/1 to 3 #20 or #22	3 #18 w/2 #20 or #22	1 #14 w/1 #16	2 #18 w/1 to 3 #22
	1 #14 w/2 #16	2 #18 w/3 #22	1 #14 w/1 #16 and 1 #18	1 #18 w/2 to 4 #20
	1 #14 w/3 #18	1 #18 str. w/5 #22 str.	1 #14 w/1 to 2 #18	1 #18 w/3 to 4 #22
	1 #14 w/4 #20	4 #20 w/1 #22	1 #14 w/1 to 3 #20	1 to 2 #16 w/1 #20 w/1 #22
	4 #16 w/1 #20 or #22	3 #20 w/1 to 2 #22	1 #14 w/1 to 3 #22	1 #16 w/1 #18 w/1 #22
	3 #16 w/1 #18	2 #20 w/2 to 3 #22	2 #16 w/1 #18	1 to 2 #18 w/1 #20 w/1 #22
3 #16 w/1 to 2 #20 or #22	1 #20 w/4 #22	2 #16 w/1 to 2 #20		
Model	300 Volt Maximum		600 Volt Maximum	
WT-4 Strip wires 3/8"; strip wires #16 and smaller 7/16"	2 #10		1 #8	3 #16 w/1 #18
	3 #12		1 #10	4 #16 w/1 #22 or #20
	5 #16		1 to 2 #12	1 #18 w/2 #20
	5 #18		1 to 3 #14	1 #18 w/3 #22
	1 #10 w/3 to 4 #16		2-5 #16	2 #18 w/3 #20
	1 #10 w/2 #14		2-6 #18	3 #18 w/1 to 2 #22 or #20
	1 #10 w/1 #16 w/4 #20		3 to 4 #20	4 #18 w/1 #22 or #20
	1 #10 w/1 #16 w/3 to 4 #18		4 #22	2 #12 w/1 #18 w/1 to 2 #20
	1 #10 w/1 #14 w/4 #22		1 #10 w/1 #14	1 #14 w/1 #16 w/1 to 4 #22
	1 #10 w/1 #14 w/3 #20		1 #10 w/1 #12	2 #14 w/1 to 2 #20 w/1 to 2 #22
	1 #10 w/1 #14 w/2 to 4 #18		1 #12 w/1 to 4 #20, #18, or #16	3 #14 w/1 #18 w/1 to 2 #22
	1 #10 w/1 #14 w/2 #16		1 #12 w/1 to 2 #14	3 #14 w/1 #18 w/1 #20
	1 #10 w/2 #14 w/1 #16		2 #12 w/1 to 2 #18	1 #16 w/1 #20 w/4 #22
	1 #10 w/1 #12 w/1 to 2 #18		2 #12 w/1 #16	1 #16 w/1 #18 w/3 to 4 #22
	1 #10 w/1 #12 w/1 #16 or #14		1 #14 w/2 to 4 #20	1 #16 w/1 #18 w/2 to 4 #20
	1 #12 w/3 #14		1 #14 w/1 to 3 #18 or #16	2 #16 w/1 to 2 #20 w/1 to 2 #22
	2 #12 w/1 to 2 #14		2 #14 w/1 to 3 #20	3 #16 w/1 #18 w/1 to 2 #22 or #20
	2 #12 w/3 #18		2 #14 w/1 to 2 #18 or #16	1 #18 w/2 #20 w/3 #22
	1 #14 w/4 #18 or #16		3 #14 w/1 to 2 #20	2 #18 w/1 #20 w/3 #22
	2 #14 w/3 #18 or #16		3 #14 w/1 #18 or #16	3 #18 w/1 to 2 #20 w/1 #22
	3 #14 w/2 #18 or #16		4 #14 w/1 #20 or #18	1 #10 w/1 #16 w/1 to 2 #18
	3 #14 w/1 #18 w/2 #20		1 #16 w/4 #20	1 #10 w/1 #14 w/1 to 2 #20
	4 #14 w/1 to 2 #16		1 #16 w/1 to 3 #18	1 #10 w/1 #14 w/1 #18
	1 #16 w/4 #18		1 #16 w/1 to 3 #20	1 #12 w/1 #16 w/1 to 4 #20 or #18
	2 #16 w/3 #18		1 #16 w/2 #22	
	3 #16 w/2 #18		2 #16 w/1 to 3 #20	
	4 #16 w/1 #18		2 #16 w/1 to 2 #18	
		2 #14 w/1 #16 w/1 to 3 #22		
		3 #16 w/1 to 2 #22 or #20		



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WireTwist™ Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
WT-6 Strip wires 7/16"; strip wires #16 and smaller 1/2"	2 #8 stranded only	2 #10 w/1 #12 w/1 to 3 #18	1 #8 w/1 #12	2 to 5 #14
	3 #10	2 #10 w/1 #12 w/1 to 2 #16	1 #10 w/1 to 4 #18 or #16	4 to 6 #16
	5 #12	3 #10 w/1 #18 or #16	1 #10 w/1 to 3 #14	1 #8 w/1 to 2 #14
	1 #6 w/1 #14	2 #12 w/2 #14 w/2 #16	1 #10 w/1 to 2 #12	2 #12 w/1 to 3 #14
	1 #6 w/1 #12	3 #12 w/2 #14	1 #10 w/1 #18 w/1 to 4 #22 or #20	2 #12 w/1 #16 w/1 to 3 #20
	1 #6 w/1 #14 w/1 to 2 #18	3 #12 w/3 #16	1 #10 w/1 #16 w/1 to 4 #20	2 #12 w/1 #14 w/1 to 3 #18
	1 #6 w/1 #14 w/1 #16	3 #12 w/1 #16 w/2 #18	1 #10 w/1 #16 w/1 to 4 #18	2 #12 w/1 #14 w/1 to 3 #16
	1 #8 w/4 #16	3 #12 w/1 #14 w/1 to 2 #16	1 #10 w/1 #14 w/1 to 4 #16 or #18	3 #12 w/1 #14
	1 #8 w/3 #14	3 #12 w/1 #14 w/1 to 2 #18	1 #10 w/2 #14 w/1 to 2 #16	3 #12 w/1 to 2 #16 or #18
	1 #8 w/2 #12	3 #12 w/2 #14 w/1 #16	1 #10 w/1 #12 w/1 to 3 #16 or #18	3 #12 w/1 #16 w/1 to 2 #20
	1 #8 w/1 #10	4 #12 w/1 #18, #16, or #14	1 #10 w/1 #12 w/1 to 2 #14	2 #12 w/2 #14 w/1 #16 or #18
	1 #8 w/1 #14 w/4 #18		1 #10 w/2 #12 w/1 #16 or #18	1 #14 w/3 to -4 #18
	1 #8 w/1 #12 w/1 to 4 #18 or #16		2 #10 w/1 to 3 #18	1 #14 w/1 #16 w/2 to 4 #20
	1 #8 w/1 #12 w/1 to 2 #14		2 #10 w/1 to 2 #16	1 to 2 #14 w/1 #16 w/1 to 3 #18
	1 #8 w/2 #12 w/1 #16 or #14		2 #10 w/1 #14	2 #14 w/2 to 4 #16
	1 #8 w/1 #10 w/1 #14 or #12		2 #10 w/1 #16 w/1 #18	2 #14 w/1 #18 w/1 to 3 #22 or #20
	1 #10 w/4 #14		2 #10 w/1 #14 w/1 #20	2 #14 w/1 #16 w/1 to 3 #22 or #20
	1 #10 w/3 #12		1 #12 w/2-4 #20 or #18	3 #14 w/1 to 2 #18 or #16
	1 #10 w/2 #14 w/3 #16		1 #12 w/1 to 4 #16 or #14	3 #14 w/1 #16 w/1 to 2 #20
	1 #10 w/1 #12 w/4 #16		1 #12 w/1 #16 w/1 to 4 #20	3 #14 w/1 #16 w/1 to 2 #18
	1 #10 w/1 #12 w/3 to 4 #14		1 #12 w/1 #14 w/1 to 4 #20, #18, or #16	1 #16 w/4 #18
	1 #10 w/2 #12 w/2 to 3 #18 or #16		1 #12 w/2 #14 w/1 to 3 #16	2 #16 w/3 to 4 #18
	1 #10 w/2 #12 w/1 to 2 #14		2 #12 w/1 to 2 #18 or #16	2 #16 w/1 #18 w/3 #22
	2 #10 w/3 #16		1 #6 or #8	2 #16 w/1 #18 w/2 to 3 #20
2 #10 w/2 to 3 #14		1 to 2 #10	3 #16 w/1 to 2 #20 or #18	
2 #10 w/1 to 2 #12		1 to 4 #12	4 #16 w/1 #20 or #18	
2 #10 w/1 #16 w/2 to 3 #18				
2 #10 w/1 #14 w/1 to 3 #18				
2 #10 w/2 #14 w/1 #16				
Buchanan WingTwist™ Wire Connectors				
Model	600 Volt Maximum			
WT-51 Strip wires 3/8"	2 to 4 #18	1 to 3 #14	3 #14 w/1 #16 or #18	1 to 3 #12
	2 to 4 #16	1 #14 w/1 to 5 #18	1 #12 w/1 to 5 #18	1 #10 w/1 to 3 #18
	1 #16 w/1 to 5 #18	1 #14 w/1 to 4 #16	1 #12 w/1 to 3 #16	1 #10 w/1 to 2 #16 or #14
	2 #16 w/1 to 4 #18	2 #14 w/1 to 3 #18	1 #12 w/1 to 2 #14	1 #10 w/1 #12
	3 #16 w/1 to 3 #18	2 #14 w/1 to 3 #16	2 #12 w/1 to 2 #18	1 #10
4 #16 w/1 to 2 #18	3 #14 w/1 to 2 #18	2 #12 w/ 1 #16 or #14		



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WingTwist™ Wire Connectors				
Model	600 Volt Maximum			
WT-41 Strip wires 1/2"	3 to 6 #22 2 to 6 #20, #18, or #16 1 to 5 #14 1 to 3 #12 4 #12 solid 1 to 3 #10 1 #22 solid w/1 #20 solid 1 #22 w/2 to 5 #20 1 #22 w/1 to 5 #18, #16 2 #22 w/1 to 4 #20, #18 or #16 3 #22 w/1 to 3 #20, #18 or #16 4 #22 w/1 to 2 #2, #18 or #16 1 #20 w/1 to 4 #18, #16 or #14 2 #20 w/1 to 3 #18, #16 or #14 3 #20 w/1 to 2 #18, #16 or #14	4 #20 w/1 to 2 #18, #16 or #14 1 #16 stranded 1 #18 w/1 to 4 #16, #14 or #12 1 #18 w/1 to 2 #10 2 #18 w/1 to 4 #16 or #14 2 #18 w/1 to 3 #12 2 #18 w/1 to 2 #10 3 #18 w/1 to 3 #16, #14 or #12 3 #18 w/1 to 2 #10 4 #18 w/1 to 2 #16, #14 or #12 4 #18 w/1 #10 5 #18 w/1 #16 or #14 1 #16 w/1 to 4 #14 or #12 1 #16 w/1 to 2 #10 2 #16 w/1 to 4 #14	2 #16 w/1 to 3 #12 or #14 3 #16 w/1 to 2 #12 or #10 4 #16 w/1 to 2 #14 or #12 4 #16 w/1 #10 5 #16 w/1 #14 5 #16 solid w/1 #10 solid 1 #14 solid w/1 to 3 #12 1 #14 w/1 to 2 #10 2 #14 w/1 to 2 #12 2 #14 w/1 to 2 #10 2 #14 w/1 #8 3 #14 w/1 #12 or #10 3 #14 w/2 #12 4 #14 w/1 #12 or #10 1 #12 w/1 to 2 #10	1 #12 w/1 #8 2 #12 w/1 #10 1 #10 w/1 #8 1 #22 w/1 #18 w/1 #16 1 #22 w/1 #20 w/1 to 2 #16 1 #16 w/1 to 2 #14 w/1 #12 or #10 1 #16 w/1 #12 w/1 #10 2 #16 w/1 #14 w/1 to 2 #12 2 #16 w/2 #14 w/1 #12 2 #16 w/1 #12 w/1 #10 3 #16 w/1 #14 w/1 #12 or #10 4 #16 w/1 #12 w/1 #10 1 #14 w/1 to 2 #12 w/1 #10 2 #14 w/1 #12 w/1 #10
Model	600 Volt Maximum			
WT-52 Strip wires 1/2"	1 #12 w/5 #14 1 #12 w/4 #16 or #14 1 #12 w/2 #14 1 #12 w/1 #14 1 #10 w/3 #14 1 #10 w/4 #14 1 #10 w/2 #14 1 #10 w/1 #12 1 #8 w/1 #10, #12, or #14 1 #10 w/2 to 5 #18 1 #10 w/1 to 4 #16 1 #10 w/1 to 2 #14 or #12	1 #10 w/1 #14 and 1 to 3 #16 1 #10 w/2 #14 and 1 #16 1 #10 w/1 #12 and 1 #14 1 #10 w/1 #12 and 1 to 2 #16 2 #10 w/1 to 2 #16 2 #10 w/1 #14 1 #12 w/2 to 5 #18 1 #12 w/1 to 5 #16 1 #12 w/1 to 4 #14 1 #12 w/1 #14 and 1 to 4 #16 1 #12 w/2 #14 and 1 to 2 #16 2 #12 w/3 to 4 #18	2 #12 w/1 to 3 #16 2 #12 w/1 to 3 #14 2 #12 w/1 #14 and 1 to 2 #16 3 #12 w/1 to 2 #16 3 #12 w/2 #18 1 #14 w/3 to 5 #18 1 #14 w/3 #12 1 #14 w/2 to 5 #16 2 #14 w/1 to 4 #18 or #16 3 #14 w/1 to 3 #16 4 #14 w/1 to 2 #18 4 #14 w/1 #16	5 #14 w/1 #18 1 #16 w/4 to 5 #18 2 #16 w/2 to 4 #18 3 #16 w/1 to 3 #18 4 #16 w/1 to 2 #18 5 #16 w/1 #18 2 to 3 #10 2 to 5 #12 2 to 6 #14 4 to 6 #16 6 #18
Model	600 Volt Maximum			
WT-53 Strip wires 1/2"	4 to 6 #14 2 to 6 #12 2 to 3 #10 2 #8 1 #6 4 #16 w/2 #18 1 #14 w/4 to 5 #16 2 #14 w/3 to 4 #18 2 #14 w/2 to 4 #16 3 #14 w/1 to 3 #18 or #16 4 #14 w/1 to 2 #18 or #16 5 #14 w/1 #18 or #16	1 #12 w/3 to 5 #16 1 #12 w/2 to 5 #14 2 #12 w/3 to 4 #18 2 #12 w/1 to 4 #16 or #14 3 #12 w/1 to 3 #18 or #16 3 #12 w/1 to 3 #14 4 #12 w/1 to 2 #16 1 #10 w/1 to 5 #16 or #14 1 #10 w/1 to 4 #12 2 #10 w/2 to 4 #18 or #16 2 #10 w/1 to 4 #14 2 #10 w/1 to 2 #12	3 #10 w/1 #14 or #12 1 #8 w/1 to 5 #14 1 #8 w/1 to 3 #12 1 #8 w/1 to 2 #10 2 #8 w/1 #14 1 #6 w/1 #10 1 #12 w/1 #14 w/1 to 4 #16 1 #12 w/2 #14 w/1 #16 2 #12 w/1 #14 w/1 to 2 #16 1 #10 w/1 #14 w/1 to 3 #16 1 #10 w/2 #14 w/1 #16 1 #10 w/1 #12 w/1 to 2 #6	1 #10 w/1 #12 w/1 to 4 #14 1 #10 w/2 #12 w/1 to 3 #14 1 #10 w/3 #12 w/1 #14 2 #10 w/2 #12 w/1 to 2 #14 1 #8 w/1 #12 w/1 to 3 #14 1 #8 w/2 #12 w/1 #14 1 #8 w/1 #10 w/1 to 2 #14 1 #8 w/1 #10 w/1 #12



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WingTwist™ Wire Connectors				
Model	600 Volt Maximum			
WT-54 Strip wires 5/8"	5 to 6 #14 3 to 6 #12 2 to 5 #10 2 to 3 #8 1 to 2 #6 1 #12 w/4 to 5 #14 2 #12 w/2 to 4 #14 3 #12 w/1 to 3 #14 4 #12 w/1 #14 1 #10 w/3 to 5 #14 1 #10 w/2 to 4 #14 2 #10 w/1 to 4 #14 or #12 3 #10 w/1 to 3 #14 or #12 4 #10 w/1 to 2 #14 or #12 1 #8 w/1 to 5 #14 or #12 1 #8 w/1 to 4 #10	2 #8 w/1 to 4 #14 2 #8 w/1 to 3 #12 2 #8 w/1 to 2 #10 3 #8 w/1 to 2 #14 1 #6 w/1 to 4 #14 1 #6 w/1 to 5 #12 1 #6 w/1 to 3 #10 1 #6 w/1 to 2 #8 2 #6 w/1 #12 2 #6 w/1 #12 1 #10 w/1 #12 w/1 to 4 #14 1 #10 w/2 #12 w/1 to 3 #14 1 #10 w/3 #12 w/1 to 2 #14 1 #10 w/4 #12 w/1 #14 2 #10 w/1 #12 w/1 to 3 #14 2 #10 w/2 #12 w/1 to 2 #14	2 #10 w/3 #12 w/1 #14 3 #10 w/1 #12 w/1 to 2 #14 3 #10 w/2 #12 w/1 #14 4 #10 w/1 #12 w/1 #14 1 #8 w/1 #12 w/1 to 4 #14 1 #8 w/2 #12 w/1 to 3 #14 1 #8 w/3 #12 w/1 to 2 #14 1 #8 w/4 #12 w/1 #14 1 #8 w/1 #10 w/1 to 4 #14 1 #8 w/1 #10 w/1 to 4 #12 1 #8 w/2 #10 w/1 to 3 #14 1 #8 w/2 #10 w/1 to 3 #12 1 #8 w/3 #10 w/1 to 2 #14 1 #8 w/3 #10 w/1 #12 2 #8 w/1 #12 w/1 to 3 #14 2 #8 w/2 #12 w/1 to 2 #14	2 #8 w/3 #12 w/1 #14 2 #8 w/1 #10 w/1 to 3 #14 2 #8 w/1 #10 w/1 to 2 #12 2 #8 w/2 #10 w/1 #14 Sol 1 #6 w/1 #12 w/1 to 4 #14 1 #6 w/2 #12 w/1 to 3 #14 1 #6 w/3 #12 w/1 to 2 #14 1 #6 w/4 #12 w/1 #14 1 #6 w/1 #10 w/1 to 4 #14 1 #6 w/1 #10 w/1 to 3 #12 1 #6 w/2 #10 w/1 to 2 #14 1 #6 w/2 #10 w/1 #12 1 #6 w/1 #8 w/1 to 3 #14 1 #6 w/1 #8 w/1 to 2 #12 1 #6 w/1 #8 w/1 #10
IDEAL Set Screw Wire Connectors				
Model	300 Volt Maximum			
10	1 #10 1 #10 str. w/1 #20 1 #10 str. w/1 to 2 #22 1 #12 1 #12 str. w/1 #14 1 #12 str. w/1 #16 w/1 #18 1 #12 str. w/1 to 2 #18 or #20 1 #12 str. w/1 #18 or #20 w/1 to 2 #22 1 #12 w/3 or 4 #20 or #22 1 to 2 #14 2 #14 w/1 #16 1 #14 w/1 to 2 #16 2 #14 str. w/1 #16 w/1 #20 or #22	1 #14 str. w/1 #16 w/1 #18, #20, or #22 2 #14 w/1 to 2 #18 1 #14 w/1 to 3 #18 2 #14 str. w/1 #18 or #20 w/1 to 2 #22 1 #14 str. w/1 #18 or #20 w/1 to 2 #22 2 #14 w/1 to 3 #20 1 #14 w/3 to 5 #20 1 #14 str. w/1 to 2 #20 1 #14 str. w/2 to 5 #22 2 #14 w/3 to 4 #22 2 #14 str. w/1 to 2 #22 2 to 4 #16	1 #16 w/1 to 5 #20 or #22 1 #16 w/1 to 4 #18 1 #16 w/1 #20 w/1 to 2 #22 1 #16 w/1 #18 w/1 to 2 #22 2 #16 w/1 to 4 #20 or #22 2 #16 w/1 to 3 #18 3 #16 w/1 #18 or #20 w/1 to 2 #22 3 #16 w/1 to 3 #20 or #22 4 #16 w/1 #18, #20 or #22 4 #16 w/1 #20 w/1 #22 2 to 6 #18 1 #18 w/1 to 5 #20 or #22 1 #18 w/1 #20 w/1 to 2 #22 2 #18 w/1 to 4 #20 or #22	2 #18 w/1 #20 w/1 to 2 #22 3 #18 w/1 to 4 #22 3 #18 w/1 to 3 #20 3 #18 w/1 #20 w/1 to 2 #22 4 #18 w/1 to 2 #20 or #22 4 #18 w/1 #20 w/1 to 2 #22 5 #18 w/1 #20 w/1 to 2 #22 2 to 6 #20 1 #20 w/1 to 5 #22 2 #20 w/1 to 4 #22 3 #20 w/1 to 3 #22 4 #20 w/1 to 2 #22 5 #20 w/1 #22 4 to 6 #22 3 #16 w/1 to 2 #18
Model	600 Volt Maximum			
11	1 #10 1 #10 str. w/1 to 2 #16, #18 or #20 1 #10 w/3 or 4 #18 1 #10 w/3 #16 2 #12 1 #12 w/4 #18 1 #12 w/2 #14 1 #12 w/1 #16 1 #12 w/3 to 5 #20 1 #12 w/1 to 3 #16 or #18 1 #12 w/1 #14 2 #12 w/2 to 3 #20 2 #12 w/1 to 2 #18 2 to 3 #14	3 #14 w/5 #22 3 #14 w/3 #20 1 #14 w/2 to 5 #22 1 #14 w/1 to 5 #18 or #20 1 #14 w/1 to 4 #16 2 #14 w/1 to 5 #20 or #22 2 #14 w/1 to 4 #18 2 #14 w/1 to 3 #16 3 #14 w/1 or 3 #22 3 #14 w/1 to 2 #18 or #20 3 #14 w/1 #16 4 or 5 #16 1 #16 w/4 or 5 #22 1 #16 w/3 to 5 #20 1 #16 w/2 to 5 #18	2 #16 w/1 to 5 #22 2 #16 w/2 to 5 #20 2 #16 w/1 to 4 #18 3 #16 w/1 to 5 #22 3 #16 w/1 to 4 #20 3 #16 w/1 to 3 #18 4 #16 w/1 to 5 #22 4 #16 w/1 to 2 #18 or #20 5 #16 w/1 to 4 #22 5 #16 w/1 #18 or 1 #20 6 or 7 #18 1 #18 w/4 or 5 #20 or #22 2 #18 w/2 to 5 #22 2 #18 w/3 or 4 #20 3 #18 w/1 to 5 #22	3 #18 w/1 to 3 #20 4 #18 w/1 to 5 #22 4 #18 w/1 to 2 #20 5 #18 w/1 to 5 #22 5 #18 w/1 #20 1 #20 w/4 or 5 #22 2 #20 w/3 to 5 #22 3 #20 w/3 to 5 #22 4 #20 w/3 to 5 #22 5 #20 w/1 to 5 #22



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

UL File No. E5238

Page 14

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Set Screw Wire Connectors				
Model	600 Volt Maximum			
22	1 to 2 #10 1 #10 str. w/3 to 5 #20 1 #10 w/3 to 5 #18 1 #10 w/2 to 5 #16 1 #10 w/1 to 4 #14 1 #10 w/1 to 2 #12 2 #10 w/2 to 4 #20 2 #10 w/1 to 3 #18 2 #10 w/1 to 2 #16 2 #10 w/1 #14	2 #10 w/1 #12 2 to 4 #12 1 #12 w/3 to 5 #18 1 #12 w/2 to 5 #16 1 #12 w/1 to 5 #14 2 #12 w/1 to 4 #18 2 #12 w/1 to 4 #16 2 #12 w/1 to 4 #14 3 #12 w/1 to 3 #18 3 #12 w/1 to 2 #16	3 #12 w/1 #14 2 to 6 #14 1 #14 w/3 to 5 #18 1 #14 w/2 to 5 #16 2 #14 w/2 to 4 #20 2 #14 w/1 to 4 #16 3 #14 w/2 to 3 #20 3 #14 w/1 to 3 #16 4 #14 w/1 to 2 #16 5 #14 w/1 #16	2 #16 or #18 4 to 6 #16 1 #16 w/3 to 5 #18 2 #16 w/2 to 4 #18 3 #16 str. w/1 to 3 #18 str. 4 #16 w/1 to 2 #18 5 #16 w/1 #18 2 #18
IDEAL Crimp Connectors				
Model	600 Volt Maximum			
48 Crimp	1 to 3 #16 1 to 4 #18 1 to 5 #20 1 to 6 #22 1 #14 w/1 to 3 #22 1 #14 w/1 to 3 #20 1 #14 w/1 to 2 #18 1 #14 w/1 #16 1 #14 w/1 #18 w/1 to 3 #22 1 #14 w/1 #18 w/1 to 2 #20 1 #14 w/1 #18 w/1 #20 w/1 #22	1 #16 w/1 to 5 #22 1 #16 w/1 to 4 #20 1 #16 w/1 to 3 #18 1 #16 w/2 #22 1 #16 w/1 #18 w/1 #22 1 #16 w/2 #18 w/1 #20 1 #16 w/2 #18 w/1 to 2 #22 1 #16 w/1 #18 w/1 #20 w/1 #22 1 #16 w/1 #18 w/1 to 2 #20 w/1 #22 2 #16 w/1 to 3 #22	2 #16 w/1 to 2 #20 2 #16 w/1 #18 w/1 #22 2 #16 w/1 #20 w/1 #22 2 #16 w/1 #18 1 #18 w/1 to 5 #20 or #22 2 #18 w/1 to 3 #20 3 #18 w/1 to 3 #22 3 #18 w/1 to 2 #20 1 #18 w/1 to 4 #20 w/1 #22 1 #18 w/1 #20 w/2 to 4 #22 1 #18 w/2 #20 w/2 or 3 #22 1 #18 w/3 #20 w/2 #22	2 #18 w/1 to 2 #20 w/1 #22 2 #18 w/1 #20 w/1 to 3 #22 3 #18 w/1 #20 w/1 #22 2 #20 w/1 to 4 #22 3 #20 w/1 to 3 #22 4 #20 w/1 to 2 #22 5 #20 w/1 #22 1 #20 w/1 to 4 #22
Model	600 Volt Maximum			
49 Crimp	2 #14 1 to 4 #16 1 to 6 #18 1 to 6 #20 1 #12 str. w/1 or 2 #18 1 #12 str. w/1 #16 1 #14 w/1 to 3 #18	1 #14 w/1 to 3 #16 1 #14 w/2 to 3 #20 1 #14 w/1 #17 w/ 1 #20 1 #16 w/1 to 4 #18 1 #16 w/1 to 4 #20 1 #16 w/1 #18 w/1 #20 2 #16 w/1 to 2 #18	2 #16 w/2 to 3 #20 3 #16 w/1 #18 w/ 1 #20 1 #17 w/1 #18 w/1 #20 all str. 1 #17 w/1 #18 w/1 #20 w/ 1 #22 all str. 1 #18 w/1 #22 1 #18 w/2 to 4 #20	1 to 2 #18 w/1 #20 2 #18 w/1 to 4 #20 2 #18 w/1 #22 3 #18 w/1 #22 4 #18 w/1 #22
Model	600 Volt Maximum			
NC-8 Stranded Wire Only	2 #10 2 to 3 #12 3 to 5 #14 4 to 7 #16 7 to 12 #18 1 #8 w/1 #14, #16 or #18 1 #8 w/2 #18 1 #10 w/1 #12	1 #10 w/2 #14 1 #10 w/1, 2 or 4 #16 (no 3 #16's) 1 #10 w/1 to 6 #18 1 #12 w/3 to 8 #18 1 #12 w/2 to 5 #16 1 #12 w/1 to 4 #14 2 #12 w/1 to 4 #14	2 #12 w/1 to 3 #16 2 #12 w/2 #14 1 #14 w/4 to 10 #18 1 #14 w/3 to 6 #16 2 #14 w/2 to 7 #18 2 #14 w/1 to 4 #16 3 #14 w/1 to 5 #18 3 #14 w/1 to 3 #16	4 #14 w/1 to 2 #18 1 #16 w/5 to 11 #18 2 #16 w/4 to 9 #18 3 #16 w/2 to 7 #18 4 #16 w/1 to 6 #18 5 #16 w/1 to 4 #18 6 #16 w/1 #18



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Crimp Connectors				
Model	600 Volt Maximum			
410	2 #14 str. 5 to 10 #18 3 to 7 #16 1 #14 sol w/1 #14 str. 3 to 6 #14 2 to 4 #12 2 #10 str. 1 #10 sol w/1 #10 str. 1 #14 w/1 to 3 #12 1 #14 w/1 to 2 #12 w/1 #10 2 #14 w/1 to 2 #12 2 #14 w/1 #10 w/1 #12 3 #14 w/1 to 2 #12 3 #14 w/1 #10 1 #12 w/1 to 4 #14 2 #12 w/1 to 3 #14 2 #12 w/1 #10 2 #10 w/1 to 2 #14 2 #10 w/1 #12 1 #10 w/1 to 4 #14 1 #10 w/1 #12	1 #10 w/2 #12 1 #10 str. or sol w/1 to 2 or 4 to 7 #18 (no combinations with 3 #18) 1 #10 str. or sol w/1 to 6 #16 str. 1 #10 str. w/1 to 6 #16 sol 1 #12 w/1 to 9 #18 or 1 to 7 #16 2 #12 w/1 to 6 #18 or 1 to 4 #16 3 #12 w/1 to 3 #18 or #1 to 2 #16 1 #14 w/1 to 9 #18 1 #14 w/1 to 7 #16 2 #14 w/1 to 8 #18 or 1 to 5 #16 3 #14 w/1 to 5 #18 3 #14 w/1 to 4 #16 4 #14 w/1 to 3 #18 or 1 to 2 #16	1 #16 w/3 to 7 #18 2 #16 w/2 to 8 #18 3 #16 w/1 to 7 #18 4 #16 w/1 to 5 #18 5 #16 w/1 to 4 #18 6 #16 w/1 to 2 #18 7 #16 w/1 #18 1 #10 w/1 #18 w/5 #16 1 #10 w/1 to 3 #18 w/4 #16 1 #10 w/1 to 4 #18 w/3 #16 1 #10 w/1 to 6 #18 w/2 #16 1 #10 w/1 to 8 #18 w/1 #16 2 #10 w/1 to 2 #16 2 #10 w/1 to 2 #18 w/1 #16 2 #10 w/1 to 4 #18 1 #12 w/1 to 2 #18 w/6 #16 1 #12 w/1 to 3 #18 w/5 #16 1 #12 w/1 to 4 #18 w/4 #16 1 #12 w/1 to 5 #18 w/3 #16 1 #12 w/1 to 6 #18 w/2 #16 1 #12 w/1 to 8 #18 w/1 #16	2 #12 w/1 #18 w/4 #16 2 #12 w/1 to 3 #18 w/3 #16 2 #12 w/1 to 4 #18 w/2 #16 2 #12 w/1 to 5 #18 w/1 #16 3 #12 w/1 to 2 #18 w/1 #16 1 #14 w/1 #18 w/6 #16 1 #14 w/1 to 2 #18 w/5 #16 1 #14 w/1 to 4 #18 w/4 #16 1 #14 w/1 to 5 #18 w/3 #16 1 #14 w/1 to 7 #18 w/2 #16 1 #14 w/1 to 8 #18 w/1 #16 2 #14 w/1 #18 w/4 #16 2 #14 w/3 #18 w/3 #16 2 #14 w/5 #18 w/2 #16 2 #14 w/7 #18 w/1 #16 3 #14 w/1 to 2 #18 w/3 #16 3 #14 w/1 to 4 #18 w/2 #16 3 #14 w/1 to 5 #18 w/1 #16 4 #14 w/1 to 2 #18 w/1 #16
Model	600 Volt Maximum			
411	2 #8 2 #8 w/1 #12 2 #8 w/1 to 2 #14 1 #8 w/1 to 2 #10 1 #8 w/1 to 3 #12 1 #8 w/1 to 4 #14	2 to 3 #10 4 #10 sol 3 #10 w/1 #12 3 #10 w/1 to 2 #14, #16, or #18 2 #10 w/1 to 3 #12, #14, or #16 2 #10 w/1 to 3 #18	1 #10 w/2 to 4 #12 1 #10 w/3 to 4 #14 1 #10 w/4 #16 3 to 5 #12 4 #12 w/1 #14, #16, or #18 3 #12 w/1 to 2 #14	3 #12 w/1 to 2 #16 or #18 2 #12 w/2 to 3 #14 2 #12 w/3 #16 1 #12 w/4 #14 5 #14
Model	600 Volt Maximum			
412	1 #4 w/1 to 3 #14 1 #4 w/1 to 2 #12 1 #4 w/1 #10 1 #4 w/1 #8 1 #6 w/1 to 6 #14 1 #6 w/1 to 5 #12 1 #6 w/1 to 3 #10 1 #6 w/1 to 2 #8 2 #6 w/1 #14 or #12 1 #8 w/1 to 5 #14 or #12 1 #8 w/1 to 3 #10 2 #8 w/1 to 5 #14 2 #8 w/1 to 3 #12	2 #8 w/1 to 2 #10 1 #10 w/1 to 6 #18 1 #10 w/1 to 6 #16 1 #10 w/1 to 5 #14 or #12 2 #10 w/1 to 5 #18, #16, or #14 2 #10 w/1 to 5 #12 3 #10 w/1 to 4 #18, #16, or #14 3 #10 w/1 to 3 #12 4 #10 w/1 to 3 #18, #16, or #14 4 #10 w/1 or 2 #12 1 #12 w/1 to 6 #18, #16, or #14 2 #12 w/1 to 5 #18 or #16 2 #12 w/1 to 5 #14	3 #12 w/1 to 3 #18 3 #12 w/1 to 3 #16 3 #12 w/1 to 4 #14 4 #12 w/1 to 3 #18, #16, or #14 5 #12 w/1 or 2 #18, #16, or #14 1 #14 w/2 to 6 #18 1 #14 w/1 to 6 #16 2 #14 w/1 to 5 #18 or #16 3 #14 w/2 to 4 #18 3 #14 w/1 to 3 #16 4 #14 w/1 to 3 #18 or #16 5 #14 w/1 to 2 #18 or #16 6 #14 w/1 #18 or #16	1 #16 w/4 to 6 #18 2 #16 w/2 to 5 #18 3 #16 w/1 to 4 #18 4 #16 w/1 to 3 #18 5 #16 w/1 or 2 #18 6 #16 w/1 #18 2 #6 2 or 3 #8 2 to 5 #10 2 to 6 #12 2 to 7 #14 3 to 7 #16 5 to 7 #18



UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan Crimp Connectors				
Model	600 Volt Maximum			
2006S	2 #18 Stranded through 10 #18 Solid or Stranded #18 w/1 to 6 #16 or 1 to 5 #15 or 1 to 3 #12 or 1 #10 2 #18 stranded w/1 to 5 #16 or 1 to 5 #14 or 1 to 3 #12 or 1 #10 3 #18 w/1 to 5 #16 or 1 to 4 #14 or 1 to 2 #12 4 #18 w/1 to 4 #16 or 1 to 3 #14 or 1 to 2 #12 or 1 #10 5 #18 w/1 to 3 #16 or 1 to 2 #14 or 1 #12 or 1 #10 6 #18 w/1 to 3 #16 or 1 to 2 #14 or 1 #12 7 #18 w/1 to 2 #16 or 1 #14	8 #18 w/1 #16 2 to 7 # 16 1 #16 w/1 to 4 #14 or 1 to 3 #12 or 1 #10 2 #16 w/1 to 3 #14 or 1 to 2 #12 or 1 #10 3 #16 w/1 to 2 #14 or 1 #12 or 1 #10 4 #16 w/1 #14 or 1 #12 2 to 5 #14 1 #14 w/1 to 3 #12 or 1 #10 2 #14 w/1 to 2 # 12 or 1 #10 3 #14 w/1 #12 2 to 4 #12 1 #12 w/1 #10 2 # 10	1 #14 w/1 #12 and 1 #10 2 #14 w/1 #12 and 1 #10 1 #10 w/5 #16 and 1 #18 1 #10 w/4 #16 and 1 to 3 #18 2 #10 w/1 #16 and 1# 18 1 #12 w/5 #16 and 1 to 3 #18 1 #12 w/4 #16 and 1 to 4 #18 1 #12 w/3 #16 and 1 to 5 #18 1 #12 w/2 #16 and 1 to 6 #18 1 #12 w/1 #16 and 1 to 8 #18 2 #12 w/4 #16 and 1 #18 2 #12 w/2 #16 and 1 to 4 #18 2 #12 w/1 #16 and 1 to 5 #18 3 #12 w/1 #16 and 1 to 2 #18 1 #14 w/6 #16 and 1 #18 1 #14 w/5 #16 and 1 to 2 #18	1 #14 w/4 #16 and 1 to 4 #18 1 #14 w/3 #16 and 1 to 5 #18 1 #14 w/2 #16 and 1 to 7 #18 1 #14 w/2 #16 and 1 to 8 #18 2 #14 w/4 #16 and 1 #18 2 #14 w/3 #16 and 3 #18 2 #14 w/2 #16 and 5 #18 2 #14 w/1 #16 and 7 #18 3 #14 w/3 #16 and 1 to 2 #18 3 #14 w/2 #16 and 1 to 4 #18 3 #14 w/1 #16 and 1 to 5 #18 4 #14 w/1 #16 and 1 to 2 #18
Model	600 Volt Maximum			
2011S	Solid Wire 4-10 # 14 3-6 #12 2-4 #10 2 #8	Stranded Wire 5 to 11 # 14 3 to 7 #12 2 to 5 #10 2 to 3 #8 2 #6	Combination Stranded Wire 1 to 3 #14 w/3 to 5 #12 1 to 3 #14 w/3 to 4 #10 1 to 2 #12 w/3 to 4 #10 1 to 3 #12 w/5 to 8 #14 2 or 4 # 14 w/1 #8 or 1 #10 1 #8 w/1 #10v	Combination Stranded & Solid 1 to 3 #14 w/3 to 5 #12 1 to 3 #14 w/3 to 4 #10 1 to 2 #12 w/3 to 4 #10 1 to 3 #12 w/5 to 8 #14 1 #4 stranded w/1 #8 or 1 #10 1 #6 stranded w/1 #8 or 1 #10 1 #8 w/1 #10 2 or 4 #14 solid w/1 #8 str.
Model	600 Volt Maximum			
2008S	2 to 10 #18 1 #18 w/1 to 6 #16 or 1 to 5 #14 or 1 to 3 #12 or 1 #10 2 #18 w/1 to 5 #16 or 1 to 5 #14 or 1 to 3 #12 or 1 #10 2 #16 w/1 to 3 #14 or 1 to 2 #12 or 1 #10 3 #16 w/1 to 2 #14 or 1 #12 or 1 #10 4 #16 w/1 #14 or 1#12 2 to 5 #14	1 #14 w/1 to 3 #12 or 1 #10 2 #14 w/1 to 2 #12 or 1 #10 3 #14 w/1 #12 2 to 4 #12 1 #12 w/1 #10 2 #10 1 #14 w/1 #12 and 1 #10 2 #14 w/1 #12 and 1 #10 1 #10 w/5 #16 and 1 #18 1 #10 w/4 #16 and 1 to 3 #18 2 #10 w/1 #16 and 1 #18	1 #12 w/5 #16 and 1 to 3 #18 1 #12 w/4 #16 and 1 to 4 #18 1 #12 w/3 #16 and 1 to 5 #18 1 #12 w/2 #16 and 1 to 6 #18 2 #12 w/1 #16 and 1 to 2 #18 1 #14 w/6 #16 and 1 #18 1 #14 w/5 #16 and 1 to 2 #18 1 #14 w/4 #16 and 1 to 4 #18 1 #14 w/3 #16 and 1 to 5 #18 1 #14 w/2 #16 and 1 to 7 #18 1 #14 w/1 #16 and 1 to 8 #18	2 #14 w/4 #16 and 1 #18 2 #14 w/3 #16 and 3 #18 2 #14 w/2 #16 and 5 #18 2 #14 w/1 #16 and 7 #18 3 #14 w/3 #16 and 1 to 2 #18 3 #14 w/2 #16 and 1 to 4 #18 3 #14 w/1 #16 and 1 to 5 #18 4 #14 w/1 #16 and 1 to 2 #18
Term-End Lugs				
Model	Solid Wire		Stranded Wire	
16-8	1 to 8 #16 1 to 4 #14	1 to 2 #12 1 #10	1 to 8 #16 1 to 5 #14	1 to 3 #12 1 #8
IDEAL Term-A-Nut™ Pigtail Connectors and Grounding Connectors				
70 Red w/blk or white Green w/grn	2 to 4 #12 or #14 4 to 5 # 16 1 #16 w/3 to 4 #18 2 #16 w/2 to 3 #18 3 #16 w/1 to 2 #18 4 #16 w/1 #18 1 #14 w/ 2-3 #18	2 #14 w/1 to 2 #18 3 #14 w/1 #18 1 #14 w/2 to 3 #16 2 #14 w/1 to 2 #16 3 #14 w/1 #16 1 #12 w/2 to 3 #18 2 #12 w/1 to 2 #18	3 #12 w/1 #18 1 #12 w/1 to 3 #16 2 #12 w/1 to 2 #16 3 #12 w/1 #16 1 #12 w/1 to 3 #14 2 #12 w/1 to 2 #14 3 #12 w/ 1 #14	

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [ideal manufacturer](#):

Other Similar products are found below :

[30-696](#) [74-027](#) [45-292](#) [45-098](#) [L-5361](#) [45-093](#) [45-177](#) [45-1987-1](#) [41-990](#) [25HK-AY-090A266-DH](#) [15DYS6150-2400625P](#) [45-418](#) [30-503](#)
[35-020](#) [35-060](#) [35-516](#) [45-1633-1](#) [45-170](#) [45-1773-1](#) [45-1774](#) [45-1939-1](#) [45-2133-1](#) [45-298](#) [45-372](#) [K-6336](#) [K-8906R](#) [L-4866](#) [L-5210](#) [L-](#)
[5562](#) [L-9038](#) [LB-1091](#) [35-522](#) [61-775](#) [KB-0276R](#) [30-429](#) [30-587](#) [33-856](#) [45-672](#) [45-171](#) [45-144](#) [34-015](#) [33-864](#) [30-506](#) [25HK-AP-](#)
[060A100-CP-3A](#) [15DYS624-240125W-K](#) [15DYS6150-4800312P](#) [33-704](#) [45-092](#) [45-121](#) [45-1513](#)