




PRODUCT BRIEF

Intel® Dual Band Wireless-AC 8265

4th Generation Intel 802.11ac, Dual Band, 2x2 Wi-Fi + Bluetooth® 4.2



Intel® Dual Band Wireless-AC 8265



Ultra Wi-Fi. Ultra Features. Ultra Connected Experience

The Intel® Dual Band Wireless-AC 8265 adapter supports Bluetooth® 4.2 and 2x2 11ac Wi-Fi delivering up to 867Mbps¹ including wave 2 features such as downlink MU-MIMO providing up to 3x increase in user speeds in dense deployments, supporting fast downloads and long battery life compared to legacy 11ac devices². Combined with Intel® Core™ processors and exceptional Intel wireless innovations, the Intel® Dual Band Wireless-AC 8265 dramatically reshapes your connected experience at home, work or on the go.

4th Generation Intel 802.11ac Wireless



**Faster Speed
Better Coverage
Larger Capacity**

802.11ac, Dual Band, 80MHz, 2x2, MU-MIMO

Delivers up to 3x faster Wi-Fi speeds (up to 867 Mbps) than 802.11n, with up to 3x more bandwidth per stream for more users and devices³. Downlink MU-MIMO allows an Access Point to simultaneously transmit data to multiple clients and can improve overall downlink network capacity by up to 3x². Intel® Wireless-AC enables smoother streaming of higher resolution videos, fewer dropped connections and less congestion, and faster speed further away from the router.



Bluetooth® 4.2

Dual mode Bluetooth® 4.2 enables BR/EDR-low energy devices to act as a hub and peripheral at the same time. Connects to the newest low energy Bluetooth® products as well as your familiar devices, such as headsets, keyboard, mice and more.



Microsoft Windows* 10 Ready

Full support for latest Microsoft Windows* 10 OS.



**M.2 2230 or M.2 1216
Form Factors**

Multiple form-factors, including M.2 2230 and M.2 1216 modules enable system configuration and platform usages flexibility. The M.2 1216 form factor delivers 70% smaller footprint and lower profile optimized for thin-and-light designs⁴.

Experience the Intel Difference



**Worldwide Regulatory Support
Intel® Dynamic Regulatory Solution**

Enables worldwide regulatory compliance on a single Intel® Wireless-AC adapter SKU. The Intel® Dual Band Wireless-AC 8265 detects its location and automatically optimizes the Wi-Fi settings to local regulatory requirements, simplifying travel experience and global enterprise procurement. Future regulatory changes are easily managed during the product lifecycle.

Business-Class Wireless



Intel® vPro™ Technology⁵

Supports Intel's hardware-based security and management features built into Intel® Core™ vPro™ processors and chipsets that enables IT to manage PCs virtually anywhere, anytime while reducing deployment costs, improving security and ROI.



**Intel® Active Management
Technology⁶**

Using integrated platform capabilities and popular third-party management and security applications, Intel® AMT allows IT or managed service providers to better discover, repair, and protect their networked computing assets. Intel® AMT is a feature of Intel® Core™ processors with Intel® vPro™ technology.



Intel® PROSet/Wireless Software⁷

Includes advanced IT tools to improve security, reduce complexity and save IT time and money. Streamlines client deployments and allows remote management of wireless settings and profiles by IT managers.

Intel® Dual Band Wireless-AC 8265 Technical Specifications

General

Dimensions (H x W x D)	M.2 2230: 22 mm x 30 mm x 2.4 mm [1.5mm Max (Top Side)/ 0.1mm Max (Bottom Side)] M.2 1216: 12 mm x 16 mm x 1.8 mm
Weight	M.2 2230: 2.6g M.2 1216: 0.6g
Antenna Diversity	Supported
Radio ON/OFF Control	Supported
Connector interface	M.2: PCIe, USB, or UART (M.2 1216 only)
Operating Temperature (Adapter Shield)	0°C to +80°C
Humidity Non-Operating	50% to 90% RH non-condensing (at temperatures of 25°C to 35°C)
Operating Systems	Microsoft Windows 7*, Microsoft Windows 8.1*, Microsoft Windows 10*, Linux* (limited feature support), Android
Wi-Fi Alliance	Wi-Fi CERTIFIED* a/b/g/n/ac, WMM*, WMM-PS*, WPA*, WPA2*, WPS2*, Protected Management Frames, Wi-Fi Direct* for peer to peer device connections, Wi-Fi Miracast* as Source.
IEEE WLAN Standard	IEEE 802.11a/b/g/n/ac, 802.11d, 802.11e, 802.11h, 802.11i, 802.11w; 802.11r, 802.11k, 802.11v pending OS support; Fine Timing Measurement based on 802.11REVmc
Roaming ⁸	Supports seamless roaming between access points
Bluetooth [®]	Dual Mode Bluetooth [®] 4.2, BLE

Security⁹

Authentication	WPA and WPA2, 802.1X (EAP-TLS, TTLS, PEAP, LEAP, EAP-FAST), EAP-SIM, EAP-AKA, EAP-AKA'
Authentication Protocols	PAP, CHAP, TLS, GTC, MS-CHAP*, MS-CHAPv2
Encryption	64-bit and 128-bit WEP, 128-bit AES-CCMP
Wi-Fi Direct* Encryption and Authentication	WPA2-PSK, AES-CCMP

Compliance

Regulatory	For a list of country approvals, please contact your local Intel representatives.
US Government	FIPS ¹⁰ , FISMA
Product Safety	UL, C-UL, CB (IEC 60950-1)

Product Name	Model Number	Version
Intel® Dual Band Wireless-AC 8265	8265NGW	802.11ac, 2x2, Bluetooth [®] 4.2, PCIe, USB, M.2 2230 MS
Intel® Dual Band Wireless-AC 8265	8265D2W	802.11ac, 2x2, Bluetooth [®] 4.2, PCIe, LTE Coexistence, M.2 1216 SD



For more information on Intel® Wireless products, visit intel.com/wireless

¹ Based on the theoretical maximum bandwidth enabled by 2x2 802.11ac implementations. Actual wireless throughput and/or range will vary depending on your specific operating system, hardware and software configurations. Check with your device manufacturer for details.

² 802.11ac downlink MU-MIMO technology allows concurrently serving multiple devices simultaneously, in turn increasing network capacity by up to 3x while improving per-user throughput.

³ Compared to 802.11n 40MHz channels, 802.11ac 80MHz provides 3x more bandwidth per stream (Max data rate for 2x2 802.11n 40MHz channel is 300Mbps, 150Mbps per stream; Max data rate for 2x2 802.11ac 80MHz channel is 867Mbps, 433Mbps per stream).

⁴ Compared to the footprint of an M.2 2230 module. An M.2 1216 module is 192mm² (12mmx16mm), approximately 70% smaller than the footprint of a M.2 2230 module (22mmx30mm = 660mm²)

⁵ Intel® vPro™ Technology is sophisticated and requires setup and activation. Availability of features and results will depend upon the setup and configuration of your hardware, software and IT environment. To learn more visit: <http://www.intel.com/technology/vpro>

⁶ Requires activation and a system with a corporate network connection, an Intel® AMT-enabled chipset, network hardware and software. For notebooks, Intel® AMT may be unavailable or limited over a host OS-based VPN, when connecting wirelessly, on battery power, sleeping, hibernating or powered off. Results dependent upon hardware, setup & configuration. For more information, visit <http://www.intel.com/technology/platform-technology/intel-amt>

⁷ Intel® PROSet/Wireless Software may not be supported by your device manufacturer. Check with your device manufacturer for details on availability.

⁸ Roaming is supported only within each respective band and mode of access points.

⁹ Some security solutions may not be supported by your device operating system and/or by your device manufacturer. Check with your device manufacturer for details on availability.

¹⁰ Microsoft Windows* 7, Microsoft Windows* 8.1, and Microsoft Windows* 10.


Software and workloads used in performance tests may have been optimized for performance only on Intel microprocessors. Performance tests, such as SYSmark and MobileMark, are measured using specific computer systems, components, software, operations and functions. Any change to any of those factors may cause the results to vary. You should consult other information and performance tests to assist you in fully evaluating your contemplated purchases, including the performance of that product when combined with other products.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Intel's Terms and Conditions of Sale for such products, Intel assumes no liability whatsoever, and Intel disclaims any express or implied warranty, relating to sale and/or use of Intel products including without limitation, liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Intel products are not intended for use in medical, lifesaving, or life sustaining applications. Intel may make changes to specifications and product descriptions at any time, without notice. For the most current product information, please visit: <http://www.intel.com/wireless>

Intel, the Intel logo, and Intel are trademarks or registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries.

*Other names and brands may be claimed as the property of others. For more information visit: <http://www.intel.com/content/www/us/en/legal/trademarks.html>

Copyright © 2016 Intel Corporation. All rights reserved.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [intel](#) manufacturer:

Other Similar products are found below :

[LW80603003240AAS LC39](#) [CT80618003201ABS LJ38](#) [FH8065802064011S R26H](#) [R1304RPOSHBN](#) [12200BS23MM](#)
[AT80612003090AAS LBWJ](#) [AXXCBL875HDHD](#) [NU3210MC S LJEF](#) [P82510](#) [PBA31309V1.00 S LK64](#) [EXPI9400PF](#) [FH8065301619509S](#)
[R1SJ](#) [FH8065801618304S R23V](#) [CL8064701575100SR1H1](#) [CM8063401376501S R1B0](#) [CM8063501287304S R19W](#) [CM8063501287602S](#)
[R19Y](#) [CM8063501374802S R1A5](#) [CM8063501375101S R1A8](#) [CM8064601483644S R1PK](#) [CM8064601560113S R1QF](#)
[CM8066201920404S R2L6](#) [CW8064701486802S R1HC](#) [403708R](#) [AT80571PH0772MLS LGUH](#) [AXXCBL650HDHD](#) [BD82QM67 S LJ4M](#)
[I350F2BLK](#) [IOTGTWY.DK300](#) [D8086-2](#) [E10G42BTDAG1P5](#) [CM8062100854905S R0LX](#) [CM8063401294008S R1AV](#)
[CM8063401376602S R1B1](#) [CM8063501374901S R1A6](#) [CM8064601560615S R1QJ](#) [CM8066201919901 SR2L0](#) [CM8066201938802S R2LU](#)
[CP80617004122AGS LBVT](#) [CM8064601466003S R14P](#) [CM8063501293200S R1A0](#) [CM80616003060AES LBTD](#) [CT80618005844AAS](#)
[LJ32](#) [JL82599EN S R1ZS](#) [AT80574JJ053NS LBBS](#) [FF8062700853304S R02U](#) [FH8065802063212S R268](#) [GCIXP1200GA](#) [GCIXP1240AA](#)
[GCIXP1250BA](#)