



industrial RFID reader **RFID IND-LED**



Application

- ✓ RFID tags reading
- ✓ identification of persons
- ✓ access control
- ✓ warehouse staff
- ✓ working time control
- ✓ data input
- ✓ starting machines

Characteristic

- Reading RFID TAG
- Reading and recording card contents * for selected transponders
- Module control through the HTTP (client/server), SNMP
- Built-in web server
- Modbus TCP and RTU communication
- Built-in memory: 1000 users and 30,000 logs
- Control of built-in relay outputs
- Configuration of relay outputs (bistable, astable, time)
- Input status control
- LED control  or 



RFID IND-LED Slot
housing option with card slot



Technical data

Supply voltage	10-24VDC and PoE 802.3af or PoE Passive 10-24VDC
Power consumption	max 2.5W (~ 200mA @ 12V)
Housing	IP65
Operating environment	-10°C to + 55°C
Dimensions	100 (W) x 100 (H) x 55,6 (D) mm

Transponders depending on the device version:

Mifare Classic® (ISO/IEC 14443-A)*	13.56MHz	RFID IND-LED Mif
Mifare Plus® (UID), Mifare DESFire® (UID)		
Unique EM4100 EM4102	125kHz	RFID IND-LED Uni
HID iClass® (only CSN)	13.56MHz	RFID IND-LED iCla
HID 125kHz	125kHz	RFID IND-LED H125
ICODE® (ISO 15693)*	13.56MHz	RFID IND-LED Ico
HITAG (HITAG 2)	125kHz	RFID IND-LED HT2

Communication

1 RS485 port	modbus RTU
1 Ethernet port	configuration and communication

Inputs / Outputs

2 inputs	dry contact, type NO
2 outputs	relay, max load 1A at 30V DC (NO / Uzas)

We also recommend:

RFID USB Desk
desk RFID reader



RFID IND-LCD
industrial RFID reader



RFID TAB
panel RFID reader



RFID reader
entirely designed and made by
a Polish company

inveo 



INVEO - Innovative, Necessary, Visionary,
Economic, Optimum

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Inveo manufacturer](#):

Other Similar products are found below :

[DS-1](#) [DS-10](#) [DS-5](#) [HERO WEB SENSOR](#) [IND-U2 \(POE\)](#) [IND-U4 \(POE\)](#) [LANTICK PE-0-1](#) [LANTICK PE-0-16](#) [LANTICK PE-0-8](#)
[LANTICK PE-1-0](#) [LANTICK PE-1-1](#) [LANTICK PE-16-0](#) [LANTICK PE-2-2](#) [LANTICK PE-4-4](#) [NANO ANALOG INPUT POE](#) [NANO](#)
[DIGITAL INPUT POE](#) [NANO IN](#) [NANO OUT](#) [NANO RELAY OUTPUT POE](#) [NANO RFID](#) [NANO RFID POE](#) [NANO TC SENSOR](#)
[NANO TEMP](#) [NANO TEMP + CZUJNIK](#) [NANO TEMPERATURE SENSOR POE](#) [RFID IND LED H125](#) [RFID IND LED H125 SLOT](#)
[RFID IND LED HT2 POE](#) [RFID IND LED ICLA](#) [RFID IND LED MIF](#) [RFID IND LED MIF POE](#) [RFID IND LED MIF SLOT](#) [RFID IND](#)
[MODBUS MIF/ IND-M1](#) [RFID IND-U2](#) [RFID IND-U4](#) [RFID MODBUS IND-U1](#) [RFID-USB-DESK](#) [RFID USB DESK HIT](#) [RFID USB](#)
[DESK ICO](#) [RFID-USB-DESK \(MIF\)](#) [RFID USB POCKET](#) [WEBSSENS COMBO](#) [WEBSSENS HT](#) [WEBSSENS T](#)