




SCHOTTKY DIODES

SOD-123



FEATURES

- Low forward voltage drop
- Guard ring construction for transient protection
- Negligible reverse recovery time
- Low reverse capacitance

MARKING: SD103AW: S4
 SD103BW: S5
 SD103CW: S6

Maximum Ratings and Electrical Characteristics, Single Diode @T_A=25°C

Parameter	Symbol	SD103AW	SD103BW	SD103CW	Unit
Peak Repetitive Peak reverse voltage	V _{RRM}				
Working Peak DC Blocking Voltage	V _{RWM}	40	30	20	V
RMS Reverse Voltage	V _{R(RMS)}	28	21	14	V
Forward Continuous Current	I _{FM}	350			mA
Repetitive Peak Forward Current @t≤1.0s	I _{FRM}	1.5			A
Power Dissipation	P _d	500			mW
Thermal Resistance Junction to Ambient	R _{θJA}	250			°C/W
Storage temperature	T _{STG}	-65~+150			°C

Electrical Ratings @T_A=25°C

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Reverse Breakdown Voltage	SD103AW SD103BW SD103CW	40 30 20			V	I _R =100μA
Forward voltage	V _F			0.37 0.60	V	I _F =20mA I _F =200mA
Reverse current	SD103AW SD103BW SD103CW			5.0	μA	V _R =30V V _R =20V V _R =10V
Capacitance between terminals	C _T		50		pF	V _R =0V, f=1.0MHz
Reverse Recovery Time	t _{rr}		10		ns	I _F =I _R =200mA I _{rr} =0.1X I _R , R _L =100Ω



Typical Characteristics




Fig. 1 Typical Forward Characteristics




Fig. 2 Typ. Junction Capacitance vs Reverse Voltage

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Schottky Diodes & Rectifiers](#) category:

Click to view products by [Jinyu](#) manufacturer:

Other Similar products are found below :

[CUS06\(Te85L,Q,M\)](#) [MA4E2039](#) [D1FH3-5063](#) [MBR0530L-TP](#) [MBR10100CT-BP](#) [MBR30H100MFST1G](#) [MMBD301M3T5G](#) [PMAD1103-LF](#) [PMAD1108-LF](#) [RB160M-50TR](#) [RB520S-30](#) [RB551V-30](#) [DD350N18K](#) [DZ435N40K](#) [DZ600N16K](#) [BAS16E6433HTMA1](#) [BAS 3010S-02LRH E6327](#) [BAT 54-02LRH E6327](#) [IDL02G65C5XUMA1](#) [NSR05F40QNXT5G](#) [NSVR05F40NXT5G](#) [JANS1N6640](#) [SB07-03C-TB-H](#) [SB1003M3-TL-W](#) [SBAT54CWT1G](#) [SBM30-03-TR-E](#) [SBS818-TL-E](#) [SK32A-LTP](#) [SK33A-TP](#) [SK34A-TP](#) [SK34B-TP](#) [SMD1200PL-TP](#) [ACDBN160-HF](#) [SS3003CH-TL-E](#) [STPS30S45CW](#) [PDS3100Q-7](#) [GA01SHT18](#) [CRS10I30A\(Te85L,QM\)](#) [MBR1240MFST1G](#) [MBRB30H30CT-1G](#) [BAS28E6433HTMA1](#) [BAS 70-02L E6327](#) [HSB123JTR-E](#) [JANTX1N5712-1](#) [VS-STPS40L45CW-N3](#) [DD350N12K](#) [SB007-03C-TB-E](#) [SB10015M-TL-E](#) [SB1003M3-TL-E](#) [SK110-LTP](#)