


HIGH CURRENT APPLICATION.

FEATURE


- Complementary to KTC8550S.

MAXIMUM RATING (Ta=25 °C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Collector-Base Voltage	V _{CBO}	35	V
Collector-Emitter Voltage	V _{CEO}	30	V
Emitter-Base Voltage	V _{EBO}	5	V
Collector Current	I _C	800	mA
Emitter Current	I _E	-800	mA
Collector Power Dissipation	P _C *	350	mW
Junction Temperature	T _j	150	
Storage Temperature Range	T _{stg}	-55 ~ 150	

* P_C : Package Mounted On 99.5% Alumina (10 × 8 × 0.6mm)

Marking








ELECTRICAL CHARACTERISTICS (Ta=25 °C)

CHARACTERISTIC	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Collector Cut-off Current	I _{CBO}	V _{CB} =15V, I _E =0	-	-	50	nA
Collector-Base Breakdown Voltage	V _{(BR)CBO}	I _C =0.5mA, I _E =0	35	-	-	V
Collector-Emitter Breakdown Voltage	V _{(BR)CEO}	I _C =1mA, I _B =0	30	-	-	V
DC Current Gain	h _{FE} (1) (Note)	V _{CE} =1V, I _C =50mA	100	-	300	
	h _{FE} (2)	V _{CE} =1V, I _C =350mA	60	-	-	
Collector-Emitter Saturation Voltage	V _{CE(sat)}	I _C =500mA, I _B =20mA	-	-	0.5	V
Base-Emitter Voltage	V _{BE}	V _{CE} =1V, I _C =500mA	-	-	1.2	V
Transition Frequency	f _T	V _{CE} =5V, I _C =10mA	-	120	-	MHz
Collector Output Capacitance	C _{ob}	V _{CB} =10V, f=1MHz, I _E =0	-	13	-	pF

Note : h_{FE}(1) Classification C : 100 200, D : 150 300

KTC8050S



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Bipolar Transistors - BJT category:

Click to view products by KEC manufacturer:

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MMBT-2369-TR](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NJVMJD148T4G](#) [NTE123AP-10](#) [NTE153MCP](#) [NTE16](#)
[NTE195A](#) [NTE92](#) [C4460](#) [2N4401-A](#) [2N6728](#) [2SA1419T-TD-H](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SC2712S-GR,LF](#) [2SC5488A-TL-H](#)
[2SD2150T100R](#) [SP000011176](#) [2N2907A](#) [2N3904-NS](#) [2N5769](#) [2SC2412KT146S](#) [2SD1816S-TL-E](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#)
[MJE340](#) [US6T6TR](#) [NJK0281DG](#) [732314D](#) [CPH3121-TL-E](#) [CPH6021-TL-H](#) [873787E](#) [IMZ2AT108](#) [UMX21NTR](#) [MCH6102-TL-E](#)
[NJK0302DG](#) [2N3583](#) [30A02MH-TL-E](#) [NSV40301MZ4T1G](#) [NTE13](#) [NTE26](#) [NTE282](#) [NTE323](#) [NTE350](#) [NTE81](#) [STX83003-AP](#)