

KXTJ2 Accelerometer

2x2x0.9mm Low-Power Accelerometer



FEATURES

- Ultra-small Package - 2x2x0.9mm LGA
- User-selectable g Range and Output Data Rate
- 8-bit, 12-bit, and 14-bit Resolution
- Low Power Consumption
- Internal voltage regulator
- User-configurable wake-up function
- Digital I²C
- Lead-free Solderability
- Excellent Temperature Performance
- High Shock Survivability
- Factory Programmable Offset and Sensitivity
- Self-test Function

APPLICATIONS

- User Interface
- Power Management
- Active/Inactive Monitoring
- Device Orientation
- Inclination and Tilt Sensing
- Gesture Recognition
- Pedometer/Activity Monitoring


FOR

- Smartphones and Mobile Devices
- Laptops
- Gaming and Virtual Reality
- Health and Fitness

PRODUCT OVERVIEW

The KXTJ2 is one of our smallest tri-axis accelerometers, designed for mobile applications. It offers excellent power performance along with an embedded motion wake-up feature, Fast-mode I²C and up to 14-bit resolution. The KXTJ2 is delivered in a 2 x 2 x 0.9 mm, 12-pin, LGA package with an operating temperature range of -40°C to +85°C.

The KXTJ2 sensor offers improved shock, reflow, and temperature performance, and the ASIC has internal voltage regulators that allow operation from 1.8 V to 3.6 V within the specified product performance.



KXTJ2 Accelerometer

2x2x0.9mm Low-Power Accelerometer



The performance parameters below are programmed and tested at 2.6 volts and T = 25°C. The device can accept supply voltages from 1.8V to 3.6V. Due to internal voltage regulators, there should be minimal change with supply voltage variations.

PERFORMANCE SPECIFICATIONS			
PARAMETERS	UNITS	KXTJ2-1009	CONDITION
Range	g	±2.0, ±4.0, ±8.0	User-selectable full-scale output range
Sensitivity ¹	counts/g	64, 32, 16	8-bit
		1024, 512, 256	12-bit
		1024 typical	14-bit ²
0g Offset vs. Temp	mg/°C	0.2	-40°C to +85°C
Sensitivity vs. Temp	%/°C	±0.01 (xy) ±0.03 (z) typical	-40°C to +85°C
Mechanical Resonance ³	Hz	3500 (xy) 1800 (z) typical	-3dB
Output Data Rate (ODR) ⁴	Hz	0.781 min; 50 typical; 1600 max	
Bandwidth (-3dB) ⁵	Hz	800	RES = 0
		ODR/2	RES = 1
Non-Linearity	% of FS	1.0 typical	% of full scale output
Cross-axis Sensitivity	%	2.0 typical	
I ² C Communication Rate	MHz	3.4 max	
Power Supply	V	2.6 typical	1.8V – 3.6V
Current Consumption ⁶	µA	135 typical	High resolution (RES = 1)
		10 typical	Low resolution (RES = 0)
		2 typical	Standby
ENVIRONMENTAL SPECIFICATIONS			
PARAMETERS	UNITS	KXTJ2-1009	CONDITION
Operating Temperature	°C	-40 to 85	Powered
Storage Temperature	°C	-55 to 150	Un-powered
Mechanical Shock	g	5,000, 0.5 ms 10,000, 0.2 ms	Powered or un-powered, halversine
ESD	V	2,000	Human body model

NOTES

- ¹ Resolution and acceleration ranges are user selectable via I2C.
- ² 14-bit Resolution is only available for registers 0x06h – 0x0Bh in the 8g Full Power mode.
- ³ Resonance as defined by the dampened mechanical sensor.
- ⁴ User selectable through I2C.
- ⁵ User selectable; dependent on ODR and RES.
- ⁶ Current varies with Output Data Rate (ODR).

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Acceleration Sensor Development Tools](#) category:

Click to view products by [Kionix](#) manufacturer:

Other Similar products are found below :

[2019](#) [EVAL-ADXL343Z-S](#) [BRKOUT-FXLN8362Q](#) [MXC6655XA-B](#) [1018](#) [EVAL-ADXL362-ARDZ](#) [EVAL-KXTJ2-1009](#) [1231](#) [1413](#) [DEV-13629](#) [2020](#) [EVAL-ADXL343Z-DB](#) [EVAL-ADXL344Z-M](#) [EVAL-ADXL375Z-S](#) [EV-BUNCH-WSN-1Z](#) [EV-CLUSTER-WSN-2Z](#) [STEVAL-MKI033V1](#) [EVAL-ADXL344Z-DB](#) [EVAL-ADXL346Z-DB](#) [EVAL-ADXL363Z-MLP](#) [EV-CLUSTER-WSN-1Z](#) [ADIS16203/PCBZ](#) [2472](#) [EVAL-ADXL312Z](#) [EVAL-ADXL343Z](#) [EVAL-ADXL344Z-S](#) [EVAL-ADXL363Z-S](#) [EVAL-ADXL375Z](#) [STEVALMKI032V1](#) [DFR0143](#) [SEN0032](#) [SEN0079](#) [SEN0168](#) [SEN0224](#) [MXD6240AU-B](#) [FIT0031](#) [SEN-13963](#) [MXP7205VW-B](#) [ASD2511-R-A](#) [3463](#) [SEN0140](#) [SEN0183](#) [SEN-11446](#) [EVAL-KX022-1020](#) [EVAL-KX023-1025](#) [163](#) [2809](#) [4097](#) [4344](#) [4627](#)