

KXTIK Accelerometer

3x3x0.9mm Accelerometer with FIFO/FILO Buffer



FEATURES

- Small Package - 3x3x0.9mm LGA
- User-selectable g Range
- User-selectable Output Data Rate
- Enhanced integrated Directional Tap/Double-Tap™, Activity-monitoring, and Device-orientation Algorithms
- Digital I²C
- 8-bit or 12-bit Resolution
- FIFO/FILO Memory Buffer
- Digital High-Pass and Low-Pass Filter Outputs
- Low Power Consumption
- Lead-free Solderability
- Excellent Temperature Performance
- High Shock Survivability
- Factory Programmable Offset and Sensitivity
- Self-test Function

APPLICATIONS

- User Interface
- Active/Inactive Monitoring
- Device Orientation
- Gesture Recognition
- Tap Detection
- Pedometer/Activity Monitoring

FOR

- Smartphones and Mobile Devices
- Gaming and Virtual Reality
- Health and Fitness


PRODUCT OVERVIEW



The Kionix KXTIK is a low power, high performance tri-axis accelerometer with digital I²C output. The KXTIK features user-selectable parameters including 8-bit or 12-bit modes, g-ranges from ± 2g, 4g or 8g, and Output Data Rates from 12.5 Hz to 800 Hz. A 252 byte FIFO/FILO buffer offers programmable watermark interrupt and provides a triggered low resolution or high resolution mode.

The KXTIK features a 16-pin package, making it pin compatible with popular products on the market. The KXTIK also offers enhanced embedded Screen Rotation, Directional Tap/Double Tap, Orientation Detection and Low Power Motion Interrupt.

The KXTIK has an internal voltage regulator that allows operation from 1.8 V to 3.6 V with an operating temperature range of -40°C to +85°C.



KXTIK Accelerometer

3x3x0.9mm Accelerometer with FIFO/FILO Buffer



The performance parameters below are programmed and tested at 2.6 volts and T = 25°C. The device can accept supply voltages from 1.8V to 3.6V. Due to internal voltage regulators, there should be minimal change with supply voltage variations.

PERFORMANCE SPECIFICATIONS			
PARAMETERS	UNITS	KXTIK-1004	CONDITION
Range	g	±2.0, ±4.0, ±8.0	User-selectable full-scale output range
Sensitivity ¹	counts/g	64, 32, 16	8-bit
		1024, 512, 256	12-bit
0g Offset vs. Temp	mg/°C	±0.7 (xy) ±0.4 (z) typical	-40°C to +85°C
Sensitivity vs. Temp	%/°C	±0.01 (xy) ±0.03 (z) typical	-40°C to +85°C
Mechanical Resonance ²	Hz	3500 (xy) 1800 (z) typical	-3dB
Output Data Rate (ODR) ³	Hz	12.5 min; 50 typical; 800 max	
Bandwidth (-3dB) ⁴	kHz	1.59	RES = 0
	Hz	ODR/2	RES = 1
Non-Linearity	% of FS	0.6 typical	% of full scale output
Cross-axis Sensitivity	%	2.0 typical	
I ² C Communication Rate	kHz	400 max	
Power Supply	V	2.6 typical	1.8V – 3.6V
Current Consumption	µA	325 typical	High resolution (RES = 1)
		165 typical	Directional Tap™, RES = 0; ODR = 400Hz
		100 typical	Low resolution; RES = 0; ODR ≤ 25Hz
		10 typical	Standby

ENVIRONMENTAL SPECIFICATIONS

PARAMETERS	UNITS	KXTIK-1004	CONDITION
Operating Temperature	°C	-40 to 85	Powered
Storage Temperature	°C	-55 to 150	Un-powered
Mechanical Shock	g	5,000, 0.5 ms 10,000, 0.2 ms	Powered or un-powered, halversine
ESD	V	2,000	Human body model

NOTES

¹ Resolution and acceleration ranges are user selectable via I2C.

² Resonance as defined by the dampened mechanical sensor.

³ User selectable through I2C.

⁴ User selectable; dependent on ODR and RES.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Accelerometers](#) category:

Click to view products by [Kionix](#) manufacturer:

Other Similar products are found below :

[AD22372Z-RL7](#) [ADXL313WACPZ-RL](#) [805M1-0050-01](#) [MXC6655XA](#) [MMA7455LT](#) [805M1-0200-01](#) [810M1-0025X](#) [AIS328DQTR](#)
[832M1-0050](#) [805-0050](#) [AD22301](#) [ADXL354BEZ](#) [SCA620-EF8H1A-1](#) [MC3413](#) [MXC6244AU](#) [3038-0500](#) [ACH-01-04/10](#) [4692](#)
[ADXL372BCCZ-RL7](#) [735T](#) [787-500](#) [787AM8](#) [793-6](#) [793L](#) [997-M4](#) [HV101](#) [HV102](#) [HV200](#) [PC420VP-50](#) [PC420VR-10](#) [786A](#) [786A-IS](#)
[787A](#) [787A-IS](#) [HT786A](#) [HT787A](#) [PC420VP-10](#) [ADCMXL1021-1BMLZ](#) [ADIS16003CCCZ](#) [ADIS16006CCCZ](#) [ADIS16228CMLZ](#)
[ADXL700WBRWZ-RL](#) [ADXL1003BCPZ](#) [ADXL103CE-REEL](#) [ADXL203CE-REEL](#) [ADXL206HDZ](#) [ADXL213AE](#) [ADXL213AE-REEL](#)
[ADXL288WBRDZ-RL](#) [ADXL295WBRDZ-RL](#)