

## DIGITAL MULTIMETER

# KPS-MT440



- Digital multimeter
- 4000 counts
- Measurements of DC / AC voltage, DC / AC current, resistance, capacity, frequency and duty cycle
- Non-contact voltage detection
- Continuity warning and diode test
- Automatic scale
- Relative measurements
- Hold readings on screen
- Auto power off, backlight display and low battery indication
- CAT.IV 600V according to EN 61010

# KPS-MT440

## DIGITAL MULTIMETER

General	
Power Supply	1x9V 6F22 Battery
Product Size	175mm × 86mm × 52mm
Product Weight	372g
Certificate	CE/ETL/RoHS
Safety Rating	-CAT IV 600V

Specs	
Display Counts	4000
Manual Range	✓
Auto Power Off	✓
Data Hold	✓
Diode	1.5V
Continuity Buzzer	<50±20Ω
Relative Measurement	✓
Non-Contact Voltage Detector	✓
Display Backlight	✓

# KPS-MT440

## DIGITAL MULTIMETER

Specs	Range	Resolution	Accuracy
DC Voltage	400mV	0.1mV	± (0.8% + 3 digits)
	4V/40V/400V/600V	1mV/10mV/0.1V/1V	± (0.5% + 5 digits)
AC Voltage	400mV	0.1mV	± (1.0% + 5 digits)
	4V/40V/400V	1mV/10mV/0.1V	± (0.8% + 5 digits)
DC Current	400µA/4000µA/40mA/400mA	0.1µA/1µA/10µA/0.1mA	± (0.8% + 2 digits)
	10A	10mA	± (2.0% + 5 digits)
AC Current	400µA/4000µA/40mA/400mA	0.1µA/1µA/10µA/0.1mA	± (1.5% + 2 digits)
	10A	10mA	± (3.0% + 5 digits)
Resistance	400Ω/4kΩ/40kΩ/400kΩ/4MΩ	0.1Ω/1Ω/10Ω/0.1kΩ/1kΩ	± (1.0% + 5 digits)
	40MΩ	10kΩ	± (1.2% + 15 digits)
Capacitance	40nF/400nF/4µF/40µF/100µF	10pF/0.1nF/1nF/10nF/0.1µF	± (3.0% + 5 digits)
Frequency	5Hz/50Hz/500Hz/5kHz	0.001Hz/0.01Hz/0.1Hz/1Hz	± (0.5% + 2 digits)
	50kHz/500kHz/5MHz	10Hz/0.1kHz/1kHz	± (0.5% + 2 digits)
Duty Cycle	0.1% - 99.9%	0.1%	± (2.0% + 5 digits)

### Product Code Information

SKU	KPSMT440CBINT
EAN code	8435394747101
UPC code	810053670040
Pcs/export carton	20

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Digital Multimeters](#) category:*

*Click to view products by [KPS](#) manufacturer:*

Other Similar products are found below :

[2727795](#) [2727486](#) [6111-517](#) [40705X](#) [3026976](#) [P 8100](#) [OW18D](#) [OW18E](#) [OW18B](#) [UT334A](#) [1833C](#) [UT611](#) [1832C](#) [BM2807CSE](#) [45218](#)  
[OW18A](#) [MM200](#) [UT52](#) [FMHT82565-0](#) [UT802](#) [UT12E-EU](#) [SEFRAM7212](#) [UT8805E](#) [UT60EU](#) [BM2803CSE](#) [45215](#) [UT8804E](#) [RS3250](#)  
[BM2805CSE](#) [STHT0-77364](#) [RS3251](#) [NP40 000M0](#) [NP45 100M0](#) [BK391B](#) [BK393B](#) [BK390B](#) [FLK-87VMAX-PVLEAD1](#) [1664FC](#) [SCH](#)  
[FTT KIT](#) [BK394B](#) [KPS-MT720](#) [KPS-MT460](#) [KPS-MT440](#) [KPS-MT700](#) [KPS-MT480](#) [KPS-SL100](#) [KPS-MT920](#) [KPS-MT470](#) [RS3248](#)  
[UT267B](#) [KPSMT490CBINT](#)