

HIGH-PERFORMANCE LoRa-ENABLED GATEWAY CARD FEATURING M2.COM INTERFACE



The **Sentrius™ RG1xx-M2 LoRa-enabled concentrator card** combines Laird's long-standing expertise in optimized RF design with the emerging LoRaWAN ecosystem. The Sentrius RG1xx-M2 card enables OEMs to integrate a high-performance, certified LoRaWAN gateway interface to any Linux based platform. Laird's optimum hardware solution expands upon Semtech drivers and reference design for improved RF performance. Comprehensive integration and design services for a custom gateway are also available via Laird's dedicated Engineering Services team, as are qualified LoRa antenna solutions from Laird.

- **Optimized RF performance** – Improvements over Semtech reference design for:-
 - Power variation over temperature
 - Performance over frequency
- **Superior TX Performance** – Up to +27dBm
- **Standardized Interface** – M2 connector with compliance to [M2.COM](#) standard E type key.
- **Comprehensive Certifications** – FCC, IC, CE

Partner with Laird to create your own custom LoRa-enabled gateway

From embedded hardware, easy-to-connect antennas to expert integration services, Laird provides a comprehensive array of capabilities to build a customized LoRaWAN implementation, including:



LoRa-Equipped Concentrator card

Quickly add LoRaWAN capability to any Linux-based Gateway design via standard M2.COM interface.

+



Product Development Services

Laird is your partner for enclosure design, Linux driver implementation, FCC/IC/CE Certification testing, and more.

+



Antennas

Laird offers a family of high-gain omnidirectional antennas ideally suited for LoRa applications.

Application Areas



Smart Metering and Remote Sensing



Industrial Automation/Monitoring and Control



Agricultural and Rural IoT / M2M Applications

Shared Specifications

Category	Feature	Specification
General Radio	Semtech Radios	SX1301 and SX1257 (x2)
	Reference Design	Based on Semtech Rev 1.0 - SX1301 AP1
Connectors	Connector Type	M2.COM E Key - http://www.m2com-standard.org/en-us
	External Antenna	u.FL connector
Power	Consumption	TX (max): 440mA.
		RX (all channels): 340mA
		Idle: 40mA
Voltage	Input	5V (+/- 10%)
RF Characteristics	Frequency Range	RG186-M2 863 to 870 MHz
		RG191-M2 902 to 928 MHz
	RX sensitivity	Up to -140 dBm
	Max RF Output Power	Up to +27 dBm
Software	Host Interface	SPI
	Driver Support	https://github.com/Lora-net/lora_gateway (Laird testing done with Linux)
Temperature	Operating Range	-30 to +85
Physical	Dimensions	75 x 53 x 3.8 mm
	Weight	<11g
Regulatory	Certifications	FCC / IC / CE
Warranty		12 months

Ordering Information

RG186-M2	LoRaWAN Concentrator Card – M2.COM Interface (Europe)	Q2 2017
RG191-M2	LoRaWAN Concentrator Card – M2.COM Interface (N. America)	Q2 2017

Related Products

Sentrius™ RM1xx - LoRa + BLE Certified Modules



LoRa Class 1 + Bluetooth Low Energy module with smartBASIC for automated / hostless operation. Now with Bluetooth Central Mode.

www.lairdtech.com/products/rm1xx-series

Sentrius™ RG1xx – LoRa-Enabled Gateway



LoRa Class 1, Bluetooth Low Energy and 802.11ac Wi-Fi, completing the end-to-end solution for your own private, custom LoRaWAN network.

Coming Q2 2017

Did You Know?

LSR, a Laird Business, is a leader in Wireless Product Development, offering true end-to-end solutions through its array of services & technical expertise



a Laird Business



Design Services

- RF Hardware & Antenna Design
- Software/Firmware Development
- Mobile App / Cloud Development
- Industrial Design
- Mechanical Engineering



EMC Testing & Certification

- On-Site FCC/IC/CE/Giteki/RCM EMC Certification
- Wireless & Antenna Testing
- EMC Emissions Testing
- International Testing Services

To learn more about LSR visit:
www.lsr.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Gateways](#) category:

Click to view products by [Laird Connectivity](#) manufacturer:

Other Similar products are found below :

[2702887](#) [MTCDT-LEU1-247A-915-EU-GB-AU](#) [MTCAP-LEU1-868-001A](#) [MTCDTIP-LEU1-275L-868](#) [MTCDTIP-LEU1-266A-915](#)
[MTCDT-LEU1-246A-868-EU-GB](#) [SGX5150020US](#) [SGX5150225US](#) [X2-HMU-EM-B](#) [100-1156-001IA](#) [UPS-EDGE-X70864-U01](#) [4345](#)
[ADAM-6717-A](#) [EKI-1224CI-CE](#) [ESRP-PCS-WISE710](#) [ICR-3201](#) [ICR-3201-W](#) [ICR-3211B](#) [ICR-3241](#) [ICR-3241W](#) [WISE-3310-D100L1E](#)
[WISE-3610ILS-51A1N](#) [WISE-6610-E100-A](#) [WISE-6610-N100-A](#) [WISE-710](#) [AKX00016](#) [CSENSE-A300-N](#) [CSENSE-A700](#) [X2E-Z3C-H2-](#)
[W](#) [X2E-Z3C-W1-A](#) [X4-Z11-E-W](#) [XGI-20CZ7-E00-W0](#) [XGI-2PCZ7-EL1-W0](#) [ReliaGATE 10-12-65](#) [BLG840F](#) [BLG840X](#) [BM833AF](#)
[BWG832F](#) [BWG832X](#) [BWG840F](#) [PKG900000001385](#) [AGS102-I50-6COM](#) [455-00008](#) [455-00028](#) [450-00038-K1](#) [450-00011-K1](#) [450-](#)
[00039-K1](#) [450-00054-K1](#) [450-00107-K1](#) [450-00109-K1](#)