



HIGH PERFORMANCE, DUAL BAND (2.4/5GHZ) DEVICE FOR WI-FI CONNECTIVITY

PremierWave® XN is a multi-port device server that offers high performance Ethernet or Wireless connectivity for remote access and easy management of machines or equipment over the network and across the Internet.

PremierWave XN provides bullet-proof security by offering robust data encryption and authentication options including AES, SSH and SSL. Remote configuration over a network is possible using Telnet, SSH, or web browser (HTTP and HTTPS).

Equipped with the market leading “Lantronix device server application suite”, the PremierWave XN provides control of serial communication on connected devices and the flexibility to have data globally available. Advanced Applications Suite includes: basic & secure tunneling application, web-based configuration manager and robust system level and diagnostic utilities.

Additionally, Lantronix’ proprietary Secure ComPort Redirector™ software allows existing serial port applications to work without code modifications.

Designed with 802.11n technology, the PremierWave XN employs antenna diversity for optimal wireless performance, signal reliability, and extended range of wireless transmissions.

With the exclusive SmartRoam technology from Lantronix, the PW-XN provides seamless mobile connectivity. By tracking the signal strength of Access Points (AP) within range along with pre-authentication and caching, smooth and automatic transition to an access point occurs without delay.

Configuration of PremierWave XN is simple with the included Windows-based DeviceInstaller.™ With the Lantronix QuickConnect Manager, PremierWave XN provides an easy connection to the wireless network through a Web-based interface.



PremierWave XN Highlights:

- > Increased wireless speed, improved reliability and extended transmission range with dualband 802.11n
- > Lantronix SmartRoam™ technology provides seamless mobile connectivity and improved reliability
- > Enterprise-level security options including AES, SSL, SSH and EAP for data encryption and authentication
- > Simple device set-up, configuration and monitoring with powerful, industry-standard management tools (Web, CLI, XML), Lantronix DeviceInstaller™, QuickConnect, and WPS support

Features

> Standards

- IEEE 802.11 a/b/g/n
- IEEE 802.11i
- IEEE 802.3
- IEEE 802.3u
- USB 2.0

> Hardware

- 400MHz ARM 9 processor
- 64MB SDRAM
- 64MB Standard NAND Flash

> Wireless

- Frequency Range – 2.412 - 2.484, 4.900 - 5.925 GHz
- Typical Receive Sensitivity
 - 802.11 b/g/n (2.4GHZ)
 - -71.0 dBm (<10% PER) @65Mbps
 - -74.0 dBm (<10% PER) @54Mbps
 - -94.0 dBm (<8% PER) @1Mbps
 - 802.11 a/n (5GHZ)
 - -69.0 dBm (<10% PER) @65Mbps
 - -72.0 dBm (<10% PER) @54Mbps
 - -88.0 dBm (<10% PER) @6Mbps
- Typical Transmit Power
 - 17 dBm for 802.11b DSSS
 - 17 dBm for 802.11b CCK
 - 15 dBm for 802.11g/n OFDM
 - 12 dBm for 802.11a/n

> Physical Interface

- (2) DB9M (DTE) Serial Connectors
 - Software selectable RS-232/422/485
 - Data rates – up to 921 Kbps
 - 15 KV ESD Protection
- (2) USB ports – Type A Host Connectors
- (1) RJ-45 Ethernet port
 - 10/100Mbps
 - 1.5 KV Surge Isolation
- (1) Reset Button
- (1) WPS Button
- (1) 12VDC Plug-in Connector
- (1) Power Terminal Block
 - 9 to 30 VDC

> LED Indicators

- Power
- Status
- Wi-Fi Wireless Signal Strength
- (2) USB
- (2) Serial
- RJ-45 Ethernet (Activity/Link)

> Physical Dimensions

Size: L x W x H

11cm (4.3 in) X 8.9cm (3.5 in) x 2.6cm (1.0 in)

Weight: 0.35 kg (0.77 lb)

> Supported Software and Features

- DeviceInstaller™ supports:
 - Windows
 - XP/Vista
 - 7 (32/64-bit versions)
 - Server 2003/2008 (32/64-bit versions)

- Secure Com Port Redirector™
- Lantronix SmartRoam™
- QuickConnect
- Wireless Bridging

> Security

- Ethernet
 - SSL v3 (2048-bit), SSH v2 (1024-bit) Client & Server
 - Encryption: AES-CCMP, 3DES, RC4
 - Authentication: SHA-1, MD5, Base-64
- Wireless
 - Encryption: TKIP, WEP (64/128-bit), WPA, WPA2 , AES-CCMP
 - Authentication: PSK, EAP (TLS, TTLS, PEAP)

Ordering Information

United States

Call: 800.422.7055

Email: sales@lantronix.com

Buy Online: <http://www.lantronix.com>

Europe

Call: +31 (0) 76.52.3.6.74 4

Email: EMEA@lantronix.com

Asia/Pacific

Call: +852 3428.2338

Email: asiapacific_sales@lantronix.com

Japan

Call: +81.3.6277.8802

Email: japan_sales@lantronix.com

> Part Number

PXN210002-01U

PXN210002-01E

PXN210002-01J

> Description

PremierWave XN 802.11a/b/g/n Device Server without I/O, 2 x Serial, 2 x USB, 10/100Mbps, Universal Power Supply 100-240 VAC, US

PremierWave XN 802.11a/b/g/n Device Server without I/O, 2 x Serial, 2 x USB, 10/100Mbps, Universal Power Supply 100-240 VAC, EUROPE

PremierWave XN 802.11a/b/g/n Device Server without I/O, 2 x Serial, 2 x USB, 10/100Mbps, Universal Power Supply 100-240 VAC, JAPAN

> Accessories

930-033-R

External Antenna for PremierWave XN
2.15 dBi, Reverse Polarity, SMA Connector

520-090-R

External Power Supply with Regional
Adapters, 100-240 VAC, 50-60Hz, 12 VDC @1A

> Management

- Web Manager (SSL option for secure login)
- CLI (over Serial Ports, Telnet or SSH)
- XML Configuration Records via CLI or FTP
- Supports SNMP v2

> Environmental

- Operating Temp: -20° to 60° C (-4° to 140° F)
- Storage Temp: -30° to 75° C (-22° to 167° F)
- Relative Humidity: 5 to 95%, Non-condensing
- IP Rating: 30
- ESD tolerance: Contact Discharge= 4Kv; Air Discharge=8Kv

> Power

- Input: 2 x DC (barrel and terminal), 9-30 VDC
- Power Consumption: Without USB Load 9V= 1.76W, 30V= 2.25W; Full USB Load 9V= 7.2W, 30V= 8.1W
- Power Supply (100-240 VAC, 50-60 Hz, 12 VDC @ 1A) with regional adapters

> Certifications

- Emissions – FCC, CE, IC, C-Tick
- Safety – UL
- Wi-Fi
- REACH
- RoHS

> Warranty

- 5-Year Limited



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Servers](#) category:

Click to view products by [Lantronix](#) manufacturer:

Other Similar products are found below :

[70002259](#) [70002261](#) [VESR321-ML](#) [NBLM-LM1CR](#) [EKI-1528TI-VDC-CE](#) [ADAM-4570L-DE](#) [ADAM-4571-CE](#) [XPC100200S-01](#) [ESP904](#)
[96NIC-10G2P-IN](#) [ADAM-4570-CE](#) [ADAM-4571L-DE](#) [AGS-913I-R11A1E](#) [EKI-1361-MB-BE](#) [EKI-1362-BE](#) [EKI-1362-MB-BE](#) [EKI-1522-](#)
[CE](#) [EKI-1526-CE](#) [EKI-1526I-CE](#) [EKI-1528-CE](#) [ABDN-ER-IN5018](#) [ESP901](#) [ESP902](#) [ESR901](#) [ESR904](#) [BB-VESR902T](#) [VESR902D](#)
[70002412](#) [70002263](#) [70002265](#) [70002269](#) [70002271](#) [70002277](#) [70002279](#) [70002281](#) [70002285](#) [70002404](#) [70002406](#) [70002410](#) [70002414](#)
[70002418](#) [ED1100002-01](#) [ED2100002-01](#) [ED41000P0-01](#) [ED41000P2-01](#) [PEN100100A-01-IT](#) [PXC2102G2-01](#) [SD2101002-11](#)
[UD1100002-01](#) [UD1100IA2-01](#)