



Application

NC14 1000A/400A measures, calculate and displays important electrical parameters of single phase or three phase power system. It also features Resistance, continuity, diode and non contact voltage detection.

Unique Design

NC141000A/400A is a highly innovative design for features those increases **safety** and **comfort** of user.

- Rotating clamp jaws facilitate the measurement at physically awkward positions, vertical bus bars, conductors placed at positions difficult to access.
- Clamp jaws can be opened or closed with the trigger placed at bottom side away from the jaws. This allows the user to place his/her hand at safer distance from live conductor. This greatly reduces exposure of human beings to electrical shocks.
- Location and design of trigger eliminates fatigues caused by single finger operation. It allows spreading the force required to open the jaws over more than one finger to ensure comfortable operation.
- Comfortable operation of push buttons and function selector switch, in adverse field conditions.

Large Jaw Opening

Jaw opening of 51mm and 41 mm for standard wire diameter of 50mm and 40mm for 1000A and 400A respectively.

Inrush Current Measurement

Clamp meter will be triggered by inrush current >5A. Inrush current for 100 msec is measured.

DATA Hold Function

By pressing DATA HOLD button, reading on the display can be latched for Hands free operation.

MIN,MAX Function

By pressing MIN/MAX button, the clamp meter will start recording latest Minimum and Maximum readings

Backlit

It is possible to conduct measurement using the clamp meter during poor light condition with the help of bright white light Backlit.

NC14

AC/DC POWER CLAMP-ON METER 1000 A/ 400A

- ✓ AC & DC voltage measurement up to 1000 V.
- ✓ AC & DC current measurement in the range of 1000 A / 400 A.
- ✓ Inrush/peak value measurement
- ✓ Active, reactive and apparent power measurement.
- ✓ Power measurement in KM.
- ✓ Energy consumption measurement in kWh.
- ✓ Measurement up to 49th harmonics.
- ✓ Phase angle measurement.
- ✓ THD measurement.
- ✓ DF measurement.
- ✓ Crest factor /CF/ measurement.
- ✓ Power factor /PF/ measurement.
- ✓ Low pass filter (LPF) mode.

Non Contact Voltage Detection

The clamp meter can detect the presence of AC Voltage between 100 to 1000 V 50hz/60Hz without any electrical connection and give acoustic signal as an indication.

Three Phase Power Measurement

Clamp meter can measure power in 3 phase 3 wire or 3 phase 4 wire (Symmetric as well as Asymmetric) network without any manual calculation like other clamp meters.

Dual Display

User friendly dual display shows the simultaneous parameters of measuring input quantity.

LPF Mode

LPF mode is available for voltage and current for true measurement of VFD Application

TRMS Measurement

In order to calculate true value of distorted waveform due to presence of high crest factor or harmonics, TRMS measurements is done for AC voltage and current

Auto Power OFF

In order to save the power of the Batteries, the clamp meter will automatically shut OFF if it detects no activity for 10 minutes.

Continuous ON Mode

In this mode, AUTO POWER OFF is disabled.

Low Battery Indication

Double molded Cover for soft touch and firm grip of the Instrument

NC14 - AC/DC POWER CLAMP-ON METER 1000 A/ 400 A

Reference conditions for Accuracy

Reference temperature	23°C ± 2°C
Relative Humidity	45%...55% RH
Input frequency	50 or 60 Hz
Power Factor	0.5L....1....0.5C
Battery Voltage	8 V ± 0.1 V

Protection from dust and water

IP20 for terminals as per EN 60529

Applicable International Safety standards

600 V CAT IV/1000V CAT III as per International Safety standard
EN 61010-1

Measuring function	Measuring range	Resolution	Intrinsic error of digital display at reference condition		Over load capacity			
			Over load value	Overload duration				
VDC	999.9 V	0.1 V	±(0.5% of rdg + 5 dgt)					
V~	999.9 V	0.1 V	±(0.75% of rdg+5 dgt)					
VACDC	999.9 V	0.1 V	±(1.25% of rdg+10dgt)					
LPF V~	999.9 V	0.1 V	50.....60 Hz	±(0.75% of rdg + 5dgt)	1000 VDC/AC eff/rms Sine wave	Continuously		
			61...400Hz	±(5.0% of rdg + 5dgt)				
POWER CLAMP 1000A ADC-AAC	999.9A	0.1 A	±(1.5% of rdg+5 dgt) ¹⁾		1100 AAC/DC for power clamp 1000A	Continuously		
POWER CLAMP 400A ADC - AAC	99.99 A	0.01 A	display value <1000 add 10 dgt	±(1.5% of rdg+0.2A) ¹⁾				
	400 A	0.1 A		±(1.5% of rdg+5 dgt) ¹⁾				
POWER CLAMP 1000A AACDC	999.9A	0.1 A	±(3% of rdg+10 dgt) ¹⁾					
POWER CLAMP 400A AACDC	99.99 A	0.01 A	display value <1000 add 10 dgt	±(3% of rdg+0.4A) ¹⁾				
	400 A	0.1 A		±(3% of rdg+10 dgt) ¹⁾				
POWER CLAMP LPF 1000A AAC	999.9A	0.1 A	50....60 Hz	±(1.5% of rdg + 5dgt)	440 AAC/DC for power clamp 400A	Continuously		
POWER CLAMP LPF 400A AAC	99.99 A	0.01 A	61...400Hz	±(5.0% of rdg + 5dgt)				
	400 A	0.1 A	50....60 Hz	±(1.5% of rdg + 5dgt)				
	400 A	0.1 A	61...400Hz	±(5.0% of rdg + 5dgt)				
Active Power ²⁾	9.999 kW	1 W	±(2% of rdg+5 dgt) ¹⁾					
	99.99 kW	10 W						
	999.9 kW	100 W						
	9999 kW	1 kW						
Reactive Power ²⁾	9.999 kVAr	1 VAr			1000 VDC/AC 1100 AAC/DC for Power Clamp 1000A 440 AAC/DC for Power Clamp 400A	Continuously		
	99.99 kVAr	10 VAr						
	999.9 kVAr	100 VAr						
	9999 kVAr	1 kVAr						
Apparent Power ²⁾	9.999 kVA	1 VA						
	99.99 kVA	10 VA						
	999.9 kVA	100 VA						
	9999 kVA	1 kVA						
Horse Power ²⁾	9.999 hp	0.001 hp						
	99.99 hp	0.01 hp						
	999.9 hp	0.1 hp						
	9999 hp	1 hp						
kWh ²⁾	9.999 kWh	0.001 kWh	±(3% of rdg+5 dgt)					
	99.99 kWh	0.01kWh						
	999.9 kWh	0.1 kWh						
	9999 kWh	1 kWh						

Technical Specification

Measuring function	Measuring range	Resolution	Intrinsic error of digital display at reference condition	Over load capacity	
				Over load value	Overload duration
Ahr	999.9 Ahr	0.1 Ahr	±(3% of rdg+5 dgt)	1000 VDC/AC 1100 AAC/DC for Power Clamp 1000A 440 AAC/DC for Power Clamp 400A	Continuously
Phase angle ²⁾	0.0°...360.0°	0.1°	±3°		
Power Factor ²⁾	-1...0...1	0.001			
Harmonics (RMS & %) ³⁾	1...13	0.1V	±(3% of rdg+10 dgt)		
	14...49	0.1A 0.1%	±(5% of rdg+20 dgt)		
THD ³⁾	0...99.9%	0.1%	±(3% of rdg+20 dgt)		
DF ³⁾	0...99.9%	0.1%	±(3% of rdg+20 dgt)		
Crest Factor ³⁾	1.0...2.9	0.1	±(2% of rdg+3 dgt)		
	3.0...5.0	0.1	±(3% of rdg+5 dgt)		
POWER CLAMP 1000A Peak	1400 A / 1400V	1 A	±(3% of rdg+3 dgt)		
POWER CLAMP 400A Peak	100 A	0.1 A	±(3% of rdg+10 dgt)		
	560 A / 1000 V	1 A / 1 V	±(3% of rdg+3 dgt)		
POWER CLAMP 1000A INRUSH ⁴⁾	999.9A	0.1 A	±(3% of rdg+5 dgt)	1000 V DC/AC eff/rms Sine wave	10 Secs
POWER CLAMP 400A INRUSH ⁴⁾	99.99 A	0.01 A	±(3% of rdg+0.3A)		
	400 A	0.1 A	±(3% of rdg+5 dgt)		
Resistance	9999 Ohm	1 Ohm	±(0.5% of rdg+5 dgt)		
Continuity	Below 40 Ohm	1 Ohm	±(0.5% of rdg+5 dgt)		
Diode	0...2.2V	0.001 V	±(0.5% of rdg+5 dgt)		

Note:- Accuracy claimed for Power and Current when conductor is positioned at the center of the jaw.

1)For DCA make auto zero correction by long pressing the **HOLD** key

For Power Clamp 1000A

- 2)Accuracy Defined for $V \geq 10V$ and $I \geq 5A$
Add 10 digit to accuracy when power is
 $< 5.000 \text{ kW/kVAr/kVA}$ or $< 6.700 \text{ hp}$
- 3)Accuracy Defined for $V \geq 10V$ and $I \geq 10A$
- 4)Accuracy Defined for $I \geq 10A$

For Power Clamp 400A

- 2)Accuracy Defined for $V \geq 10V$ and $I \geq 4A$
Add 10 digit to accuracy when power is
 $< 5.000 \text{ kW/kVAr/kVA}$ or $< 6.700 \text{ hp}$
- 3)Accuracy Defined for $V \geq 10V$ and $I \geq 10A$
- 4)Accuracy Defined for $I \geq 5A$

For Power Clamp 1000A

- In 1P2W mode maximum power meter can measure is, 1000 kVA / 1000 kVAr / 1000 kW / 1341 hp
- In 3P4W mode maximum power meter can measure is, 3000 kVA / 3000 kVAr / 3000 kW / 4023 hp
- In 3P3W mode maximum power meter can measure is, 1732 kVA / 1732 kVAr / 1732 kW / 2322 hp

For Power Clamp 400A

- In 1P2W mode maximum power meter can measure is, 400 kVA / 400 kVAr / 400 kW / 536 hp
- In 3P4W mode maximum power meter can measure is, 1200 kVA / 1200 kVAr / 1200 kW / 1608 hp
- In 3P3W mode maximum power meter can measure is, 693 kVA / 693 kVAr / 693 kW / 928 hp

AC current measurement in both 1000A and 400A model starts from 0.5A in AC Amp mode and from 1A in LPF mode

Influence Quantity

Influence quantity	Range of Influence	Measured quantity / Measuring Range	Variation
Temperature	0 °C... 21 °C and 25 °C....50 °C	VAC	0.15 X Intrinsic Error / °C
		VDC	
		VACDC	
		AAC	
		ADC	
		AAACDC	
		AC Power	
		DC Power	
		Resistance/ Diode/ Continuity	
		Resistance/ Diode/ Continuity	
Frequency of the measured quantity	40 Hz... 50 Hz and 60 Hz...400 Hz	VAC	1 X Intrinsic Error
		VACDC	
		AAC	
		AAACDC	
	45 Hz...65 Hz ²⁾	AC Power	
Crest Factor ¹⁾	1.4...2	VAC	1% + Intrinsic Error
	2...2.5		2.5% + Intrinsic Error
	2.5...5	AAC	4% + Intrinsic Error
Supply Voltage	When Low Battery symbol is ON	All Ranges	1 X Intrinsic Error
Relative humidity	75%	All Ranges	1 X Intrinsic Error

1) Except SineWave

CF 2 @ 690V, 690A for Power Clamp Meter 1000 A AC/DC
CF 3 @ 690V, 186A for Power Clamp Meter 400 A AC/DC
CF 4 @ 345V, 345A for Power Clamp Meter 1000 A AC/DC
CF 4 @ 345V, 140A for Power Clamp Meter 400 A AC/DC
CF 2 @ 690V, 280A for Power Clamp Meter 400 A AC/DC
CF 5 @ 280V, 280A for Power Clamp Meter 1000 A AC/DC
CF 3 @ 460V, 460A for Power Clamp Meter 1000 A AC/DC
CF 5 @ 280V, 112A for Power Clamp Meter 400 A AC/DC

2) Except for 50 or 60 Hz

Environmental

Operating temperature	0 to +55°C
Storage temperature	-20 to +70°C
Temp. Coefficient	0.15 X(Intinsic Error) / °C
Relative humidity	0... 75% non condensing
Terminal Protection for terminals	IP50 for Housing and IP20

Display

Display	Seven Segment
Character Height	Main Display Character : 11.5 mm Sub Display Character : 7.2 mm
Number of digits	4 digits.
Maximum count	9999 counts For V, I and Power 9999 counts For Resistance
Over range indication	"OL" is displayed
Polarity indication	"—" sign is displayed for negative values.

Applicable Standards

EMC	Electro magnetic compatibility
Emission	EN 61000-6-4
Immunity	EN 61000-6-4
	EN 61000-4-2 :-
	8 kV air discharge, 4 kV contact discharge
	EN 61000-4-3 :- 3 V/m

Safety

IP for water & dust acc. to EN 60529	EN 61010-1
	IP 50 for housing
	IP 20 for terminal
Pollution degree	2
Installation category	III IV 1000V 600V

High Voltage Test

between housing and input. 7.4 kV AC, 50Hz for 1 minute
 between housing with jaws and 4.26 kV AC, 50Hz for 1 minute
 input.

Scope of delivery

- Clamp Meter
- Probe Set
- Instruction Manual/Warranty card
- Clamp Carrying Case
- Test Certificate
- Battery
- Two crocodile clips

Mechanical Configuration

Dimensions 90 mm (W) x 270 mm (L) x 70 mm (H)
 Weight 500gm approx. including battery.

ORDERING CODE

Clamp meter NC14 -	X	XX	X	X
Maximal range of current measurement a.c./d.c.:				
400 A	1			
1000 A		2		
Version:				
standard		00		
custom-made*		XX		
Language:				
Polish		P		
English		E		
other*		X		
Acceptance tests:				
with an extra quality inspection certificate		1		
with test certificate		2		
acc. to customer's request		X		

ITEMS AVAILABLE FROM OUR STOCK:

NC14 - 100E1

version: 400A

NC14 - 200E1

version: 1000A

* after agreeing with the manufacturer

NC14-19_en



LUMEL S.A.
 ul. Sulechowska 1, 65-022 Zielona Góra, POLAND
 tel.: +48 68 45 75 100, fax +48 68 45 75 508
www.lumel.com.pl

Export department:
 tel.: (+48 68) 45 75 139, 45 75 233, 45 75 321, 45 75 386
 fax.: (+48 68) 32 54 091
 e-mail: export@lumel.com.pl

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [LUMEL](#) manufacturer:

Other Similar products are found below :

[I800](#) [1000-304](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM197](#) [UT204](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I310S](#) [FLUKE I400](#) [TESTO 770-2](#) [0590 7702](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#) [FLUKE-1630-2FC](#) [CM42](#) [FLUKE-376 FC](#) [A193 \(800 MM\)](#) [F201](#) [F205](#) [F65](#) [DIGIFLEX 4000A 350MM](#) [DIGIFLEX 400A 250MM](#) [FLUKE A3001FC](#) [FLUKE I6000SFLEX-24](#) [KEW2010](#) [P1670](#) [UT203](#) [FLK-A3004FC](#) [AMP-330-EUR](#) [APPA SFLEX-18D](#) [UT200A](#) [UT201](#) [UT205](#) [UT205A](#) [UT206](#) [UT206A](#) [UT210A](#) [UT210B](#) [UT213A](#)