

2WAY-90° POWER SPLITTER / COMBINERS

Designer's Kit **K1-QCN+**

MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
THE SOLUTION!



220 to 4500 MHz

QCN+ Features

- Wideband, 50 Ω
- Low insertion loss, 0.4 dB typical
- High isolation up to 32 dB typical
- Wrap-around terminals for excellent solderability
- Ultra small ceramic cases, (L) 0.12" x (W) 0.60" x (H) 0.35"



All models are
RoHS compliant

Kit K1-QCN+ Electrical specifications of each model (10 models, 2 of each, 20 total)

Model	Frequency Range (MHz)		Isolation (dB)		Insertion Loss (dB) Above 3 dB		Phase Unbalance (Degrees) Max.	Amplitude Unbalance	Power Input (W) (as a splitter) Max.
	Low	High	Typ.	Min.	Typ.	Max.			
QCN-3+	220	470	24	18	0.6	0.8	8	1.3	15
QCN-5+	330	580	20	14	0.3	0.6	8	1.3	15
QCN-7+	425	675	17	11	0.4	0.7	8	1.0	15
QCN-12+	800	1375	19	14	0.4	0.8	12	0.9	15
QCN-12A+	800	1250	17	13	0.3	0.7	5	0.8	15
QCN-19+	1100	1925	25	19	0.4	0.9	4	1.1	15
QCN-25+	1350	2450	25	18	0.4	0.9	5	1.1	15
QCN-27+	1700	2700	26	18	0.4	0.9	6	1.0	15
QCN-34+	2500	3400	32	20	0.4	0.7	4	1.2	15
QCN-45+	2500	4500	19	15	0.5	0.8	6	2.5	15

Patent pending



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For quick access to product information see MINI-CIRCUITS CATALOG & WEB SITE

IF RF MICROWAVE COMPONENTS

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Development Tools](#) category:

Click to view products by [Mini-Circuits](#) manufacturer:

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [122410-HMC686LP4E](#) [ADL5363-EVALZ](#) [130437-HMC1010LP4E](#) [EKIT01-HMC1197LP7F](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#) [MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC520ALC4](#) [EV1HMC244AG16](#) [EV1HMC539ALP3](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2692EVKIT#](#) [SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#) [ADL5725-EVALZ](#) [106815-HMC441LM1](#) [UXN14M9PE](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#) [SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#) [SKY13380-350LF-EVB](#) [SKY13355-374LF-EVB](#) [SKY13322-375LF-EVB](#) [SKY12207-478LF-EVB](#) [SE5023L-EK1](#) [SE5004L-EK1](#) [SE2436L-EK1](#) [Se2435L-EK1](#) [CLA4609-086-EVB](#) [SIMSA915C-DKL](#) [SIMSA915-DKL](#) [SIMSA433C-DKL](#)