



DESIGNER'S KIT K1-TCN+

Transformers


50Ω 600 to 2600 MHz

Mini-Circuits

FEATURES

- Balanced transmission line
- Very wide bandwidth
- Rugged LTCC construction
- Small size, 0.12" (L) x .06" (W) x .037" (H)
- Low cost

MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
THE SOLUTION





K1-TCN+ ELECTRICAL SPECIFICATIONS

(7 models, 5 of each, 35 total)

Model	Ω Ratio	Frequency (MHz)	Insertion Loss (dB)	Phase Unbalance (dB)	Phase Unbalance (dB)	Configuration
TCN1-10+	1	680-1050	1.5-500	2.5-400	2.5-400	G
TCN1-23+	1	1300-2300	—	600-1100	600-1100	G
TCN2-14+	2	700-1400	800-1900	—	—	G
TCN2-26+	2	1600-2600	—	—	—	G
TCN3-11+	3	600-1100	—	2-500	2-500	G
TCN4-13+	4	650-1250	3-800	5-400	5-400	G
TCN4-22+	4	1200-2200	200-1400	300-1300	300-1300	J

* Insertion loss is referenced to mid-band loss

CONFIGURATIONS



REV. A
ECO-009388
M108655
K1-TCN+
210823

Mini-Circuits

www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Audio Transformers / Signal Transformers](#) category:

Click to view products by [Mini-Circuits](#) manufacturer:

Other Similar products are found below :

[CX2041NLT](#) [MGPWT-00449-P](#) [PE-64961](#) [H1302FNLT](#) [H5008FNL](#) [H5012FNL](#) [H5020FNLT](#) [H5077NLT](#) [H5084FNLT](#)
[B78476A9558A003](#) [1812WBT2-4](#) [1879479-1](#) [HX2260FNL](#) [HX5014FNL](#) [EX2024FNL](#) [FL1066](#) [T1137NLT](#) [T3012NL](#) [PE-65812FNL](#) [PE-65848FNLT](#) [H1174FNL](#) [H1302FNL](#) [H5015FNL](#) [H5019EFNL](#) [H5062FNLT](#) [CX2047LNL](#) [MGPWT-00059-P](#) [MGPWT-00266-P](#) [MGPWT-00278-P](#) [MGPWT-00431-P](#) [TTC-100](#) [TTC-143-H](#) [TTC-5032-1](#) [BX1194WNLT](#) [HX1234NLT](#) [HX5008FNLT](#) [HX5019FNL](#) [HX5084NL](#) [3-1879385-5](#) [TX1263NLT](#) [4-1879391-0](#) [T1142NL](#) [HX6101FNL](#) [HX5084FNL](#) [HX1148NL](#) [HX5020FNLT](#) [HX5014FNLT](#) [T1124NL](#)
[1879732-1](#) [2-1879391-5](#)