



DC to 4 GHz

ERA-SM+ Features

- Wideband, 50 Ω
- Up to +18.4 dBm typ. output power
- Low thermal resistance
- Miniature microwave amplifier
- Plastic micro-x surface mount package



Kit K3-ERASM+ Electrical specifications of each model (3 models, 10 of each, 30 total)

Evaluation boards available
See individual model data sheets.

Model	Freq. GHz ▲ f_L - f_U	Gain, dB Typical					Max. Pwr. (dBm) @ 1 GHz			Dynamic Range @ 1 GHz		VSWR (:1) Typ.				Absolute Max. Rating ¹		DC ² Operating Power @ pin 3			Therm. Resist. θ_{jc} Typ. °C/W	Evaluation Board		
		over frequency, GHz					Output (1 dB Comp.) Typ.	Input ¹ Min.	NF Typ.	IP3 (dBm) Typ.	In DC-3 GHz	In 3-4 GHz	Out DC-3 GHz	Out 3-4 GHz	I (mA)	P (mW)	Current (mA)	Device Volt. Typ. Min. Max.						
ERA-4SM+	DC-4	14.3	14.0	13.4	12.7	11.8	11	17.3	15.0	20.0	4.2	34.0	1.2	1.2	1.3	1.8	120	650	65	4.5	4.2	5.5	196	TB-408-4+
ERA-5SM+	DC-4	20.2	19.5	17.6	15.6	14.0	16	18.4	16.5	13.0	4.3	32.5	1.3	1.3	1.2	1.3	120	650	65	4.9	4.2	5.5	133	TB-408-5+
ERA-6SM+	DC-4	12.6	12.5	12.2	11.7	11.3	10.5	17.9	16.0	20.0	4.5	36.0	1.3	1.2	1.6	1.8	120	650	70	5.0	4.6	5.6	143	TB-408-6+

Protected under U.S. Patent 6,943,629

▲ Low frequency cutoff determined by external coupling capacitors. f_U is the upper frequency limit for each model.

1. Permanent damage may occur if any of these limits are exceeded. These ratings are not intended for continuous normal operation.
2. Supply voltage must be connected to pin 3 through a bias resistor in order to prevent damage. See "Biasing MMIC Amplifiers" at minicircuits.com/applications.shtml. Reliability predictions are applicable at specified current and normal operating conditions.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Development Tools](#) category:

Click to view products by [Mini-Circuits](#) manufacturer:

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [122410-HMC686LP4E](#) [ADL5363-EVALZ](#) [130437-HMC1010LP4E](#) [EKIT01-HMC1197LP7F](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#) [MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC520ALC4](#) [EV1HMC244AG16](#) [EV1HMC539ALP3](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2692EVKIT#](#) [SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#) [ADL5725-EVALZ](#) [106815-HMC441LM1](#) [UXN14M9PE](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#) [SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#) [SKY13380-350LF-EVB](#) [SKY13355-374LF-EVB](#) [SKY13322-375LF-EVB](#) [SKY12207-478LF-EVB](#) [SE5023L-EK1](#) [SE5004L-EK1](#) [SE2436L-EK1](#) [Se2435L-EK1](#) [CLA4609-086-EVB](#) [SIMSA915C-DKL](#) [SIMSA915-DKL](#) [SIMSA433C-DKL](#)