

FIXED ATTENUATORS

Designer's Kit K4-VAT2+

MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
 THE SOLUTION!



DC to 6 GHz

VAT-W2+ Features

- Wideband, 50 Ω
- Input power 2 W max.
- 3,6,10 and 20 dB attenuation
- Rugged Unibody construction
- SMA Male and Female connectors
- Length less than 1.5"
- Low cost



All models are RoHS compliant

Kit K4-VAT2+ Electrical specifications of each model *ea. kit (4 models, 1 of each, 4 total)*

Model	Frequency (GHz) <i>f_L-f_U</i>	Attenuation ² (dB)					VSWR (:1)					Input Power (W) Max.	
		Flatness ¹					DC-3 GHz			3-5 GHz			5-6 GHz
		Nom.	Typ.	Typ.	Typ.	Typ.	Typ.	Max.	Typ.	Max.	Max.		
VAT-3W2+	DC-6	3±0.3	0.20	0.15	0.15	.45	1.05	1.20	1.30	1.40	1.45	2	
VAT-6W2+	DC-6	6±0.3	0.20	0.10	0.20	.45	1.10	1.20	1.30	1.45	1.50	2	
VAT-10W2+	DC-6	10±0.3	0.10	0.20	0.15	.35	1.15	1.25	1.35	1.60	1.60	2	
VAT-20W2+	DC-6	20±0.3	0.50	0.45	0.20	1.05	1.35	1.55	1.70	1.95	1.95	2	

1. Flatness=variation overband divided by 2.
 2. Attenuation varies by 0.3 dB max. over temperature.



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For quick access to product information see MINI-CIRCUITS CATALOG & WEB SITE

IF/RF & MICROWAVE COMPONENTS

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Development Tools](#) category:

Click to view products by [Mini-Circuits](#) manufacturer:

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [122410-HMC686LP4E](#) [ADL5363-EVALZ](#) [130437-HMC1010LP4E](#) [EKIT01-HMC1197LP7F](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#) [MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC520ALC4](#) [EV1HMC244AG16](#) [EV1HMC539ALP3](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2692EVKIT#](#) [SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#) [ADL5725-EVALZ](#) [106815-HMC441LM1](#) [UXN14M9PE](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#) [SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#) [SKY13380-350LF-EVB](#) [SKY13355-374LF-EVB](#) [SKY13322-375LF-EVB](#) [SKY12207-478LF-EVB](#) [SE5023L-EK1](#) [SE5004L-EK1](#) [SE2436L-EK1](#) [Se2435L-EK1](#) [CLA4609-086-EVB](#) [SIMSA915C-DKL](#) [SIMSA915-DKL](#) [SIMSA433C-DKL](#)