

FIXED ATTENUATORS

Designer's Kit K5N-BW3+

MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
 THE SOLUTION!



DC to 18 GHz

BW-NXW5+ Features

- Wideband, 50 Ω
- 3,6 and 10 dB precision attenuation
- Input power 5 W max.
- Excellent VSWR, 1.25:1 typ.
- Stainless steel Type-N Male & Female connectors
- Length 1.90"



All models are
 RoHS compliant

Kit K5N-BW3+ Electrical specifications of each model (3 dB, 6 dB Qty. 1ea.) (10 dB Qty. 2) 4 total

Model	Frequency (GHz) f_L - f_U	Attenuation ¹ (dB)		VSWR ² (:1)			Input Power ³ (W) Max.
		Nominal	Accuracy	DC-4 GHz Max.	4-8 GHz Max.	8-12.4 GHz Max.	
BW-N3W5+	DC - 18	3	± 0.40	1.20	1.25	1.30	5
BW-N6W5+	DC - 18	6	± 0.40	1.20	1.25	1.30	5
BW-N10W5+	DC - 18	10	± 0.60	1.20	1.25	1.30	5

1. At 25°C, accuracy includes frequency and power variations. Temperature coefficient for attention .0004 dB/dB/C° typ.

2. VSWR from 12.4 to 18 GHz, 1.6:1 typ.

3. Average power at 25°C ambient, derate linearly to 2 W at 100°C. Peak power 125 W max. 5 μ sec pulse width, 100 Hz PRF.



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For quick access to product information see MINI-CIRCUITS CATALOG & WEB SITE

RF/IF & MICROWAVE COMPONENTS

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Development Tools](#) category:

Click to view products by [Mini-Circuits](#) manufacturer:

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [122410-HMC686LP4E](#) [ADL5363-EVALZ](#) [130437-HMC1010LP4E](#) [EKIT01-HMC1197LP7F](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#) [MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC520ALC4](#) [EV1HMC244AG16](#) [EV1HMC539ALP3](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2692EVKIT#](#) [SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#) [ADL5725-EVALZ](#) [106815-HMC441LM1](#) [UXN14M9PE](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#) [SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#) [SKY13380-350LF-EVB](#) [SKY13355-374LF-EVB](#) [SKY13322-375LF-EVB](#) [SKY12207-478LF-EVB](#) [SE5023L-EK1](#) [SE5004L-EK1](#) [SE2436L-EK1](#) [Se2435L-EK1](#) [CLA4609-086-EVB](#) [SIMSA915C-DKL](#) [SIMSA915-DKL](#) [SIMSA433C-DKL](#)