

Ohmite radio frequency plate chokes have a single-layer winding designed to avoid adverse harmonic effects and prevents breakdown from high r.f. potentials. Windings are insulated and protected by a moisture-proof coating.

- Z-7 type furnished with non-magnetic mounting bracket.
- Z-14, Z-28 type have wire leads welded to lug type terminals.
- Z-50, Z-144, Z-235, Z-460 type have axial wire leads.

It is generally advisable to select a choke with a resonant frequency (see chart) slightly higher than the desired operating frequency since any additional capacity to ground will tend to shift the resonant frequency closer to the operating frequency.



Z Series

R. F. Plate Chokes



ORDERING INFO

RoHS Compliant

Z - 1 4 4 E

Z Series Specifier
see chart

STOCK PART NUMBERS								
Part number	Inductance (μH) ±10% @ 1kHz	Rated DC current (A)	DCR (Ω)	Operating range (MHz)	SRF (MHz)	Diameter (in./mm)	Length (in./mm)	
Z-7	84.0	1.00	4.70	3 - 20	13	0.563 / 14.29	6	152.4
Z-14	44.0	0.68	2.60	7 - 35	23	0.438 / 11.11	2	50.6
Z-28	21.0	0.60	2.70	20 - 60	41	0.313 / 7.94	1.750	44.45
Z-50	7.0	1.00	0.98	35 - 110	79	0.281 / 7.14	1	25.4
Z-144	1.8	1.10	0.33	80 - 200	168	0.188 / 4.76	0.750	19.05
Z-235	0.84	1.70	0.14	160 - 350	300	0.188 / 4.76	0.750	19.05
Z-460	0.20	4.00	0.034	320 - 520	500	0.156 / 3.97	0.500	12.70

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Fixed Inductors](#) category:

Click to view products by [Ohmite](#) manufacturer:

Other Similar products are found below :

[CR43NP-680KC](#) [CR54NP-820KC](#) [CR54NP-8R5MC](#) [CTX32CT-100](#) [70F224AI](#) [MGDQ4-00004-P](#) [MHL1ECTTP18NJ](#) [MHL1JCTTD12NJ](#)
[PE-51506NL](#) [PE-53601NL](#) [PE-53602NL](#) [PE-53630NL](#) [PE-53824SNLT](#) [PE-62892NL](#) [PE-92100NL](#) [PG0434.801NLT](#) [PG0936.113NLT](#)
[9310-16](#) [PM06-2N7](#) [PM06-39NJ](#) [A01TK](#) [1206CS-471XJ](#) [HC2-2R2TR](#) [HC2LP-R47-R](#) [HC3-2R2-R](#) [1206CS-151XG](#) [RCH664NP-140L](#)
[RCH664NP-4R7M](#) [RCH8011NP-221L](#) [RCP1317NP-332L](#) [RCP1317NP-391L](#) [RCR1010NP-470M](#) [RCR110DNP-331L](#) [DH2280-4R7M](#)
[DS1608C-106](#) [ASPI-4020HI-R10M-T](#) [B10TJ](#) [B82477P4333M](#) [B82498B3101J000](#) [B82498B3680J000](#) [ELJ-RE27NJF2](#) [1812CS-153XJ](#)
[1812CS-183XJ](#) [1812CS-223XJ](#) [1812LS-104XJ](#) [1812LS-105XJ](#) [1812LS-124XJ](#) [1812LS-154XJ](#) [1812LS-223XJ](#) [1812LS-224XJ](#)