



Technical criteria

Rated supply voltage	24 to 48 VAC (50/60 Hz) or 12 to 48 VDC			
Reset Power Off time	0.1 s min			
Operating Temperature	-10 to 55 °C			
Signal Input type	No-voltage input			
Start Signal input time	0.05 s min			
Output	Contact Output: Time limit contact (DPDT) 5A at 250 VAC/30 VDC, 0.15A at 125 VDC, resistive load (cosI = 1) Minimum applied load: 10mA at 5 VDC (failure level: P, reference value) Contact materials: Ag-alloy			
Time Setting Error	±0.2% Full Scale max. (±0.2% • 10 ms max. in a range of 1.2 s or 3 s)			
Operating mode	A: ON-delay B: Flicker OFF start B2: Flicker ON start C: Signal ON/OFF-delay	D: Signal OFF-delay E: Interval G: Signal ON/OFF-delay J: One-shot		
Safety Standards	UL 508, CSA C22.2 No.14 CCC CE Marking under EN 61812-1, IEC 60664-1 Marine Approvals (NK, Lloyds)	For the most recent information on models that have been certified for safety standards, refer to your OMRON website.		

Nomenclature

Power indicator: Green

(Flashes when Timer operates; lit when Timer stops operating)



Operating mode display window Operating mode selector Select a mode from: A, B, B2, C, D, E, G, and J

Scale range display windows

Time unit display window

Time range selector (select one from 1.2, 3, 12, and 30 at full scale)

(lit when output)

Time setting knob (Set the pointer by turning a knob)

Time unit selector (select one from sec, 10s, min, 10m, hrs, and 10h)

Time range

Time un	nit	sec (second)	10s (x 10 seconds)	min (minute)	10m (x 10 minutes)	hrs (hour)	10h (x 10 hours)
	1.2	0.05 to 1.2	1.2 to 12	0.12 to 1.2	1.2 to 12	0.12 to 1.2	1.2 to 12
Full scale	3	0.3 to 3	3 to 30	0.3 to 3	3 to 30	0.3 to 3	3 to 30
setting	12	1.2 to 12	12 to 120	1.2 to 12	12 to 120	1.2 to 12	12 to 120
	30	3 to 30	30 to 300	3 to 30	30 to 300	3 to 30	30 to 300

Timing Chart

A: ON-delay	Power (2-10)	D: Signal OFF-delay	Power (2-10)
B: Flicker OFF start	Power (2-10) Start (2-6) Reset (2-7) Output relay (NC) (1-4, 8-11) Output relay (NC) (1-3, 9-11) Power indicator	E: Interval	Power (2-10) Start (2-6) Reset (2-7) Output relay (NC) (1-4, 8-11) Output relay (NC) Power indicator
B2: Flicker ON start	Power (2-10) Start (2-6) Reset (2-7) Output relay (NC) (1-4, 8-11) Output relay (ND) (1-3, 9-11) Power indicator	G: Signal ON/OFF-delay	Power (2-10) Start (2-6) Reset (2-7) Output relay (NO) (1-4, 8-11) Output relay (NO) (1-3, 9-11) Power indicator
C: Signal ON/OFF-delay	Power (2-10) Start (2-6) Reset (2-7) Output relay (NC) (1-4, 8-1) Output relay (NC) (1-3, 9-11) Power indicator	J: One-shot	Power (2-10) 1-3 1-3 Start (2-6) 1-3 1-3 Reset (2-7) 1-4 1-4 Output relay (NC) 1-20.6 s 1-20.6 s (1-4, 8-11) 1-20.6 s 1-20.6 s Power indicator 1-20.6 s 1-20.6 s

Accessories

On-panel Mounting Adaptor DIN rail Mount Socket On-panel Mount Socket Water Proof Hard protect Cover (IP66) Cover P2CF-08-E/P2CF-11-E P3G-08/P3GA-11 Y92F-30 Y92A-48B Y92A-48N **OMRON Corporation Industrial Automation Company** Authorized Distributor: Kyoto, JAPAN Contact: www.ia.omron.com **Regional Headquarters** OMRON EUROPE B.V. OMRON ELECTRONICS LLC 2895 Greenspoint Parkway, Suite 200 Hoffman Estates, IL 60169 U.S.A. Tel: (1) 847-843-7900/Fax: (1) 847-843-7787 Wegalaan 67-69, 2132 JD Hoofddorp The Netherlands Tel: (31)2356-81-300/Fax: (31)2356-81-388

OMRON ASIA PACIFIC PTE. LTD. No. 438A Alexandra Road # 05-05/08 (Lobby 2), Alexandra Technopark, Singapore 119967 Tel: (65) 6835-3011/Fax: (65) 6835-2711

OMRON (CHINA) CO., LTD. Room 2211, Bank of China Tower, 200 Yin Cheng Zhong Road, PuDong New Area, Shanghai, 200120, China Tel: (86) 21-5037-2222/Fax: (86) 21-5037-2200

© OMRON Corporation 2018 All Rights Reserved. In the interest of product improvement, specifications are subject to change without notice.

Note: Refer to the official Datasheet, how to use Gate input

Cat. No. L131-E1-02

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Timers category:

Click to view products by Omron manufacturer:

Other Similar products are found below :

 79237785
 H5AN-4DM DC12-24
 H5CN-YAN AC100-240
 H5CX-L8S-N AC100-240
 H5AN-4D DC12-24
 THR2U-110A
 81506944

 88225029
 H5S-YB4-X
 H7AN-2D DC12-24
 H5CN-XANS DC12-48
 H7AN-W4DM DC12-24
 H7AN-4DM DC12-24
 H7AN-4D DC12-24

 H7AN-RT6M AC100-240
 600DT-CU
 7PV1513-1AP30
 7PV1538-1AW30
 1SVR508100R0000
 1SVR550127R4100
 1SVR550212R4100

 1SVR730010R3200
 1SVR730020R3300
 1SVR730120R3100
 1SVR730180R3100
 1SVR730211R2300
 PCU-5111UNI
 H3C-R
 H3CR-A8-301

 24-48AC/12-48DC
 H3CR-A8E 24-48AC/DC
 H3CR-F8
 100-240AC/100-125DC
 H3CR-FN
 100-240AC/100-125DC
 H3DK-G
 24-230AC/DC

 H3DK-HBL AC/DC24-48
 H3DK-M1A DC12
 LT4H-AC24V
 LT4HW8-AC240V
 LT4HW-AC24VS
 31L48AP

 31L48TPM240
 RC302
 RC312
 REV-201M
 RG
 AT78051
 ATC180041
 TMM1
 TMP