

# Type FSH

## Fast Acting Glass Tube Fuse

### Automotive Glass



www.optifuse.com (619) 593-5050

**Fuse Size:** 1/4" x 5/8" (6.35 x 15.9mm)

**Ampere Rating:** 100mA ~ 30A

**Voltage Rating:** 125V / 250V / 32V

**Electrical Characteristics:**




100%	135%	200%
Min.	Max.	Max.
4h	1h	120s

**Agency Standards and Listings:**



According to UL248-14

**Mechanical Dimensions: Inches[mm]**



Part Number	Ampere Rating	Interrupt Rating	Voltage Rating	UL US	CUL US	PS E JET		
FSH-100mA	100mA	10KA @125VAC 35A @250VAC	125V/250V	•				
FSH-125mA	125mA			•				
FSH-250mA	250mA			•				
FSH-375mA	375mA			•				
FSH-500mA	500mA			•				
FSH-600mA	600mA			•				
FSH-750mA	750mA			•				
FSH-1A	1A	10KA @125VAC 100A @250VAC	125V/250V	•		•		
FSH-1.25A	1.25A			•		•		
FSH-1.5A	1.5A			•		•		
FSH-1.6A	1.6A			•		•		
FSH-2A	2A			•		•		
FSH-2.5A	2.5A			•		•		
FSH-3A	3A			•		•		
FSH-3.15A	3.15A	2020A @125VAC 1000A @32VAC	125V/32V	•		•		
FSH-3.5A	3.5A			•		•		
FSH-4A	4A			•		•		
FSH-5A	5A			•		•		
FSH-6A	6A			•				
FSH-6.3A	6.3A			•				
FSH-7A	7A			1000A @32VAC	125V/32V	•		
FSH-7.5A	7.5A	•						
FSH-8A	8A	•						
FSH-10A	10A	•						
FSH-12A	12A	100A @125VAC 1000A @32VAC	125V/32V			•		•
FSH-13A	13A					•		•
FSH-15A	15A					•		•
FSH-16A	16A			•				
FSH-20A	20A			•				
FSH-25A	25A			•				
FSH-30A	30A			•				

	<p><b>Warning:</b> -Operation beyond the specified maximum ratings or improper use may result in damage and possible electrical arcing and/or flame.</p>
	<p>-Avoid contact of Fuse device with chemical solvent. Prolonged contact may damage the device performance.</p>

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Optifuse manufacturer](#):*

Other Similar products are found below :

[FSC-3.5A](#) [TPK-10A](#) [TSA-250MA](#) [BLR-304](#) [BLR-504](#) [BLC-05-GTA](#) [BLR-I-504](#) [BLM-304](#) [CBW57-EL4-10A](#) [FPK-10A](#) [FPK-1A](#) [FPK-30A](#) [LPM-08](#) [LPX-23B-08R-LOOP](#) [FPK-12A](#) [FPK-15A](#) [FPK-20A](#) [FPK-25A](#) [FPK-2A](#) [FPK-3A](#) [FPK-4A](#) [FPK-5A](#) [FPK-6A](#) [FPK-7A](#) [FPK-8A](#) [FPK-R-1.5A](#) [FPK-R-10A](#) [FPK-R-15A](#) [FPK-R-1A](#) [FPK-R-20A](#) [FPK-R-25A](#) [FPK-R-2A](#) [FPK-R-30A](#) [FPK-R-3A](#) [FPK-R-4A](#) [FPK-R-5A](#) [FPK-R-6A](#) [FPK-R-8A](#) [LPM-01B-12R](#) [ACB-12-V-50A](#) [LPR-13C-10R](#) [ACBP4-PM-5A](#) [BLR-306](#) [ACB-12-V-30A](#) [CBW57-EL4-5A](#) [CBW57-ES-5A](#) [CBW57-PB-10A-5X](#) [CBW57-PS-10A-5X](#) [CBW57-PS-3A-1X](#) [CBW28-1A](#)