

XDM2041 Digital Multimeter



- + 3.7 inch (480x320) high resolution LCD
- + 55,000 counts
- + Up to 65 readings per second
- + True RMS AC voltage / current measurement
- + Dual line display supported
- + Trend analysis accessible in chart mode
- + SCPI support

+ Performance Specifications

	Measurement Range	Resolution	Accuracy \pm (% of reading + % of range)
DC Voltage	50.000mV	0.001mV	0.1%+10
	500.00mV	0.01mV	0.025%+5
	5.0000V	0.0001V	0.025%+5
	50.000V	0.001V	0.03%+5
	500.00V	0.01V	0.1%+5
	1000.0V	0.1V	0.1%+5
AC Voltage	500mv-750v	20Hz~45Hz	1% + 30
		45Hz~65Hz	0.5% + 30
		65Hz~1KHz	0.7% + 30
DC Current	500uA	0.01uA	0.15%+20
	5000uA	0.1uA	0.15%+10
	50mA	0.001mA	0.15%+20
	500mA	0.01mA	0.15%+10
	5A	0.0001A	0.5%+10
	10A	0.001A	0.5%+10
AC Current	500uA-500mA	/	0.5%+20
	5A-10A		1.5%+20
Resistance	500 Ω	0.01 Ω	0.1%+10
	5K Ω	0.0001K Ω	0.1%+5
	50K Ω	0.001K Ω	0.1%+5
	500K Ω	0.01K Ω	0.1%+5
	5M Ω	0.0001M Ω	0.25%+5
	50M Ω	0.001M Ω	0.1%+10
Four-wire resistance	500 Ω	0.01 Ω	0.1%+10
	5K Ω	0.0001K Ω	0.1%+5

	50K Ω	0.001K Ω	0.1%+5
	Measurement Range	Resolution	Accuracy \pm (% of reading + % of range)
Frequency	10.000Hz - 60MHz	/	\pm (0.2%+8)
Capacitance	50nF-500uF	/	2.5%+5
	5mF-50mF		5%+8
Diode	3.0000 V	0.0001V	/
Continuity	1000 Ω	0.1 Ω	/
Temperature	K type , PT100		
Display	55,000		

Data-logging Function

Logging Duration	15ms-9999s
Logging Length	1,000 points

General

Dimensions (W×H×D)	235 x 110 x 295 (mm)
Device Weight	Approximately 2.3kg

Specifications subject to change without prior notice

+ Accessories The accessories subject to final delivery


Power Cord




Manual



Spare Fuse



Multimeter Leads



Alligator Clips

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Digital Multimeters](#) category:

Click to view products by [OWON](#) manufacturer:

Other Similar products are found below :

[6111-517](#) [FS881](#) [40705X](#) [C.A 6133 LAUNCH KIT P 1020 A](#) [SEFRAM7303](#) [BS K-CLIP 19290](#) [DM285-FLEX-KIT](#) [IBT6K](#) [1000-219](#)
[1001-613](#) [1006-969](#) [1008-221](#) [1012-597](#) [1013-099](#) [30XR](#) [34XR](#) [35XP](#) [TESTO 745](#) [0590 7450](#) [TESTO 760-2](#) [0590 7602](#) [TESTO 760-3](#)
[0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-594](#) [AX-LCR42A](#) [AX-MS811](#) [AX-MS8250](#) [AX-](#)
[PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM525S](#) [BM805S](#) [BM807S](#) [BM817S](#) [BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#)
[BM867S](#) [BM907S](#) [33XR](#)