

- FIBER SENSORS
- LASER SENSORS
- PHOTOELECTRIC SENSORS
- MICRO PHOTOELECTRIC SENSORS
- AREA SENSORS
- SAFETY LIGHT CURTAINS / SAFETY COMPONENTS
- PRESSURE / FLOW SENSORS
- INDUCTIVE PROXIMITY SENSORS
- PARTICULAR USE SENSORS
- SENSOR OPTIONS
- SIMPLE WIRE- SAVING UNITS
- WIRE- SAVING SYSTEMS
- MEASUREMENT SENSORS
- STATIC CONTROL DEVICES
- LASER MARKERS
- PLC
- HUMAN MACHINE INTERFACES
- ENERGY MANAGEMENT SOLUTIONS
- FA COMPONENTS
- MACHINE VISION SYSTEMS
- UV CURING SYSTEMS
- Timers
- Time Switches
- Counters
- Hour Meters
- Options
- Limit Switches
- Temperature Controllers
- Solenoids
- Fan Motors
- Selection Guide
- LT4H series
- QM4H
- PM4S
- PM4H series
- S1DXM-A/M
- S1DX
- PMH

Related Information

- General terms and conditions..... F-3
- Selection guide P.1383~
- Options P.1425



panasonic.net/id/pidsx/global

Features

- Large dial for improved visibility and operability
- Four operation modes (Power ON-delay, Power flicker, Power one-shot, Power one-cycle)
- LED display for easy operation check
- Mounting frame available for easy panel installation

S1DX can be mounted on not only a DIN rail but also a panel with the mounting frame (optional).

S1DX timers that widely cover functions required as compact analog timers

PRODUCT TYPES

Plug-in terminal

Power ON-delay AC operating type

| | Time range | 100 to 120 V AC | 200 to 220 V AC |
|---------------------------|--------------------|---------------------|---------------------|
| | | Model No. | Model No. |
| Time-out 2 Form C type | 0.05 to 0.5 s | S1DX-A2C0.5S-AC120V | S1DX-A2C0.5S-AC220V |
| | 0.1 to 1 s | S1DX-A2C1S-AC120V | S1DX-A2C1S-AC220V |
| | 0.1 to 3 s | S1DX-A2C3S-AC120V | S1DX-A2C3S-AC220V |
| | 0.2 to 5 s | S1DX-A2C5S-AC120V | S1DX-A2C5S-AC220V |
| | 0.5 to 10 s | S1DX-A2C10S-AC120V | S1DX-A2C10S-AC220V |
| | 1 to 30 s | S1DX-A2C30S-AC120V | S1DX-A2C30S-AC220V |
| | 3 to 60 s | S1DX-A2C60S-AC120V | S1DX-A2C60S-AC220V |
| | 0.1 to 3 min | S1DX-A2C3M-AC120V | S1DX-A2C3M-AC220V |
| | 0.5 to 10 min | S1DX-A2C10M-AC120V | S1DX-A2C10M-AC220V |
| | 1 to 30 min | S1DX-A2C30M-AC120V | S1DX-A2C30M-AC220V |
| Time-out 4 Form C type | 3 to 60 min | S1DX-A2C60M-AC120V | S1DX-A2C60M-AC220V |
| | 0.1 to 3 hr | S1DX-A2C3H-AC120V | S1DX-A2C3H-AC220V |
| | 0.05 to 0.5 s | S1DX-A4C0.5S-AC120V | S1DX-A4C0.5S-AC220V |
| | 0.1 to 1 s | S1DX-A4C1S-AC120V | S1DX-A4C1S-AC220V |
| | 0.1 to 3 s | S1DX-A4C3S-AC120V | S1DX-A4C3S-AC220V |
| | 0.2 to 5 s | S1DX-A4C5S-AC120V | S1DX-A4C5S-AC220V |
| | 0.5 to 10 s | S1DX-A4C10S-AC120V | S1DX-A4C10S-AC220V |
| | 1 to 30 s | S1DX-A4C30S-AC120V | S1DX-A4C30S-AC220V |
| | 3 to 60 s | S1DX-A4C60S-AC120V | S1DX-A4C60S-AC220V |
| | 0.1 to 3 min | S1DX-A4C3M-AC120V | S1DX-A4C3M-AC220V |
| 0.5 to 10 min | S1DX-A4C10M-AC120V | S1DX-A4C10M-AC220V | |
| 1 to 30 min | S1DX-A4C30M-AC120V | S1DX-A4C30M-AC220V | |
| 3 to 60 min | S1DX-A4C60M-AC120V | S1DX-A4C60M-AC220V | |
| 0.1 to 3 hr | S1DX-A4C3H-AC120V | S1DX-A4C3H-AC220V | |

Notes: 1) Socket line holding clips for HC relay terminal socket (ADX18005) are included.
 2) You cannot use socket line holding clip when using the HJ relay terminal socket. Therefore, please procure a S1DX socket leaf holding clip B (ADX18012: dedicated socket leaf holding clip for HJ relay terminal socket).

PRODUCT TYPES

Plug-in terminal

Power ON-delay DC operating type

| | Time range | 12 V DC | 24 V DC | 48 V DC | 100 to 110 V DC |
|------------------------|------------------|--------------------|--------------------|--------------------|---------------------|
| | | Model No. | Model No. | Model No. | Model No. |
| Time-out 2 Form C type | 0.05 to 0.5 s | S1DX-A2C0.5S-DC12V | S1DX-A2C0.5S-DC24V | S1DX-A2C0.5S-DC48V | S1DX-A2C0.5S-DC110V |
| | 0.1 to 1 s | S1DX-A2C1S-DC12V | S1DX-A2C1S-DC24V | S1DX-A2C1S-DC48V | S1DX-A2C1S-DC110V |
| | 0.1 to 3 s | S1DX-A2C3S-DC12V | S1DX-A2C3S-DC24V | S1DX-A2C3S-DC48V | S1DX-A2C3S-DC110V |
| | 0.2 to 5 s | S1DX-A2C5S-DC12V | S1DX-A2C5S-DC24V | S1DX-A2C5S-DC48V | S1DX-A2C5S-DC110V |
| | 0.5 to 10 s | S1DX-A2C10S-DC12V | S1DX-A2C10S-DC24V | S1DX-A2C10S-DC48V | S1DX-A2C10S-DC110V |
| | 1 to 30 s | S1DX-A2C30S-DC12V | S1DX-A2C30S-DC24V | S1DX-A2C30S-DC48V | S1DX-A2C30S-DC110V |
| | 3 to 60 s | S1DX-A2C60S-DC12V | S1DX-A2C60S-DC24V | S1DX-A2C60S-DC48V | S1DX-A2C60S-DC110V |
| | 0.1 to 3 min | S1DX-A2C3M-DC12V | S1DX-A2C3M-DC24V | S1DX-A2C3M-DC48V | S1DX-A2C3M-DC110V |
| | 0.5 to 10 min | S1DX-A2C10M-DC12V | S1DX-A2C10M-DC24V | S1DX-A2C10M-DC48V | S1DX-A2C10M-DC110V |
| | 1 to 30 min | S1DX-A2C30M-DC12V | S1DX-A2C30M-DC24V | S1DX-A2C30M-DC48V | S1DX-A2C30M-DC110V |
| | 3 to 60 min | S1DX-A2C60M-DC12V | S1DX-A2C60M-DC24V | S1DX-A2C60M-DC48V | S1DX-A2C60M-DC110V |
| 0.1 to 3 hr | S1DX-A2C3H-DC12V | S1DX-A2C3H-DC24V | S1DX-A2C3H-DC48V | S1DX-A2C3H-DC110V | |
| Time-out 4 Form C type | 0.05 to 0.5 s | S1DX-A4C0.5S-DC12V | S1DX-A4C0.5S-DC24V | S1DX-A4C0.5S-DC48V | S1DX-A4C0.5S-DC110V |
| | 0.1 to 1 s | S1DX-A4C1S-DC12V | S1DX-A4C1S-DC24V | S1DX-A4C1S-DC48V | S1DX-A4C1S-DC110V |
| | 0.1 to 3 s | S1DX-A4C3S-DC12V | S1DX-A4C3S-DC24V | S1DX-A4C3S-DC48V | S1DX-A4C3S-DC110V |
| | 0.2 to 5 s | S1DX-A4C5S-DC12V | S1DX-A4C5S-DC24V | S1DX-A4C5S-DC48V | S1DX-A4C5S-DC110V |
| | 0.5 to 10 s | S1DX-A4C10S-DC12V | S1DX-A4C10S-DC24V | S1DX-A4C10S-DC48V | S1DX-A4C10S-DC110V |
| | 1 to 30 s | S1DX-A4C30S-DC12V | S1DX-A4C30S-DC24V | S1DX-A4C30S-DC48V | S1DX-A4C30S-DC110V |
| | 3 to 60 s | S1DX-A4C60S-DC12V | S1DX-A4C60S-DC24V | S1DX-A4C60S-DC48V | S1DX-A4C60S-DC110V |
| | 0.1 to 3 min | S1DX-A4C3M-DC12V | S1DX-A4C3M-DC24V | S1DX-A4C3M-DC48V | S1DX-A4C3M-DC110V |
| | 0.5 to 10 min | S1DX-A4C10M-DC12V | S1DX-A4C10M-DC24V | S1DX-A4C10M-DC48V | S1DX-A4C10M-DC110V |
| | 1 to 30 min | S1DX-A4C30M-DC12V | S1DX-A4C30M-DC24V | S1DX-A4C30M-DC48V | S1DX-A4C30M-DC110V |
| | 3 to 60 min | S1DX-A4C60M-DC12V | S1DX-A4C60M-DC24V | S1DX-A4C60M-DC48V | S1DX-A4C60M-DC110V |
| 0.1 to 3 hr | S1DX-A4C3H-DC12V | S1DX-A4C3H-DC24V | S1DX-A4C3H-DC48V | S1DX-A4C3H-DC110V | |

- Notes: 1) Socket line holding clips for HC relay terminal socket (ADX18005) are included.
 2) You cannot use socket line holding clip when using the HJ relay terminal socket. Therefore, please procure a S1DX socket leaf holding clip B (ADX18012: dedicated socket leaf holding clip for HJ relay terminal socket).

Ordering information

Ex. S1DX- C 2C 5S — 120 V AC

| Operation mode | Control output arrangement | Time range (Note) | | Operating voltage (Note) |
|---|--|---|---|---|
| F: Power Flicker S: Power One-shot C: Power One-cycle | 2C: Timed-out 2 Form C 4C: Timed-out 4 Form C | 0.5S: 0.05 to 0.5 s 1S: 0.1 to 1 s 3S: 0.1 to 3 s 5S: 0.2 to 5 s 10S: 0.5 to 10 s 30S: 1 to 30 s | 60s: 3 to 60 s 3M: 0.1 to 3 min 10M: 0.5 to 10 min 30M: 1 to 30 min 60M: 3 to 60 min 3H: 0.1 to 3 hr | 24 V AC: 24 V AC 120 V AC: 100 to 120 V AC 220 V AC: 200 to 220 V AC 240 V AC: 220 to 240 V AC 12 V DC: 12 V DC 24 V DC: 24 V DC |

Note: For other time range types and operating voltage types, please consult us.

FIBER SENSORS

LASER SENSORS

PHOTO-ELECTRIC SENSORS

MICRO PHOTO-ELECTRIC SENSORS

AREA SENSORS

SAFETY LIGHT CURTAINS / SAFETY COMPONENTS

PRESSURE / FLOW SENSORS

INDUCTIVE PROXIMITY SENSORS

PARTICULAR USE SENSORS

SENSOR OPTIONS

SIMPLE WIRE-SAVING UNITS

WIRE-SAVING SYSTEMS

MEASUREMENT SENSORS

STATIC CONTROL DEVICES

LASER MARKERS

PLC

HUMAN MACHINE INTERFACES

ENERGY MANAGEMENT SOLUTIONS

FA COMPONENTS

MACHINE VISION SYSTEMS

UV CURING SYSTEMS

Timers

Time Switches

Counters

Hour Meters

Options

Limit Switches

Temperature Controllers

Solenoids

Fan Motors

Selection Guide

LT4H series

QM4H

PM4S

PM4H series

S1DXM-A/M

S1DX

PMH

PRODUCT TYPES

PC board terminal

Power ON-delay

| Time range | 100 to 120 V AC | 200 to 220 V AC | 24 V DC |
|------------------------|-----------------|-----------------------------|----------------------------|
| | Model No. | Model No. | Model No. |
| Time-out 2 Form C type | 0.05 to 0.5 s | S1DX-A2C0.5S-AC120VP | S1DX-A2C0.5S-DC24VP |
| | 0.1 to 1 s | S1DX-A2C1S-AC120VP | S1DX-A2C1S-DC24VP |
| | 0.1 to 3 s | S1DX-A2C3S-AC120VP | S1DX-A2C3S-DC24VP |
| | 0.2 to 5 s | S1DX-A2C5S-AC120VP | S1DX-A2C5S-DC24VP |
| | 0.5 to 10 s | S1DX-A2C10S-AC120VP | S1DX-A2C10S-DC24VP |
| | 1 to 30 s | S1DX-A2C30S-AC120VP | S1DX-A2C30S-DC24VP |
| | 3 to 60 s | S1DX-A2C60S-AC120VP | S1DX-A2C60S-DC24VP |
| Time-out 4 Form C type | 0.05 to 0.5 s | S1DX-A4C0.5S-AC120VP | S1DX-A4C0.5S-DC24VP |
| | 0.1 to 1 s | S1DX-A4C1S-AC120VP | S1DX-A4C1S-DC24VP |
| | 0.1 to 3 s | S1DX-A4C3S-AC120VP | S1DX-A4C3S-DC24VP |
| | 0.2 to 5 s | S1DX-A4C5S-AC120VP | S1DX-A4C5S-DC24VP |
| | 0.5 to 10 s | S1DX-A4C10S-AC120VP | S1DX-A4C10S-DC24VP |
| | 1 to 30 s | S1DX-A4C30S-AC120VP | S1DX-A4C30S-DC24VP |
| | 3 to 60 s | S1DX-A4C60S-AC120VP | S1DX-A4C60S-DC24VP |

SCALE INTERVALS

| Time type | Scale intervals |
|-----------|--------------------------------------|
| 0.5 | 0.05 (0.02 in a range of 0.1 to 0.5) |
| 1 | 0.05 |
| 3 | 0.1 |
| 5 | 0.2 |
| 10 | 0.5 |
| 30 | 1 |
| 60 | 2 |

FIBER SENSORS

LASER SENSORS

PHOTO-ELECTRIC SENSORS

MICRO PHOTO-ELECTRIC SENSORS

AREA SENSORS

SAFETY LIGHT CURTAINS / SAFETY COMPONENTS

PRESSURE / FLOW SENSORS

INDUCTIVE PROXIMITY SENSORS

PARTICULAR USE SENSORS

SENSOR OPTIONS

SIMPLE WIRE-SAVING UNITS

WIRE-SAVING SYSTEMS

MEASURE-MENT SENSORS

STATIC CONTROL DEVICES

LASER MARKERS

PLC

HUMAN MACHINE INTERFACES

ENERGY MANAGEMENT SOLUTIONS

FA COMPONENTS

MACHINE VISION SYSTEMS

UV CURING SYSTEMS

Timers

Time Switches

Counters

Hour Meters

Options

Limit Switches

Temperature Controllers

Solenoids

Fan Motors

Selection Guide

LT4H series

QM4H

PM4S

PM4H series

S1DXM-A/M

S1DX

PMH

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Panasonic](#) manufacturer:

Other Similar products are found below :

[ECE-A1HKAR47](#) [ELK-EA102FA](#) [ELC-09D151F](#) [EEC-S0HD224H](#) [ELL-5PS3R3N](#) [HC2-H-DC48V-F](#) [HL2-HP-AC120V-F](#) [HL2-HP-DC12V-F](#) [HL2-HP-DC6V-F](#) [HL2-HP-DC24V-F](#) [HC4-H-DC24V](#) [HL2-HTM-DC24V-F](#) [HL2-HTM-AC24V-F](#) [HC3-HL-AC120V-F](#) [HC4-H-AC120V](#) [AMV9003](#) [EEC-RG0V155H](#) [AZH2031](#) [RP-SDMF64DA1](#) [RP-SDMF32DA1](#) [EEF-UD0K101R](#) [RP-SMLE08DA1](#) [EVM-F6SA00B55](#) [ELC-12D101E](#) [ERA-3YEB272V](#) [EEC-RF0V684](#) [ERA-3YEB153V](#) [ELC-3FN2R2N](#) [ERA-3YEB512V](#) [ERJ-1GEJ564C](#) [ERZ-V20R391](#) [ELL-6RH221M](#) [ETQ-P3W3R3WFN](#) [ELL-ATV681M](#) [ELL-VGG4R7N](#) [EEF-UD0J101R](#) [ECQ-U2A474ML](#) [LC-R121R3P](#) [ELK-EA100FA](#) [EVP-AKB11A](#) [ECQ-U2A154ML](#) [ELK-E101FA](#) [ERA-3YEB303V](#) [ERA-V15J100V](#) [ERZ-V05V680CB](#) [EEF-UE0K101R](#) [EEC-S0HD224V](#) [EVQ-PAC05R](#) [EVQ-PAG04M](#) [ELK-EA222FA](#)