

## Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)




Electromechanical reversing load motor starter for INTERBUS; fiber optic technology with 2 Mbaud, inputs (24 V DC), integrated motor protection relay (220 V AC to 480 V AC; 8 A, maximum), sensor connection via 5-pos. M12 female connectors, rugged metal housing, IP67 protection

### Your advantages

- Rugged metal housing
- Emergency operation on the device or via external operating elements
- Comprehensive diagnostic functions including motor current monitoring
- Rugged Line connector for INTERBUS with fiber optic and supply voltage
- COMBICON connector for motor output
- M12 connector for digital inputs

### Key Commercial Data

Packing unit	1 pc
GTIN	 4 017918 974190
GTIN	4017918974190

### Technical data

#### Note

Utilization restriction	EMC: class A product, see manufacturer's declaration in the download area
-------------------------	---

#### Dimensions

Width	185.1 mm
Height	193 mm
Depth	138 mm

#### Ambient conditions

Ambient temperature (operation)	0 °C ... 55 °C
Ambient temperature (storage/transport)	-25 °C ... 70 °C
Permissible humidity (operation)	100 %

# Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

## Technical data

### Ambient conditions

Permissible humidity (storage/transport)	95 % (non-condensing)
Air pressure (operation)	860 hPa ... 1080 hPa (up to 1500 m above sea level)
Air pressure (storage/transport)	660 hPa ... 1080 hPa (up to 3500 m above sea level)
Degree of protection	IP65/IP67

### Interfaces

Designation	INTERBUS
Connection method	Fiber optics
Transmission speed	2 Mbps

### Power supply for module electronics

Supply voltage	24 V DC
Supply voltage range	18.5 V DC ... 32 V DC (including ripple)
Ripple	3.6 V <sub>pp</sub>

### Mains connection

Designation	Mains connection
Connection method	POWER-COMBICON with silver contacts
Designation connection point	Terminal strip X11 and X12
Number of positions	4
Permissible conductor cross section	2.5 mm <sup>2</sup> ... 4 mm <sup>2</sup>
Operating voltage	230 V AC ... 480 V AC ±10 % (conductor voltage)
Max. current carrying capacity	20 A

### Motor starter, output

Connection method	POWER-COMBICON
Number	1
Designation connection point	X10
Number of positions	8
Pg screw connection	Pg16
Operating voltage	230 V AC ... 480 V AC
Frequency range	50 Hz ... 60 kHz
Nominal current range	0.2 A ... 8 A (parameterizable, observe derating)
Utilization category	on the basis of AC 3
Switching rate	max. 5 cycles per minute
Motor startup time	1 s

### Motor monitoring

Parameterization	Via INTERBUS
Overspeed tripping	≥ 40 A (after 1 second at I <sub>nom</sub> > 3.6 A)

### Motor starter, brake

Continuous load current	max. 1 A
Type of contact	Mechanical relay contact

# Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

## Technical data

### Motor starter, brake

Connection technology	POWER-COMBICON terminal strips
Connection voltage	12 V AC/DC ... 480 V AC/DC

### Digital inputs

Input name	Digital inputs
Number of inputs	6
Connection method	M12 connector
Connection technology	3, 4-wire
Number of positions	5
Input voltage	24 V DC (DIN EN 61131-2)
Input voltage range "0" signal	0 V ... 5 V
Input voltage range "1" signal	11 V ... 30 V
Typical input current per channel	5 mA (for $U_{S1} = 24 V$ )
Filter time	3 ms
Power supply for sensors	$U_{NI} = U_{S1}$ minus 1 V 50 mA Protected against inductive reverse voltages, electronically protected against short-circuiting

### Digital outputs

Number of outputs	1
Connection method	M12 connector
Number of positions	5
Output current	0.5 A
Minimum output voltage with nominal current	$U_{S1}$ minus 2 V
Type of protection	Electronic short-circuit/overload protection

### General

Mounting type	Wall mounting
Net weight	3800 g
Diagnostics messages	Mains failure, phase failure, blown fuse Error message in diagnostic code (bus) and display by means of the E LED on the motor starter
	Motor connector not plugged in, motor temperature exceeded, thermistor line short-circuited Error message in diagnostic code (bus) and display by means of the E LED on the motor starter
	Sensor supply failure Error message in diagnostic code (bus) and display by means of the E LED on the motor starter
	Failure of the actuator supply Error message in diagnostic code (bus) and display by means of the E LED on the motor starter
	Motor overcurrent Error message in diagnostic code (bus) and display by means of the E LED on the motor starter
	Output stage cannot be controlled Error message in diagnostic code (bus) and display by means of the E LED on the motor starter
	Module error during self test Message to the master
Mounting type	on mounting plate

### Standards and Regulations

# Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

## Technical data

### Standards and Regulations

Air clearances and creepage distances	according to EN 50178: 1998
Protection class	I (MЭК 61140, EN 61140, VDE 0140-1)

### Environmental Product Compliance

REACH SVHC	Lead 7439-92-1
China RoHS	Environmentally friendly use period: unlimited = EFUP-e
	No hazardous substances above threshold values

## Classifications

### eCl@ss

eCl@ss 10.0.1	27242609
eCl@ss 4.0	27250300
eCl@ss 4.1	27250300
eCl@ss 5.0	27250300
eCl@ss 5.1	27242600
eCl@ss 6.0	27242600
eCl@ss 7.0	27242609
eCl@ss 8.0	27242609
eCl@ss 9.0	27242609

### ETIM

ETIM 2.0	EC001433
ETIM 3.0	EC001605
ETIM 4.0	EC001605
ETIM 5.0	EC001605
ETIM 6.0	EC001605
ETIM 7.0	EC001605

### UNSPSC

UNSPSC 6.01	43172015
UNSPSC 7.0901	43201404
UNSPSC 11	43172015
UNSPSC 12.01	43201404
UNSPSC 13.2	32151602
UNSPSC 18.0	32151602
UNSPSC 19.0	32151602
UNSPSC 20.0	32151602
UNSPSC 21.0	32151602

## Approvals

### Approvals

# Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

## Approvals

### Approvals

UL Listed / cUL Listed / VDE Zeichengenehmigung / INTERBUS CLUB / cULus Listed

### Ex Approvals

### Approval details

UL Listed		<a href="http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm">http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm</a>	FILE E 228652
Nominal voltage UN	24 V		
mm²/AWG/kcmil	30-10		

cUL Listed		<a href="http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm">http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm</a>	FILE E 228652
Nominal voltage UN	24 V		
mm²/AWG/kcmil	30-10		

VDE Zeichengenehmigung		<a href="http://www2.vde.com/de/Institut/Online-Service/VDE-gepruefteProdukte/Seiten/Online-Suche.aspx">http://www2.vde.com/de/Institut/Online-Service/VDE-gepruefteProdukte/Seiten/Online-Suche.aspx</a>	40015947
------------------------	--	---	----------

INTERBUS CLUB	449/29.07.05
---------------	--------------

cULus Listed	
--------------	--

## Accessories

Accessories

Assembly element

## Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

### Accessories

Lower mounting part - IBS RL AP - 2731128



Mounting plate for Ruggedline devices

---

### Bridge

Cable set - IBS RL CONNECTION-LK - 2733029



Assembled cable jumper as a short connection between two INTERBUS Rugged Line devices with fiber optic bus connectors and power supply, approximately 30 cm

---

### Cable by the meter

Cable - IBS PWR/5HD/F - 2731775



Power supply cable, gray, welding-splash-resistant in standard applications, 5 x 1.5 mm<sup>2</sup>, highly flexible, sold by the meter

---

Cable - IBS PWR/5 - 2820000



Power supply cable, gray, welding-splash-resistant in standard applications, 5 x 1.5 mm<sup>2</sup>, sold by the meter

---

### Connector set

Connector set - IBS RL MLR PLSET R-8A - 2740504



Accessory set comprising: connectors and Pg screw connections

---

### Data cable by the meter

## Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

### Accessories

FO cable - PSM-LWL-RUGGED-980/1000 - 2744322



Polymer fiber cable, duplex 980µm/1000µm, heavy-weight version for installation in stationary systems and machines, by the meter without male connector

FO cable - PSM-LWL-RUGGED-FLEX-980/1000 - 2744335



Polymer fiber cable, duplex 980/1000 µm, heavy-weight, highly flexible version for flexible conduit applications, by the meter, without connector

FO cable - PSM-LWL-KDHEAVY-980/1000 - 2744319



Polymer fiber cable, duplex 980 µm/1000 µm, medium-weight version for installation in stationary systems and machines, by the meter without male connector

### Labeling panel

Marking label - IBS RL MARKER-SET - 2732729



Set of 50 small and 50 large metal marking labels

### Operator interface

Operator panel - IBS HVO/M12 - 2837006



Handheld operator panel, for INTERBUS motor starters and INTERBUS variable frequency drives in IP54 protection

### Plug

## Motor starter - IBS RL 480 MLR R DIO6/1-LK2MBD - 2734497

### Accessories

Adapter set - IBS RL 24 ADAP-LK/T - 2725040



INTERBUS Rugged Line adapter for converting the fiber optic remote bus to a copper wire remote bus

---

Adapter set - IBS RL 24 ADAP-T/LK - 2725037



INTERBUS Rugged Line adapter for converting the copper wire remote bus to a fiber optic remote bus

---

Bus connector - IBS RL PLUG-LK/POF - 2731076



Connector for the fiber optic bus with polymer fiber cable and for the power supply with QUICKON connection method

---

User manual - IBS RL SYS PRO UM - 2743705



User manual, German, for configuring and installing the Rugged Line product range, only available as a download.

---

---

Phoenix Contact 2020 © - all rights reserved  
<http://www.phoenixcontact.com>

PHOENIX CONTACT GmbH & Co. KG  
Flachmarktstr. 8  
32825 Blomberg  
Germany  
Tel. +49 5235 300  
Fax +49 5235 3 41200  
<http://www.phoenixcontact.com>



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [I/O Modules](#) category:*

*Click to view products by [Phoenix Contact](#) manufacturer:*

Other Similar products are found below :

[70L-IDC5S](#) [70L-OAC-L](#) [70Z3289-4](#) [G21960000700](#) [G21960002700](#) [G34960002700](#) [G88104401](#) [OACU](#) [C4SWOUT](#) [PB16H](#)  
[G34960001700](#) [G3TA-OA101SZ-1](#) [DC24](#) [G77-S](#) [G78-16-E](#) [5607189](#) [DA5](#) [ODC-24A](#) [IDC5P](#) [FC6A-N16B1](#) [6421](#) [70MRCQ32-HL](#)  
[G3TAOD201SDC24](#) [C200H-LK201-V1](#) [G3TA-OA202SZ-US](#) [DC12](#) [GT1-OD16](#) [GT1-AD04CST](#) [B7AM-6BS](#) [70GRCQ24-HS](#) [6422](#)  
[84110410](#) [GT1-OD16MX](#) [G7VC-OC16-B7](#) [70MRCK24-DIN](#) [6202](#) [6402](#) [PI/NI-2D/24](#) [FC6A-J2C1](#) [FC6A-KC1C](#) [FC6A-R081](#) [FC6A-](#)  
[J8CU1](#) [GP32900003700](#) [641-480-5022](#) [PB16H](#) [84145010](#) [84110210](#) [FRUSB1601](#) [PCL-720+-BE](#) [FRRJ451601](#) [AP24MX3DB25F](#) [ADAM-](#)  
[5053S-AE](#)