


**Model 4233 with Assembly Instructions  
Do-It-Yourself Micrograbber® & Test Clip Kits**



**Features**

- Ideal for connecting to small circuit board components
- Use with Model #'s 6383, 5173, 3690, 122505A or any other Pomona "Do-It-Yourself" product to create custom cables
- Supports 20 to 22 AWG wire

**Materials**

Contact: Beryllium Copper, Alloy 165 per QQ-C-533, ¼ HM  
 Spring: Stainless Steel, 302  
 Finish: Contact – Gold plated per MIL-G-45204, Type 1, Class 00  
 Insulation: Glass filled Nylon  
 Markings: "POMONA", "GRABBER®", "4233"

**Ratings**

Operating Temperature: +102°C (+216°F) Max  
 Voltage: Maximum voltage for *hands free use*: 150 Vrms Max.  
 For CE compliance, do not hold in hand when voltages exceed 30 Vrms / 60 Vdc  
 Current: 3 Amperes

**Ordering Information**

Model: 4233-  
 \* = Color, -0 Black, -2 Red, -5 Green, -9 White  
 Ordering Example: 4233-0, test clip color is Black.




**USA:** Sales: 800-490-2361  
 Technical Support: [technicalsupport@pomonatest.com](mailto:technicalsupport@pomonatest.com)  
 Fax: 425-446-5844  
**Europe:** 31-(0) 40 2675 150 **International:** 425-446-5500  
**Where to Buy:** [www.pomonaelectronics.com](http://www.pomonaelectronics.com)


All dimensions are in inches. Tolerances (except noted): .xx = ±.02" (.51 mm), .xxx = ±.005" (.127 mm). All specifications are to the latest revisions. Specifications are subject to change without notice. Registered trademarks are the property of their respective companies.

**Model 4233 with Assembly Instructions  
Do-It-Yourself Micrograbber® & Test Clip Kits****FIGURE #1**


- A. Remove the cap from housing assembly, the contact will now be exposed.
- B. Insert the wire into the cap assembly allowing approximately 1 to 2 inches of wire to extend beyond the cap.
- C. Strip wire 1/8 to 3/16 inches.
- D. Insert exposed conductor through the hole in the contact and solder to surface.

**FIGURE #2**

- E. Important: Solder must not extend beyond the indicated width.

**FIGURE #3**

- F. Install the cap onto the housing assembly. Align the contact with the slots located on the cap.



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Test Clips](#) category:*

*Click to view products by [Pomona](#) manufacturer:*

Other Similar products are found below :

[010000](#) [923743-16](#) [BU-656-0](#) [4140A](#) [4324A](#) [TL820](#) [TL822](#) [5116](#) [5450](#) [5216](#) [5252](#) [5454](#) [5694](#) [923700](#) [923698](#) [CR0060](#) [3038](#) [927739-20](#)  
[923743-14](#) [932146101](#) [930318100](#) [930126101](#) [Z-SB3FA3250AAAB04001](#) [Z-S11F0107G1000](#) [Z-S11F0207B1520](#) [Z-S11F0207B2030](#) [Z-](#)  
[S11F0207B15000](#) [Z-SB3FA3226AAAB11001](#) [Z-S11F0207B1010](#) [923706](#) [930317800](#) [973889100](#) [972405100](#) [972405101](#) [R999720600](#) [949-](#)  
[1](#) [458-3](#) [SK 201200278 020](#) [BU-65-B](#) [BU-21CPN-GZZZ](#) [PK-HVA-02](#) [BU-25C-DZZZ](#) [BU-142-2](#) [00425](#) [R8-1A RED](#) [R8-54 BLACK](#) [R8-](#)  
[54 RED](#) [MA1SW](#) [MA260SH SW](#) [AX-CR-02-SET](#)