

# COAXIAL ATTENUATORS

## SMA

### 2 WATTS

Part Number	Freq. range (GHz)	ATTENUATION (dB)					V.S.W.R.				Power (W)		Fig.
		Nom.	DEVIATION				DC - 4	4 - 8	8 - 12.4	12.4 - 15	avg.	peak	
			DC - 4	4 - 8	8 - 12.4	12.4-15							
R411800000	DC - 15	0	+0.2	+0.3	+0.5	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1	
R411801000		1	± 0.3	± 0.4	± 0.5	± 0.7	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411802000		2	± 0.3	± 0.4	± 0.5	± 0.7	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411803000		3	± 0.3	± 0.4	± 0.5	± 0.7	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411804000		4	± 0.3	± 0.4	± 0.5	± 0.7	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411805000		5	± 0.4	± 0.5	± 0.6	± 0.8	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411806000		6	± 0.4	± 0.5	± 0.6	± 0.8	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411807000		7	± 0.4	± 0.5	± 0.6	± 0.8	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411808000		8	± 0.4	± 0.5	± 0.6	± 0.8	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411809000		9	± 0.4	± 0.5	± 0.6	± 0.8	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411810000		10	± 0.4	± 0.5	± 0.6	± 0.8	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411811000		11	± 0.5	± 0.6	± 0.7	± 0.9	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411812000		12	± 0.5	± 0.6	± 0.7	± 0.9	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411813000		13	± 0.5	± 0.6	± 0.7	± 0.9	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411814000		14	± 0.5	± 0.6	± 0.7	± 0.9	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411815000		15	± 0.5	± 0.6	± 0.7	± 1.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411816000		16	± 0.5	± 0.6	± 0.7	± 1.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411817000		17	± 0.5	± 0.6	± 0.7	± 1.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411818000		18	± 0.5	± 0.6	± 0.7	± 1.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411819000		19	± 0.5	± 0.6	± 0.7	± 1.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411820000		20	± 0.5	± 0.6	± 0.7	± 1.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.35	2	100	1
R411821000		21	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411822000		22	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411823000		23	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411824000		24	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411825000		25	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411826000		26	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411827000		27	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411828000		28	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411829000		29	± 0.6	+0.7/-0.6	+1/-0.6	+1.4/-0.6	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411830000		30	± 0.6	± 0.7	+0.8/-1	+0.8/-2.0	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411840000		40	± 0.9	+0.9/-1.0	+0.8/-1.5	+0.6/-3.2	≤ 1.20	≤ 1.25	≤ 1.30	≤ 1.50	2	100	2
R411850000	DC-12.4	50	± 1.5	± 1.7	± 2.0		≤ 1.20	≤ 1.25	≤ 1.30	2	100	3	





Figure	A inch (mm)	B inch (mm)	Weight (g)
1	.75" (19)	.35" (9)	5
2	.95" (24)		7
3	1.14" (29)		10

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Attenuators - Interconnects](#) category:*

*Click to view products by [Radiall](#) manufacturer:*

Other Similar products are found below :

[R411803119](#) [R413806115](#) [R413808000](#) [R413810115](#) [R413850115](#) [R414510000](#) [R414701000](#) [BNC-13](#) [R411800121](#) [R411801121](#)  
[R412412124](#) [R412450000](#) [R413800000](#) [R413805000](#) [R413830000](#) [R413840115](#) [R414730000](#) [R415420000](#) [R415703000](#) [R416010000](#)  
[R420003110](#) [R411801000](#) [R411815121](#) [R413305000](#) [R413801000](#) [R414520000](#) [R411808121](#) [R412500124](#) [R412414124](#) [R412501124](#)  
[HMC-C584](#) [R413802000](#) [R412400124](#) [R411700124](#) [R417310130](#) [R411801119](#) [R412419124](#) [R411703124](#) [R412401124](#) [R443131000](#)  
[R417130110](#) [R414700000](#) [R414505000](#) [R411802119](#) [R417720128](#) [R420706110](#) [R413811000](#) [R413803115](#) [R414501000](#) [R417903128](#)